

CORRECTED

PARTS LIST — PLUS/4 PCB ASSEMBLY #310163-01

PLEASE NOTE: Commodore part numbers are provided for reference only and do not indicate the availability of parts from Commodore. Industry standard parts (Resistors, Capacitors, Connectors) should be secured locally. Approved cross-references for TTL chips, Transistors, etc. will be available in manual form through the Service Department in November of 1984. Unique or non-standard parts will be stocked by Commodore and are indicated on the parts list by a "C".

INTEGRATED CIRCUITS		DIODES (Continued)	
U1	7360 VLSI, Text Display (TED) Sub: C 251535-01 8360 C 251535-02	CR1 (cont.)	Bridge Rectifiers DBA20C Sanyo 251026-03
U2	7501 Custom Microprocessor C 251536-01	CR2	Diode, Zener RD 6.8 EB 900927-01
U3	6551A (Synertek) 901895-02	CR11-20	Diode, IN 914 Sub: 900850-16
U4	74LS08 901521-03		Diode, IN 4148 Taping 251819-21 Sub:
U5	6529B Single Port Interface C 251640-03		Diode, IN 4148 900850-01
U6	74LS04 901521-02	RESISTORS — All values are in ohms-1/4 W 5% unless noted otherwise.	
U7	7406 901522-06	R1	4.7K
U8	555 901523-01	R2	10K
U9-10	74LS257 901521-57	R3	470
U11-18	4164-2 D-RAM 901505-01	R4	220
U19	7700-010 PLA C 251641-02	R5	18K
U20	74LS139 901521-18	R6	1.5K
U21	74LS175 901521-34	R7	470
U22	74LS27 901521-22	R8	100K
U23	2312B ROM TED Basic C 318006-01	R9	1K
U24	23128 ROM TED Kernal C 318005-04	R10	1K
U25	23128 FUNCTION ROM, 3+1 LOW C 317053-01	R11	12K
U26	23128 FUNCTION ROM, 3+HIGH C 317054-01	R12	10K
U27	6529B Single Port Interface C 251640-03	R13	1K
TRANSISTORS		R14	240
Q1-Q3	2SC 1815 902693-01	R15	250 240
Q4	2SD 880 902694-01 Sub: Tip 29A 902653-01 Sub: 2SD 1266 902694-04	R16	100K
DIODES		R17	1.5K
CR1	Bridge Rectifiers S2VB10 Sindengen 215026-01 Sub: Bridge Rectifiers DBA20B Sanyo 251026-02 Sub:	R18	47K
		R19	100K
		R20	3K
		R21	1K
		R22	1K
		R23	1K
		R24	1K
		R25	1K
		R26	10 K
		R27	10 K
		RESISTOR PACK	
		RP1, 2	3.3K, 6 PIN 902441-29
		RP3, 4	68, 8 PIN 4 ISOLATED 326149-06
		CAPACITORS	
		C1	Elect 100 μ F 25V 900100-40
		C2	Ceramic 0.1 μ F 25V 251075-06
		C3	Film 0.22 μ F 100V 900150-11
		C4	Film 0.22 μ F 100V 900150-11
		C5-C6	Ceramic 0.22 μ F 50V 900022-01
		C7	Elect 2200 μ F 16V 900101-33
		C8	Elect 10 μ F 16V 900100-25
		C9	Ceramic 0.1 μ F 25V 251075-06
		C10	Trimmer 40 pF 251029-02
		C11	Ceramic 22 pF 50V 251070-14

PARTS LIST — PLUS/4
PCB ASSEMBLY # 310163-01 (Continued)

CAPACITORS (Continued)				MISCELLANEOUS (Continued)		
C12	Ceramic	220 pF 50V	Sub: 251071-26 Sub:	FB2-14	Ferrite bead	325563-01
	Ceramic	220 pF 50V	900463-08	FB15-21	Ferrite bead	903025-01
C13	Ceramic	150 pF 50V	251071-24	FB22-26, FB28-38, FB40	Ferrite bead	325563-01
	Ceramic	150 pF 50V	900462-41	FB41-58	Ferrite bead	903025-01
C14	Ceramic	0.01 μ F 25V	251075-01	FB59	Ferrite bead	325563-01
C15-C16	Ceramic	0.1 μ F 25V	251075-06	FB60	Ferrite bead	903025-01
C17-C18	Ceramic	10 μ F 16V	900100-25	FB61-63	Ferrite bead	325563-01
C19	Ceramic	0.01 μ F 25V	251075-01	FB64-65	Ferrite bead	903025-01
C20	Elect	10 μ F 16V	900100-25			
C21	Ceramic	0.1 μ F 25V	251075-06	EM1,2	EMI Filter	251842-01
C22	Elect	10 μ F 16V	900100-25			
C23	Elect	1 μ F 16V	900100-16	CN1	Connector 4 PIN (power supply)	C 251614-01
C24-C26	Ceramic	0.1 μ F 25V	251075-06	CN2	Connector 6 PIN DIN (serial bus)	C 903361-01
C27	Elect	10 μ F 16V	900100-25			
C28-C29	Ceramic	0.1 μ F 25V	251075-06	CN3	Connector 7 PIN MINI DIN (cassette)	C 251616-01
C30	Elect	10 μ F 16V	900100-25			
C31-C32	Ceramic	0.1 μ F 25V	251075-06	CN4	Connector 50 PIN Female Edge (exoab)	C 251630-01
C33-C40	Ceramic	0.22 μ F 25V	251075-07	CN5-6	Connector 8 PIN MINI DIN (joy 1 & 2)	C 251259-01
	Sub:			CN7	Connector 8 PIN DIN (audio/video)	325573-01
C41-C51	Ceramic	0.22 μ F 50V	900022-01			
	Ceramic	0.1 μ F 50V	900020-06	CN8	Connector 18 PIN (keyboard)	C 251841-01
	Sub:					
C100	Ceramic	0.1 μ F 50V	9000010-01			
	Ceramic	0.1 μ F 50V	900010-20			
MISCELLANEOUS				L1	Noise Filter	251264-01
Y1	Crystal	14.31818 MHZ	251081-01	L2	Line Filter	906127-01
	Sub:				Sub:	251701-01
	Crystal	14.31818 MHZ	251081-02		Sub:	
Y2	Crystal	1.8432 MHZ	900555-02	L3, L4	Coil Inductor 1.2 uHpt	901152-01
					Sub:	325570-01
SW1	Switch, Rocker (PC Mount)		C 251587-01			
SW2	Switch, Push Button		C 251260-01	F1	Fuse 250V 1.5A	903556-18
					Fuse Clip	906102-01
M1	RF Modulator		C 251844-01		Cartridge Guide	310171-01
	Sub:				Shield Box	C 310172-01
	RF Modulator		251311-01		Shield Cap	C 310173-01