ELECTRICITY BOARD CUT-OUT ETC.

L 10mm² — MINIATURE CIRCUIT BREAKER (MCB) — 10mm²
N 10mm² — 10mm²
E — 6mm²
EARTH LEAKAGE CIRCUIT BREAKERS (ELCB) 3/4, 5/6 — 6mm²
10mm²
SK1: L 6mm², N 6mm², E 6mm², 10mm², pins 6, 7, 8
CASE EARTH

TB3
1 LINK NORMAL
2 LINK TEST
3 LINK NORMAL
4 LINK TEST
5 LINK NORMAL
6 LINK TEST
7
8

CONTROLLER ON/OFF SWG
TB5 3
C16 0·47µF
MAINS FILTER L1
R, BK, BN, BL
CASE STUD
TB5 6
FS1 10A
FS3 3A
240V
T1 POWER SUPPLY
FOR DETAILS OF CONNECTIONS SEE DRG XA1/5236 SHT. 1

DIMMING & DETECTORS T2
240V
80V
120V
24V
0V
6 0V
5 ES
BUZZER PROVING RELAY
RL8
RL7/1
RL7/2
RL9/1
RL11/2
L2
RL4/2
R2 3·3K
LINK
R1 6·8K
RL9/3
C7 0·1µF
DIMMING RELAY (1) RL9
RL10/1
ADD LINK IF 120V DIMMING IS REQD

TRANSFORMER MTG BOARD ASSY
C15
RL1/1
C16
C10
RMGC/T1
RMGC/T2
VRS1
VRS2
R1 1·5K
C9 0·047µF
C17
T10
SCR1
RL1/2
RL2/1
RL2/2
C11
VAS
VGS
RMGC/TB1/2
RL3/1
C12
RL5/2
C13
RL4/1
RL3/2
RL5/1
C14
FRS
PCS
RMGC TB1/3

TB1/11 MV DETECTOR
B/AH DET 1 — TB3/1
B/AF DET 2 — TB3/2
B/AM FM — TB3/9
B/AJ — TB3/13 DET COMMON
PWS — TB1/7 WAIT
TB1/1 RED
TB1/2
VAS — TB1/3 AMBER
VGS — TB1/4 GREEN
RMGC/TB1/2
FRS — TB1/E
PCS — TB1/G
RMGC TB1/3
PHOTO — TB1/2
240V AC LINE — TB1/9 PHOTO CELL
240V AC NEUTRAL — TB1/10
RMGC/TB1/1
EARTH — TB1/12
RMGC/TB1/G
FS5 3A
FS4 3A
24VAC — TB3/15
40VAC — TB3/16
TB4/15
TB4/16
DETECTORS
TB2/16

TYPE 125C ONLY
SW7 WIPER
POS1 ENA 7/8 (4/8)
ENB 7/29 (4/39)
ENC 7/10 (4/10)
END 7/18 (4/18)
ENE 5/8
ENF 5/39
ENG 5/10
ENH 5/18
DIS 7/12 (4/12)
SK6
8/20 8/19

SW1 A B F E
SW2 B
SW3 B
SW4 C B
SW5 A B F
OV(5) 8/2 FVP 9/F VA 8/4 NTT PD 9/AM PED DEMAND VE 8/5 VEHICLE EXTENSION 1/AL OR G/AL RESET DFL 8/R DETECTOR FAULT LAMP TEST PEDMON 9/19 LAMPS ON 1 1/AB OR G/AB LOS 1/AK OR G/AK

CHASSIS EARTH
EP1
LP1 DETECTOR FAULT LAMP
1/36 OR G/36
LAMPS ON/OFF RELAY RL11/3
D11
D1 RL1/2 VRD2 9/AC VEH RED
D2 RL2/2 VAD2 9/22 VEH AMBER
D3 RL3/2 VGD2 9/AB VEH GREEN
D4 RL4/2 PRD2 9/AH PED RED
D7 RL7/2 DIMMING RELAY (2)
D5 RL5/2 PGD2 9/AF PED GREEN
D6 RL6/2 PWD2 9/24 PED WAIT INDICATOR
9/AS OV (24)
9/31 WAIT INDICATOR REPLY
RL9/2
RL6/2
1K5
4/1 OR 7/1 OR 4/1 & 5/1
4/14 OR 7/14 OR 4/14 & 5/14
9/30
+24V(1) 1/AE OR G/AE 1/31 OR G/31 +24V(3)
RL10 DIMMING OVERRIDE RELAY
D10
9/32 VGE1 TB2/1 VEH GREEN CONFIRM
9/35 VGE2 TB2/2
9/AL VPH TB2/3 VEH STAGE HOLD
9/AM 1·2K C8 1·0µF 0V (24) PD TB2/4
PD TB2/15
UNDER AREA TRAFFIC CONTROL
+24V(3) TB2/12
PUSH BUTTON
9/36 RLB/1 AA TB2/8
BUZZER
OV(24) TB2/5
OV(24) TB2/7
OV(24) TB2/6
TB3/4 LOOP
TB3/5 LOOP
TB3/6
TB3/7
9/23 TB2/13
9/AR TB2/14
WAIT IND CONFIRM
1/24 OR G/24 TRID
1/AE OR G/AE +24(1)

© GEC Traffic Automation Limited 1983
All rights reserved. Without our prior written consent this document may not in any manner or form whatsoever be reproduced, stored in a retrieval system or divulged to any third party and shall be used solely for adjudicating tenders, performing contracts or operating equipment.

COPYRIGHT © 1976
GEC TRAFFIC AUTOMATION LTD.
ELSTREE WAY, BOREHAMWOOD, HERTS
THIS DRAWING MAY NOT BE REPRODUCED IN WHOLE OR IN PART WITHOUT OUR WRITTEN PERMISSION.

APPROVED

MOD. No.	M.C.R. 3217	M.C.R. 3246	M.C.R. 3284	E.C.N. 3276	L.O.P. 3324	E.C.N. 3540
ISSUE	1	2	3	4	5	6
DATE	13/4/84	19/6/84	3/9/84	13/11/84	11/12/84	8/3/85

T125 CONTROLLER MAIN WIRING DIAGRAM

(PEDESTRIAN CROSSING LIGHTS — ROYAL "SEAFORTH" FREEPORT ENTRANCE)

ISSUE –
DATE

PL

XA1/5238/2

GEC TRAFFIC AUTOMATION LTD