

五倍卷購物活動(佔分 20 分)

問題描述：

為了配合五倍卷活動，A 店家正在舉辦購物多買多送活動。口罩每盒 x 元，每買一盒口罩送集點卡一點，累積 Y 點就可再換一盒口罩，換到一盒口罩後也可以得到一點，直到無法兌換為止。請你寫一個程式，計算總金額 Z 最多可以買到以加換到幾盒口罩？還剩下多少元沒有買？剩下多少點沒有兌換？

輸入說明：

輸入資料含多組測試案例。每組測試案例為三個正整數 X, Y, Z ，中間以空格區分，代表口罩每盒 X 元、累積 Y 點就可再換一盒口罩與總金額 Z 。若 X, Z 任一數字為 0 或負數，或者 Y 為 0, 1 或負數，則代表所有測試案例結束。

輸出說明：

每組測試案例輸出 3 個整數，第 1 個為總共買到以及加換到幾盒口罩，第 2 個為剩下多少元沒有買，第 3 個為剩下沒有兌換的點數，3 個數字之間空一個空格，每組測試案例輸出 1 行。

範例 1：

輸入：

100 10 5000

1 10 5000

4 10 5000

0 1 1

輸出：

55 0 5

5555 0 5

1388 0 8

範例 2：

輸入：

43 22 4888

53 11 1700

500 5 4444

-1 1 1

輸出：

118 29 8

35 4 2

9 444 4

Quintuple Voucher Shopping Event (20 points)

Problem Description:

To tie in with the Quintuple Voucher event, Store A is holding a "buy more, get more" promotion. Masks are X dollars per box. Each box of masks purchased earns one reward point. Accumulating Y points can be exchanged for another box of masks. Exchanging points for a box of masks also earns one point. This process continues until no more exchanges can be made. Please write a program to calculate the maximum number of mask boxes that can be obtained (purchased plus exchanged) with a total amount Z . How much money is left unspent? How many points are left unexchanged?

Input Specification:

The input data contains multiple test cases. Each test case consists of three positive integers X , Y , and Z , separated by spaces. They represent the price X per box of masks, the number of points Y required to exchange for another box, and the total amount of money Z , respectively. If either X or Z is 0 or a negative number, or if Y is 0, 1, or a negative number, it indicates the end of all test cases.

Output Specification:

For each test case, output 3 integers on a single line, separated by a single space. The 1st integer is the total number of mask boxes obtained (purchased plus exchanged), the 2nd integer is the remaining unspent money, and the 3rd integer is the remaining unexchanged points.

Example 1:

Input:

100 10 5000

1 10 5000

4 10 5000

0 1 1

Output:

55 0 5

5555 0 5

1388 0 8

Example 2:

Input:

43 22 4888

53 11 1700

500 5 4444

-1 1 1

Output:

118 29 8

35 4 2

9 444 4