

Team ID	PNT2022TMID06179
Project Name	Signs With Smart Connectivity for Better Road Safety

Simulation:

```

#include <WiFi.h>
#include <HTTPClient.h>
#include <Adafruit_GFX.h>
#include <Adafruit_ILI9341.h>
#include <string.h>

const char* ssid = "Wokwi-GUEST";
const char* password = "";

#define TFT_DC 2
#define TFT_CS 15
Adafruit_ILI9341 tft = Adafruit_ILI9341(TFT_CS, TFT_DC);

String myLocation = "Chennai,IN";
String usualSpeedLimit = "70"; // kmph

int schoolZone = 32;
int hospitalZone = 26;

int uid = 2504;

String getString(char x)
{
    String s(1, x);
    return s;
}

String stringSplitter1(String fullString,char delimiter='$')
{
    String returnString = "";
    for(int i = 0; i<fullString.length();i++) {
        char c = fullString[i];
        if(delimiter==c)
            break;
        returnString+=String(c);
    }
    return(returnString);
}

String stringSplitter2(String fullString,char delimiter='$')
{
    String returnString = "";
    bool flag = false;

```

```

    for(int i = 0; i<fullString.length();i++) {
        char c = fullString[i];
        if(flag)
            returnString+=String(c);
        if(delimiter==c)
            flag = true;
    }
    return(returnString);
}

void rightArrow()
{
    int refX = 50;
    int refY = tft.getCursorY() + 40;

    tft.fillRect(refX,refY,100,20,ILI9341_RED);
    tft.fillTriangle(refX+100,refY-
30,refX+100,refY+50,refX+40+100,refY+10,ILI9341_RED);
}

void leftArrow()
{
    int refX = 50;
    int refY = tft.getCursorY() + 40;

    tft.fillRect(refX+40,refY,100,20,ILI9341_RED);
    tft.fillTriangle(refX+40,refY-30,refX+40,refY+50,refX,refY+10,ILI9341_RED);
}

void upArrow()
{
    int refX = 125;
    int refY = tft.getCursorY() + 30;

    tft.fillTriangle(refX-40,refY+40,refX+40,refY+40,refX,refY,ILI9341_RED);
    tft.fillRect(refX-15,refY+40,30,20,ILI9341_RED);
}

String APICall() {
    HTTPClient http;

    String url = "https://node-red-nwmrt-2022-11-04.eu-
gb.mybluemix.net/getSpeed?";
    url += "location="+myLocation+"&";
    url += "schoolZone="+String(digitalRead(schoolZone))+String("&");
    url += "hospitalZone="+String(digitalRead(hospitalZone))+String("&");
    url += "usualSpeedLimit="+String(usualSpeedLimit)+String("&");
    url += "uid="+String(uid);
}

```

```

http.begin(url.c_str());
int httpResponseCode = http.GET();

if (httpResponseCode>0) {
    String payload = http.getString();
    http.end();
    return(payload);
}
else {
    Serial.print("Error code: ");
    Serial.println(httpResponseCode);
}
http.end();
}

void myPrint(String contents) {
    tft.fillScreen(ILI9341_BLACK);
    tft.setCursor(0, 20);
    tft.setTextSize(4);
    tft.setTextColor(ILI9341_RED);
    //tft.println(contents);

    tft.println(stringSplitter1(contents));
    String c2 = stringSplitter2(contents);
    if(c2=="s") // represents Straight
    {
        upArrow();
    }
    if(c2=="l") // represents left
    {
        leftArrow();
    }
    if(c2=="r") // represents right
    {
        rightArrow();
    }
}

void setup() {
    WiFi.begin(ssid, password, 6);

    tft.begin();
    tft.setRotation(1);

    tft.setTextColor(ILI9341_WHITE);
    tft.setTextSize(2);
    tft.print("Connecting to WiFi");
}

```

```
while (WiFi.status() != WL_CONNECTED) {  
    delay(100);  
    tft.print(".");  
}  
  
tft.print("\nOK! IP=");  
tft.println(WiFi.localIP());  
}  
  
void loop() {  
  
    myPrint(APICall());  
  
    delay(100);  
}
```

Link:

[Smart Connectivity Features.ino - Wokwi Arduino and ESP32 Simulator](#)



Simulation

00:36.998 19%

