

ASSIGNMENT-4

Connecting wokwi and IBM Cloud Service

Assignment Date	24 October 2022
Student Name	Mr. Akash V S
Student Roll Number	923819106004
Maximum Marks	2 Marks

Question1:

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100cms send "alert" to IBM cloud and display in device recent events.

CODE:

```
1  #include <WiFi.h> //library for wifi
2  #include <PubSubClient.h> //library for MQTT
3
4
5  void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);
6
7  //-----credentials of IBM Accounts-----
8
9  #define ORG "4hn0jp" //IBM ORGANITION ID
10 #define DEVICE_TYPE "ULTRASON" //Device type mentioned in ibm watson IOT Platform
11 #define DEVICE_ID "DISTANCEDTECT" //Device ID mentioned in ibm watson IOT Platform
12 #define TOKEN "wuo5s7PR)ZSegVk&Rx" //Token
13 String data3;
14 float dist;
15
16
17 //----- Customise the above values -----
18 char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name
19 char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform and format in which data to be send
20 char subscribetopic[] = "iot-2/cmd/test/fmt/String"; // cmd REPRESENT command type AND COMMAND IS TEST OF FORMAT STRING
21 char authMethod[] = "use-token-auth"; // authentication method
22 char token[] = TOKEN;
23 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID; //client id
24
25
26 //-----
27 WiFiClient wificlient; // creating the instance for wificlient
28 PubSubClient client(server, 1883, callback, wificlient); //calling the predefined client id by passing parameter like server id, port and wificredential
29
30 int LED = 4;
31 int trig = 5;
32 int echo = 18;
33 void setup()
34 {
35   Serial.begin(115200);
```

esp32-blink.ino • diagram.json • libraries.txt • Library Manager ▼

```
36 pinMode(trig,OUTPUT);
37 pinMode(echo,INPUT);
38 pinMode(LED, OUTPUT);
39 delay(10);
40 wificonnect();
41 mqttconnect();
42 }
43 void loop()// Recursive Function
44 {
45
46     digitalWrite(trig,LOW);
47     digitalWrite(trig,HIGH);
48     delayMicroseconds(10);
49     digitalWrite(trig,LOW);
50     float dur = pulseIn(echo,HIGH);
51     float dist = (dur * 0.0343)/2;
52     Serial.print ("Distancein cm");
53     Serial.println(dist);
54
55
56     PublishData(dist);
57     delay(1000);
58     if (!client.loop()) {
59         mqttconnect();
60     }
61 }
62
63
64
65 /*.....retrieving to Cloud.....*/
66
67 void PublishData(float dist) {
68     mqttconnect();//function call for connecting to ibm
69     /*
70     | creating the String in in form JSon to update the data to ibm cloud
```

```

69  |
70  | | creating the String in in form JSON to update the data to ibm cloud
71  */
72  String object;
73  if (dist <100)
74  {
75      digitalWrite(LED,HIGH);
76      Serial.println("object is near");
77      object = "Near";
78  }
79  else
80  {
81      digitalWrite(LED,LOW);
82      Serial.println("no object found");
83      object = "No";
84  }
85
86  String payload = "{\"distance\":\"";
87  payload += dist;
88  payload += "," " \"object\": \"";
89  payload += object;
90  payload += "\"}";
91
92
93  Serial.print("Sending payload: ");
94  Serial.println(payload);
95
96
97
98

```

```

esp32-blink.ino • diagram.json • libraries.txt • Library Manager
98
99  if (client.publish(publishTopic, (char*) payload.c_str())) {
100      Serial.println("Publish ok");// if it sucessfully upload data on the cloud then it will print publish ok in Serial monitor or else it will print publish failed
101  } else {
102      Serial.println("Publish failed");
103  }
104
105  }
106  void mqttconnect() {
107      if (!client.connected()) {
108          Serial.print("Reconnecting client to ");
109          Serial.println(server);
110          while (!client.connect(clientId, authMethod, token)) {
111              Serial.print(".");
112              delay(500);
113          }
114
115          initManagedDevice();
116          Serial.println();
117      }
118  }
119  void wificonnect() //function defination for wificonnect
120  {
121      Serial.println();
122      Serial.print("Connecting to ");
123
124      Wifi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish the connection
125      while (Wifi.status() != WL_CONNECTED) {
126          delay(500);
127          Serial.print(".");
128      }
129      Serial.println("");
130      Serial.println("Wifi connected");
131      Serial.println("IP address: ");
132      Serial.println(Wifi.localIP());

```


esp32-blink.ino • diagram.json • libraries.txt • Library Manager ▼

```
123
124   WiFi.begin("Wokwi-GUEST", "", 6); //passing the wifi credentials to establish the connection
125   while (WiFi.status() != WL_CONNECTED) {
126       delay(500);
127       Serial.print(".");
128   }
129   Serial.println("");
130   Serial.println("WiFi connected");
131   Serial.println("IP address: ");
132   Serial.println(WiFi.localIP());
133 }
134
135 void initManagedDevice() {
136     if (client.subscribe(subscribetopic)) {
137         Serial.println((subscribetopic));
138         Serial.println("subscribe to cmd OK");
139     } else {
140         Serial.println("subscribe to cmd FAILED");
141     }
142 }
143
144 void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
145 {
146
147     Serial.print("callback invoked for topic: ");
148     Serial.println(subscribetopic);
149     for (int i = 0; i < payloadLength; i++) {
150         //Serial.print((char)payload[i]);
151         data3 += (char)payload[i];
152     }
153
154     // Serial.println("data: " + data3);
155     // if(data3=="Near")
156     // {
157     // Serial.println(data3);
158     // if (data3=="Near") {
159     //     Serial.println("Near");
160     // }
161 }
```

```
esp32-blink.ino • diagram.json • libraries.txt • Library Manager ▼

142 }
143
144 void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
145 {
146
147     Serial.print("callback invoked for topic: ");
148     Serial.println(subscribetopic);
149     for (int i = 0; i < payloadLength; i++) {
150         //Serial.print((char)payload[i]);
151         data3 += (char)payload[i];
152     }
153
154     // Serial.println("data: "+ data3);
155     // if(data3=="Near")
156     // {
157     // Serial.println(data3);
158     // digitalWrite(LED,HIGH);
159
160     // }
161
162     // else
163     // {
164     // Serial.println(data3);
165     // digitalWrite(LED,LOW);
166
167     // }
168     data3="";
169
170
171 }
```


OUTPUT:



The screenshot shows the IBM Watson IoT Platform interface. The top navigation bar includes 'Browse', 'Action', 'Device Types', and 'Interfaces'. A blue 'Add Device' button is in the top right. Below the navigation bar, a header bar displays 'DISTANCEDETECT', 'Disconnected', 'ULTRASON', 'Device', and the timestamp 'Oct 20, 2022 9:46 AM'. The main content area has tabs for 'Identity', 'Device Information', 'Recent Events', 'State', and 'Logs'. The 'Recent Events' tab is active, showing a table of events. The table has columns for 'Event', 'Value', 'Format', and 'Last Received'. There are five rows of data, all with a value of '["distance":141.21,"object":"No"]' and a format of 'json'. The 'Last Received' column shows 'a few seconds ago' for each row. At the bottom, there is a pagination bar showing 'Items per page 50' and '1-2 of 2 items'.

Event	Value	Format	Last Received
Data	["distance":141.21,"object":"No"]	json	a few seconds ago
Data	["distance":141.21,"object":"No"]	json	a few seconds ago
Data	["distance":141.21,"object":"No"]	json	a few seconds ago
Data	["distance":141.18,"object":"No"]	json	a few seconds ago
Data	["distance":141.2,"object":"No"]	json	a few seconds ago

Data send to the IBM cloud device when the objects far



The screenshot shows the Arduino IDE with a code editor on the left and a simulation window on the right. The code editor displays the following code:

```
1 #include <WiFi.h> //library for wifi
2 #include <PubSubClient.h> //library for MQTT
3
4
5 void callback(char* topic, byte* payload, unsigned int payloadlength);
6
7 //-----credentials of IBM Accounts-----
8
9 #define ORG "4hn0jp" //IBM ORGANIZATION ID
10 #define DEVICE_TYPE "ULTRASON" //Device type mentioned in ibm watson IOT Platform
11 #define DEVICE_ID "DISTANCEDETECT" //Device ID mentioned in ibm watson IOT Platform
12 #define TOKEN "wuo5s7PR)ZSegV&RxC" //Token
13 String data3;
14 float dist;
15
16
17 //----- Customise the above values -----
18 char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name
19 char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform and form
20 char subscribeTopic[] = "iot-2/cmd/test/fmt/String"; // cmd REPRESENT command type AND COMMAND I
21 char authMethod[] = "use-token-auth"; // authentication method
22 char token[] = TOKEN;
23 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID; //client id
24
25 //-----
26
27 WiFiClient wificlient; // creating the instance for wificlient
28 PubSubClient client(server, 1883, callback, wificlient); //calling the predefined client id by p
29
30 int LED = 4;
31 int trig = 5;
32 int echo = 18;
33 void setup()
34 {
35   Serial.begin(115200);
```

The simulation window on the right shows a circuit diagram with an ESP32 microcontroller connected to an HC-SR04 ultrasonic sensor. The sensor's VCC pin is connected to the ESP32's VCC pin, and its GND pin is connected to the ESP32's GND pin. The sensor's TRIG pin is connected to the ESP32's pin 5, and its ECHO pin is connected to the ESP32's pin 18. A red LED is connected to the ESP32's pin 4. The simulation window also displays the following text:

```
no object found
Sending payload: {"distance":141.21,"object":"No"}
Publish ok
Distance in cm 141.21
no object found
Sending payload: {"distance":141.21,"object":"No"}
Publish ok
```

Data sent to the IBM Cloud Device when the object is near

Browser Action Device Types Interfaces Add Device

DistanceDETECT Disconnected ULTRASON Device Oct 20, 2022 9:46 AM

Identity Device Information Recent Events State Logs

The recent events listed show the last streams of data that's coming and going from this device.

Event	Value	Format	Last Received
Data	["distance":79.66,"object":"Near"]	json	a few seconds ago
Data	["distance":79.64,"object":"Near"]	json	a few seconds ago
Data	["distance":79.66,"object":"Near"]	json	a few seconds ago
Data	["distance":79.64,"object":"Near"]	json	a few seconds ago
Data	["distance":79.66,"object":"Near"]	json	a few seconds ago

Items per page: 50 1-2 of 2 items 1 of 1 page 1


When objects near to the ultrasonic sensor

wokwi.com/projects/305566932847821378

esp32-arduino.ino by urish

Simulation

00:12.028 100%



```
object is near
Sending payload: {"distance":97.82,"object":"Near"}
Publish ok
Distancein cm97.82
object is near
Sending payload: {"distance":97.82,"object":"Near"}
Publish ok
```