

# VELAMMAL ENGINEERING COLLEGE

## INFORMATION TECHNOLOGY

Assignment Date	07 October 2022
Student Name	D S NIRANJANAA
Student Roll Number	113219071026
Maximum Marks	2 Marks

### Question:

Write python code for blinking LED and Traffic lights for Raspberry pi.

### CODE 1:

#### LED BLINKING

```
import RPi.GPIO as GPIO
import time
GPIO.setmode(GPIO.BCM)
cnt = 0
MAIL_CHECK_FREQ = 1
RED_LED = 4
GPIO.setup(RED_LED, GPIO.OUT)
while True:
    if cnt == 0 :
```

```
GPIO.output(RED_LED, False)

cnt = 1

else:

    GPIO.output(RED_LED, True)

    cnt = 0

time.sleep(MAIL_CHECK_FREQ)

GPIO.cleanup()
```

## **CODE 2:**

### **TRAFFIC LIGHTS FOR RASPBERRY PI**

```
import RPi.GPIO as GPIO

import time

try:

    def lightTraffic(led1, led2, led3, delay ):

        GPIO.output(led1, 1)

        time.sleep(delay)

        GPIO.output(led1, 0)

        GPIO.output(led2, 1)

        time.sleep(delay)

        GPIO.output(led2, 0)

        GPIO.output(led3, 1)

        time.sleep(delay)

        GPIO.output(led3, 0)

    GPIO.setmode(GPIO.BCM)

    button = 19

    GPIO.setup(button, GPIO.IN, pull_up_down=GPIO.PUD_UP)

    ledGreen = 16

    ledYellow = 12
```

```
ledRed = 23
GPIO.setup(ledGreen, GPIO.OUT)
GPIO.setup(ledYellow, GPIO.OUT)
GPIO.setup(ledRed, GPIO.OUT)
while True:
    input_state = GPIO.input(button)
    if input_state == False:
        print('Button Pressed')
        lightTraffic(ledGreen, ledYellow, ledRed, 1)
    else:
        GPIO.output(ledGreen, 0)
        GPIO.output(ledYellow, 0)
        GPIO.output(ledRed, 0)
except KeyboardInterrupt:
    print ("You've exited the program")
finally:
    GPIO.cleanup()
```