ASSIGNMENT-4

Name	BHARANI DHARAN M
Student Roll Number	737819CSL234

Problem Statement:

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100 cm send "alert" to IBM cloud and display in device recent events.

CODE :

```
#include <WiFi.h>//library for wifi
#include <PubSubClient.h>//library for MQtt


void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);

//-------credentials of IBM Accounts------

#define ORG "4hn0jp"//IBM ORGANITION ID
#define DEVICE_TYPE "ULTRASON"//Device type mentioned in ibm watson IOT Platform
#define DEVICE_ID "DISTANCEDETECT"//Device ID mentioned in ibm watson IOT Platform
#define TOKEN "wuo5s7PR)ZSegVk&Rx"//Token
String data3;
float dist;


//-------- Customise the above values --------
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";// Server Name
char publishTopic[] = "iot-2/evt/Data/fmt/json";// topic name and type of event perform and format in which data to be send
char subscribetopic[] = "iot-2/cmd/test/fmt/String";// cmd  REPRESENT command type AND COMMAND IS TEST OF FORMAT STRING
char authMethod[] = "use-token-auth";// authentication method
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;//client id


//-----------------------------------------
WiFiClient wifiClient; // creating the instance for wificlient
PubSubClient client(server, 1883, callback ,wifiClient); //calling the predefined client id by passing parameter like server id,portand wificredential

int LED = 4;
int trig = 5;
int echo = 18;
void setup()
{
Serial.begin(115200);
```

esp32-blink.ino e diagrarri.json e' libra'ñ s.b‹t. e Library Manager

```
pinMode(trig,OUTPUT);
pinMode(echo,INPUT);
pinMode(LED, OUTPUT);
delay(10);
wificonnect();
mqttconnect();
}
void loop()// Recursive Function
{

 digitalWrite(trig,LOW);
  digitalWrite(trig,HIGH);
  delayMicroseconds(10);
  digitalWrite(trig,LOW);
  float dur = pulseIn(echo,HIGH);
  float dist = (dur * 0.0343)/2;
  Serial.print ("Distancein cm");
  Serial.println(dist);


  PublishData(dist);
  delay(1000);
  if (!client.loop()) {
    mqttconnect();
  }
}



/*.....................................retrieving to Cloud.............................*/

void PublishData(float dist) {
  mqttconnect();//function call for connecting to ibm
  /*
     creating the String in in form JSon to update the data to ibm cloud
```

```
     creating the String in in form JSon to update the data to ibm cloud
  */
  String object;
  if (dist <100)
  {
    digitalWrite(LED,HIGH);
    Serial.println("object is near");
    object = "Near";
  }
  else
  {
    digitalWrite(LED,LOW);
    Serial.println("no object found");
    object = "No";
  }

  String payload = "{\"distance\":";
  payload += dist;
  payload += "," "\"object\":\"";
  payload += object;
  payload += "\"}";


  Serial.print("Sending payload: ");
  Serial.println(payload);
```

esp32-blink.ino ● diagram.json ● libraries.txt ● Library Manager

```
98
99    if (client.publish(publishTopic, (char*) payload.c_str())) {
100     Serial.println("Publish ok");// if it sucessfully upload data on the cloud then it will print publish ok in Serial monitor or else it will print publish failed
101   } else {
102     Serial.println("Publish failed");
103   }
104
105 }
106 void mqttconnect() {
107   if (!client.connected()) {
108     Serial.print("Reconnecting client to ");
109     Serial.println(server);
110     while (!!!client.connect(clientId, authMethod, token)) {
111       Serial.print(".");
112       delay(500);
113     }
114
115     initManagedDevice();
116     Serial.println();
117   }
118 }
119 void wificonnect() //function defination for wificonnect
120 {
121   Serial.println();
122   Serial.print("Connecting to ");
123
124   WiFi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish the connection
125   while (WiFi.status() != WL_CONNECTED) {
126     delay(500);
127     Serial.print(".");
128   }
129   Serial.println("");
130   Serial.println("WiFi connected");
131   Serial.println("IP address: ");
132   Serial.println(WiFi.localIP());
```

esp32-bJink.ino e diagram.json e libraries.txt o Library Manager

```
WiFi.:?: ?.:"("t":'I.:'...i-‹)!.'E'I"',    , 6);
      (WiFi.status() != WL CONNECTED) (
       (500);




:s:iai.:'   ' (Wiki.]ocall°());


   initManagedDevice() {
   (client.suoscribe{subscribetopic)) (
  °a i:I. '     !((subscribetopic));




   callback(    * subscribetopic,     ' payload,              payloadLength)


148   sc.'ia:. :.'      (subscribetopic);
        (.    1 = 6j i ‹ payToa dLengt hj 1++) (

     data3 += (    )pay]oad[i];
```

esp32-blink.ino ● diagram.json ● libraries.txt ● Library Manager

```
142  }
143
144  void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
145  {
146
147    Serial.print("callback invoked for topic: ");
148    Serial.println(subscribetopic);
149    for (int i = 0; i < payloadLength; i++) {
150      //Serial.print((char)payload[i]);
151      data3 += (char)payload[i];
152    }
153
154  //   Serial.println("data: "+ data3);
155  //   if(data3=="Near")
156  //   {
157  // Serial.println(data3);
158  // digitalWrite(LED,HIGH);
159
160  //   }
161
162  //   else
163  //   {
164  // Serial.println(data3);
165  // digitalWrite(LED,LOW);
166
167  //   }
168  data3="";
169
170
171  }
```

OUTPUT:

esp32-blink.ino ● diagram.json ● libraries.txt ● Library Manager

```
#include <WiFi.h>//library for wifi
#include <PubSubClient.h>//library for MQtt


void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);

//-------credentials of IBM Accounts------

#define ORG "4hn0jp"//IBM ORGANITION ID
#define DEVICE_TYPE "ULTRASON"//Device type mentioned in ibm watson IOT Platform
#define DEVICE_ID "DISTANCEDETECT"//Device ID mentioned in ibm watson IOT Platform
#define TOKEN "wuo5s7PR)ZSegVk&Rx"//Token
String data3;
float dist;


//-------- Customise the above values --------
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";// Server Name
char publishTopic[] = "iot-2/evt/Data/fmt/json";// topic name and type of event perform and form
char subscribetopic[] = "iot-2/cmd/test/fmt/String";// cmd  REPRESENT command type AND COMMAND I
char authMethod[] = "use-token-auth";// authentication method
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;//client id


//-------------------------------------
WiFiClient wifiClient; // creating the instance for wificlient
PubSubClient client(server, 1883, callback ,wifiClient); //calling the predefined client id by p

int LED = 4;
int trig = 5;
int echo = 18;
void setup()
{
Serial.begin(115200);
```

Simulation

00:18.152 98%




```
no object found
Sending payload: {"distance":141.21,"object":"No"}
Publish ok
Distancein cm141.21
no object found
Sending payload: {"distance":141.21,"object":"No"}
Publish ok
```

Data send to the IBM cloud device when the object is far



when object is near to the ultrasonic sensor



Data sent to the IBM Cloud Device when the object is near