Assignment -3

Python Programming

Assignment Date	02 October 2022
Student Name	Y. Malathi
Student Roll Number	211519106080
Maximum Marks	2 Marks

Question-1:

Write a python code for led blinking in raspberry pi

SOLUTION:

```
import RPi.GPIO as GPIO # Import Raspberry Pi GPIO library

from time import sleep # Import the sleep function from the time module


GPIO.setwarnings(False) # Ignore warning for now

GPIO.setmode(GPIO.BOARD) # Use physical pin numbering

GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set initial value to low (off)

while True: # Run forever

 GPIO.output(8, GPIO.HIGH) # Turn on

 sleep(1) # Sleep for 1 second

 GPIO.output(8, GPIO.LOW) # Turn off

 sleep(1) # Sleep for 1 second
```

```
File  Edit  Format  Run  Options  Window  Help
import RPI.GPIO as GPIO # Import Raspberry Pi GPIO library
from time import sleep # Import the sleep function from the time module

GPIO.setwarnings(False) # Ignore warning for now
GPIO.setmode(GPIO.BOARD) # Use physical pin numbering
GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set initial value to low (off)

while True: # Run forever
 GPIO.output(8, GPIO.HIGH) # Turn on
 sleep(1) # Sleep for 1 second
 GPIO.output(8, GPIO.LOW) # Turn off
 sleep(1) # Sleep for 1 second
```

Question-2:

Write a python code for traffic light in raspberry pi

SOLUTION:

```
from gpiozero import Button, TrafficLights, Buzzer
from time import sleep

buzzer = Buzzer(15)
button = Button(21)
lights = TrafficLights(25, 8, 7)

while True:
    button.wait_for_press()
    buzzer.on()
    light.green.on()
    sleep(1)
    lights.amber.on()
    sleep(1)
    lights.red.on()
    sleep(1)
    lights.off()
    buzzer.off()
```