

Assignment -3

Python Programming

Assignment Date	01 September 2022
Student Name	Suriyakumar C
Student Roll Number	422419106040

Question-1:

Write python code for blinking LED and Traffic lights for Raspberry pi.

Solution:

```
import RPi.GPIO as GPIO
import time
import signal
import sys

# Setup
GPIO.setmode(GPIO.BCM)
GPIO.setup(9, GPIO.OUT)
GPIO.setup(10, GPIO.OUT)
GPIO.setup(11, GPIO.OUT)

# Turn off all lights when its end
def allLightsOff(signal, frame):
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, False)
    GPIO.cleanup()
    sys.exit(0)

signal.signal(signal.SIGINT, allLightsOff)

# Loop for led light
while True:
```

RED LIGHT

GPIO.output(9, True)

time.sleep(3)

RED AND YELLOW

GPIO.output(10, True)

time.sleep(1)

GREEN LIGHT

GPIO.output(9, False)

GPIO.output(10, False)

GPIO.output(11, True)

time.sleep(5)

YELLOW LIGHT

GPIO.output(11, False)

GPIO.output(10, True)

time.sleep(2)

#YELLOW OFF (red start from first loop)

GPIO.output(10, False)