

Assignment -4
ARDUINO Programming

Assignment Date	9 September 2022
Student Name	G.P.VISHNU PRAKASH
Student Roll Number	910619106068
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events. Upload document with wokwi share link and images of IBM cloud

Solution:

```
#include <WiFi.h>
#include <PubSubClient.h>
#include <ArduinoJson.h>

WiFiClient wifiClient;

#define ORG "kr9fjo"
#define DEVICE_TYPE "TestDeviceType"
#define DEVICE_ID "12345"
#define TOKEN "VJsSC148dk1dCN3UqS"
#define speed 0.034

char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/abcd_1/fmt/json";
char topic[] = "iot-2/cmd/home/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
void publishData();

const int trigpin=5;
const int echopin=18;
String command;
String data="";
String lat="14.167589";
String lon="80.248510";
String name="point2";
String icon="";

long duration;
int dist;

void setup()
{
```

```

Serial.begin(115200);
pinMode(trigpin, OUTPUT);
pinMode(echopin, INPUT);
wifiConnect();
mqttConnect();
}

void loop() {

  publishData();
  delay(500);

  if (!client.loop()) {
    mqttConnect();
  }
}

void wifiConnect() {
  Serial.print("Connecting to "); Serial.print("Wifi");
  WiFi.begin("Wokwi-GUEST", "", 6);
  while (WiFi.status() != WL_CONNECTED) {
    delay(500);
    Serial.print(".");
  }
  Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}

void mqttConnect() {
  if (!client.connected()) {
    Serial.print("Reconnecting MQTT client to "); Serial.println(server);
    while (!client.connect(clientId, authMethod, token)) {
      Serial.print(".");
      delay(1000);
    }
    initManagedDevice();
    Serial.println();
  }
}

void initManagedDevice() {
  if (client.subscribe(topic)) {
    Serial.println(client.subscribe(topic));
    Serial.println("subscribe to cmd OK");
  } else {
    Serial.println("subscribe to cmd FAILED");
  }
}

void publishData()
{
  digitalWrite(trigpin, LOW);

```


```

digitalWrite(trigpin,HIGH);
delayMicroseconds(10);
digitalWrite(trigpin,LOW);
duration=pulseIn(echopin,HIGH);
dist=duration*speed/2;

if(dist<100){
    dist=100-dist;
    icon="fa-trash";
}else{
    dist=0;
    icon="fa-trash-o";
}
DynamicJsonDocument doc(1024);
String payload;
doc["Name"]=name;
doc["Latitude"]=lat;
doc["Longitude"]=lon;
doc["Icon"]=icon;
doc["FillPercent"]=dist;
serializeJson(doc, payload);
delay(3000);
Serial.print("\n");
Serial.print("Sending payload: ");
Serial.println(payload);
if (client.publish(publishTopic, (char*) payload.c_str())) {
    Serial.println("Publish OK");
} else {
    Serial.println("Publish FAILED");
}
}
}

```

OUTPUT:



<input type="checkbox"/>	Device ID	Status	Device Type	Class ID	Date Added	Descriptive Location
<input checked="" type="checkbox"/>	12345	Disconnected	RaspberryPI	Device	Oct 29, 2022 8:53 PM	
Identity Device Information Recent Events State Logs						
The recent events listed show the live stream of data that is coming and going from this device.						
Event	Value	Format	Last Received			
Ultra_Sonic	{"Distance":29}	json	a few seconds ago			
Ultra_Sonic	{"Distance":92}	json	a few seconds ago			
Ultra_Sonic	{"Distance":86}	json	a few seconds ago			
Ultra_Sonic	{"Distance":62}	json	a few seconds ago			
Ultra_Sonic	{"Distance":10}	json	a few seconds ago			

1 Simulation running