

PROJECT DEVELOPMENT PHASE
DELIVERY OF SPRINT-3
INDUSTRY SPECIFIC INTELLIGENT FIRE MANAGEMENT SYSTEM

```
#include <WiFi.h>
#include <Wire.h>
#include <SPI.h>
#include "ThingSpeak.h"
#include <WiFiClient.h>

unsigned long myChannelNumber = 2; const char *
myWriteAPIKey = "25V40ZAPI6KIZFGY";
int LED_PIN = 32; // the current reading from the input pin
int BUZZER_PIN= 12; const
int mq2 = 4;
int value = 0;

//Flame
int flame_sensor_pin = 10 ;// initializing pin 10 as the sensor digital output pin int
flame_pin = HIGH ; // current state of sensor

char ssid[] = "Amirtha"; char
pass[] = "Amirtharavi";
WiFiClient client;
#define PIN_LM35 39
#define ADC_VREF_mV 3300.0
#define ADC_RESOLUTION 4096.0
#define RELAY_PIN 17
#define RELAY_PIN1 27

void setup()
{
  Serial.begin(115200);
  pinMode(RELAY_PIN, OUTPUT);
  pinMode(RELAY_PIN1, OUTPUT);
  Serial.print("Connecting to ");
  Serial.println(ssid);
  WiFi.begin(ssid, pass);
  int wifi_ctr = 0;
  while (WiFi.status() != WL_CONNECTED)
  {
    delay(1000);
    Serial.print(".");
```

```

}
Serial.println("WiFi connected");
ThingSpeak.begin(client); pinMode(LED_PIN,
OUTPUT); pinMode(mq2, INPUT);
pinMode ( flame_sensor_pin , INPUT ); // declaring sensor pin as input pin for Arduino
pinMode(BUZZER_PIN, OUTPUT);
}

```

```

void temperature()
{
int adcVal = analogRead(PIN_LM35);
float milliVolt = adcVal * (ADC_VREF_mV / ADC_RESOLUTION);
float tempC = milliVolt / 10; Serial.print("Temperature: ");
Serial.print(tempC);
Serial.print("°C");
if(tempC > 60)
{
Serial.println("Alert");
digitalWrite(BUZZER_PIN, HIGH); // turn on
}
else
{
digitalWrite(BUZZER_PIN, LOW); // turn on
}
int x = ThingSpeak.writeField(myChannelNumber,1, tempC, myWriteAPIKey); }

```

```

void GasSensors()
{
//mq2

int gassensorAnalogmq2 = analogRead(mq2);
Serial.print("mq2 Gas Sensor: ");
Serial.print(gassensorAnalogmq2);
Serial.print("\t");
Serial.print("\t");
Serial.print("\t");

if (gassensorAnalogmq2 > 1500)
{
Serial.println("mq2Gas");
Serial.println("Alert");
digitalWrite(RELAY_PIN1, HIGH); // turn on fan 10 seconds
delay(100);
}
}

```

```

    }
else
{
    Serial.println("No mq2Gas");
    digitalWrite(RELAY_PIN1, LOW); // turn off fan 10 seconds
    delay(100);

}

int a = ThingSpeak.writeField(myChannelNumber,4, gassensorAnalogmq2,
myWriteAPIKey);

}

void flamesensor()
{
    flame_pin = digitalRead ( flame_sensor_pin ) ; // reading from the sensor if
(flame_pin == LOW ) // applying condition
{
    Serial.println ( " ALERT: FLAME IS DETECTED" ) ;
    digitalWrite (BUZZER_PIN, HIGH ) ;// if state is high, then turn high the BUZZER
} else
{
    Serial.println ( " NO FLAME DETECTED " ) ;
    digitalWrite (BUZZER_PIN , LOW ) ; // otherwise turn it low
}
    int value = digitalRead(flame_sensor_pin); // read the analog value from sensor

    if (value ==LOW) {
    Serial.print("FLAME");
    digitalWrite(RELAY_PIN, HIGH);
    } else {
        Serial.print("NO FLAME");
        digitalWrite(RELAY_PIN, LOW);
    }

} void loop() {
temperature();
GasSensors();
flamesensor();
}

```