

Assignment -4
Python Programming

Assignment Date	10 oct2022
Student Name	J.V.K.Vishwapoojitha
Student Roll Number	910619106070
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for the ultrasonic sensor. Whenever the distance is less than 100 cms send an "alert" to the IBM cloud and display in the device recent events. Upload document with wokwi share link and images of IBM cloud

Program:

```
#include <WiFi.h>
#include <PubSubClient.h>
#include <ArduinoJson.h>

WiFiClient wifiClient;

#define ORG "kr9fjo"
#define DEVICE_TYPE "TestDeviceType"
#define DEVICE_ID "12345"
#define TOKEN "VJsSC148dk1dCN3UqS"
#define speed 0.034

char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/abcd_1/fmt/json";
char topic[] = "iot-2/cmd/home/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
void publishData();

const int trigpin=5;
const int echopin=18;
String command;
String data="";
String lat="14.167589";
String lon="80.248510";
String name="point2";
String icon="";

long duration;
int dist;
```

```

void setup()
{
    Serial.begin(115200);
    pinMode(trigpin, OUTPUT);
    pinMode(echopin, INPUT);
    wifiConnect();
    mqttConnect();
}

void loop() {

    publishData();
    delay(500);

    if (!client.loop()) {
        mqttConnect();
    }
}

void wifiConnect() {
    Serial.print("Connecting to "); Serial.print("Wifi");
    WiFi.begin("Wokwi-GUEST", "", 6);
    while (WiFi.status() != WL_CONNECTED) {
        delay(500);
        Serial.print(".");
    }
    Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}

void mqttConnect() {
    if (!client.connected()) {
        Serial.print("Reconnecting MQTT client to "); Serial.println(server);
        while (!client.connect(clientId, authMethod, token)) {
            Serial.print(".");
            delay(1000);
        }
        initManagedDevice();
        Serial.println();
    }
}

void initManagedDevice() {
    if (client.subscribe(topic)) {
        Serial.println(client.subscribe(topic));
        Serial.println("subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    }
}

void publishData()

```

```

{
    digitalWrite(trigpin,LOW);
    digitalWrite(trigpin,HIGH);
    delayMicroseconds(10);
    digitalWrite(trigpin,LOW);
    duration=pulseIn(echopin,HIGH);
    dist=duration*speed/2;

    if(dist<100){
        dist=100-dist;
        icon="fa-trash";
    }else{
        dist=0;
        icon="fa-trash-o";
    }
    DynamicJsonDocument doc(1024);
    String payload;
    doc["Name"]=name;
    doc["Latitude"]=lat;
    doc["Longitude"]=lon;
    doc["Icon"]=icon;
    doc["FillPercent"]=dist;
    serializeJson(doc, payload);
    delay(3000);
    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish OK");
    } else {
        Serial.println("Publish FAILED");
    }
}

```

Output:

The screenshot shows the WOKWI simulation environment. On the left, the sketch code is displayed, which includes the following details:

- Includes: `<WiFi.h>`, `<PubSubClient.h>`, `<ArduinoJson.h>`
- Constants: `ORG "kr9fjo"`, `DEVICE_TYPE "TestDeviceType"`, `DEVICE_ID "12345"`, `TOKEN "Vj5SC148dk1dCN3Uq5"`, `speed 0.034`
- Variables: `server[]`, `publishTopic[]`, `topic[]`, `authMethod[]`, `token[]`, `clientId[]`
- Functions: `publishData()`, `setup()`
- Hardware: `trigpin=5`, `echopin=18`, `OUTPUT`

On the right, the simulation interface shows an ESP32 microcontroller connected to an HC-SR04 ultrasonic sensor. The sensor is connected to the microcontroller's pins 5, 18, and GND. The simulation is running, and the output is visible in the console.

The screenshot shows the IBM Watson IoT Platform dashboard. The top navigation bar includes "Browse", "Action", "Device Types", and "Interfaces". The main content area displays a list of devices, with the following details:

Device ID	Status	Device Type	Class ID	Date Added	Descriptive Location	Added By
12345	Disconnected	RasberryPi	Device	Oct 31, 2022 3:19 PM		venkateshbg01@gmail.com

Below the device list, the "Recent Events" tab is selected, showing a table of events:

Event	Value	Format	Last Received
Distance	{"distance":74}	json	a few seconds ago
Distance	{"distance":89}	json	a few seconds ago
Distance	{"distance":12}	json	a few seconds ago
Distance	{"distance":52}	json	a few seconds ago
Distance	{"distance":45}	json	a few seconds ago

The bottom status bar indicates "1 Simulation running".