ASSIGNMENT 3

PYTHON CODE FOR BLINKING LED(Raspberry pi)

```python
import RPi.GPIO as GPIO
import time
GPIO.setmode(GPIO.BCM)
GPIO.setwarnings(False)
GPIO.setup(18,GPIO.OUT)
print "LED on"
GPIO.output(18,GPIO.HIGH)
time.sleep(1)
print "LED off"
GPIO.output(18,GPIO.LOW)
```

PYTHON CODE FOR TRAFFIC LIGHT(Raspberry pi)

```python
import RPi.GPIO as GPIO
import time
try:
  def lightTraffic(led1, led2, led3, delay ):
    GPIO.output(led1, 1)
    time.sleep(delay)
    GPIO.output(led1, 0)
    GPIO.output(led2, 1)
    time.sleep(delay)
    GPIO.output(led2, 0)
    GPIO.output(led3, 1)
    time.sleep(delay)
    GPIO.output(led3, 0)
  GPIO.setmode(GPIO.BCM)
  button = 19
  GPIO.setup(button, GPIO.IN, pull_up_down=GPIO.PUD_UP)
  ledGreen = 16
  ledYellow = 12
  ledRed = 23
  GPIO.setup(ledGreen, GPIO.OUT)
```

```python
    GPIO.setup(ledYellow, GPIO.OUT)
    GPIO.setup(ledRed, GPIO.OUT)
    while True:
        input_state = GPIO.input(button)
        if input_state == False:
            print('Button Pressed')
            lightTraffic(ledGreen, ledYellow, ledRed, 1)
        else:
            GPIO.output(ledGreen, 0)
            GPIO.output(ledYellow, 0)
            GPIO.output(ledRed, 0)
except KeyboardInterrupt:
    print "You've exited the program"
finally:
    GPIO.cleanup()
```