

PANIMALAR INSTITUTE OF TECHNOLOGY

E.C.E

Assignment Date	07 October 2022
Student Name	G YASWANTH
Student Roll Number	211519106041
Maximum Marks	2 Marks

Question:

Write python code for blinking LED and Traffic lights for Raspberry pi.

CODE 1:

LED BLINKING

```
import RPi.GPIO as GPIO
import time

GPIO.setmode(GPIO.BCM)

cnt = 0

MAIL_CHECK_FREQ = 1
RED_LED = 4

GPIO.setup(RED_LED, GPIO.OUT)

while True:

    if cnt == 0 :
```

```
GPIO.output(RED_LED, False)
```

```
cnt = 1
```

```
else:
```

```
GPIO.output(RED_LED, True)
```

```
cnt = 0
```

```
time.sleep(MAIL_CHECK_FREQ)
```

```
GPIO.cleanup()
```

CODE 2:

TRAFFIC LIGHTS FOR RASPBERRY PI

```
import RPi.GPIO as GPIO
```

```
import time
```

```
try:
```

```
def lightTraffic(led1, led2, led3, delay ):
```

```
    GPIO.output(led1, 1)
```

```
    time.sleep(delay)
```

```
    GPIO.output(led1, 0)
```

```
    GPIO.output(led2, 1)
```

```
    time.sleep(delay)
```

```
    GPIO.output(led2, 0)
```

```
    GPIO.output(led3, 1)
```

```
    time.sleep(delay)
```

```
    GPIO.output(led3, 0)
```

```
GPIO.setmode(GPIO.BCM)
```

```
button = 19
```

```
GPIO.setup(button, GPIO.IN, pull_up_down=GPIO.PUD_UP)
```

```
ledGreen = 16
```

```
ledYellow = 12
```

```
ledRed = 23
GPIO.setup(ledGreen, GPIO.OUT)
GPIO.setup(ledYellow, GPIO.OUT)
GPIO.setup(ledRed, GPIO.OUT)

while True:
    input_state = GPIO.input(button)
    if input_state == False:
        print('Button Pressed')
        lightTraffic(ledGreen, ledYellow, ledRed, 1)
    else:

        GPIO.output(ledGreen, 0)
        GPIO.output(ledYellow, 0)
        GPIO.output(ledRed, 0)
except KeyboardInterrupt:
    print ("You've exited the program")
finally:
    GPIO.cleanup()
```