

## **IOT BASED SMART FARMING-ASSINGMENT 3**

Write a python code for blinking LED and Traffic lights for Raspberry pi.

### **CODE:**

#### **RASPBERRY PI LED BLINK:**

```
import RPi.GPIO as GPIO
import time

GPIO.setmode(GPIO.BCM)
GPIO.setwarnings(False)
GPIO.setup(18,GPIO.OUT) print
("LED on")
GPIO.output(18,GPIO.HIGH)
time.sleep(1) print ("LED
off")
GPIO.output(18,GPIO.LOW)
```

## **CODE:**

### **RASPBERRY PI FOR TRAFFIC LIGHT:**

```
import RPi.GPIO as GPIO
import time
import signal
import sys

GPIO.setmode(GPIO.BCM)
GPIO.setup(9, GPIO.OUT)
GPIO.setup(10, GPIO.OUT)
GPIO.setup(11, GPIO.OUT)

def allLightsOff(signal, frame):
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, False)
    GPIO.cleanup()
    sys.exit(0)

signal.signal(signal.SIGINT,
allLightsOff)

while True:
    GPIO.output(9, True)
    time.sleep(3)
    GPIO.output(10, True)
    time.sleep(1)
```

```
GPIO.output(9, False)
GPIO.output(10, False)
GPIO.output(11, True)
time.sleep(5)
GPIO.output(11, False)
GPIO.output(10, True)
time.sleep(2)
GPIO.output(10, False)
```