ASSIGNMENT 1

Date	4th November 2022
Team ID	PNT2022TMID10102
Project Name	Industry Specific Intelligent Fire Management System

```
#include <Servo.h>

int output1Value = 0;
int sen1Value = 0;
int sen2Value = 0;
int const gas_sensor = A1;
int const LDR = A0;
int limit = 400;

long readUltrasonicDistance(int triggerPin, int echoPin)
{
  pinMode(triggerPin, OUTPUT);  // Clear the trigger
  digitalWrite(triggerPin, LOW);
  delayMicroseconds(2);
// Sets the trigger pin to HIGH state for 10 microseconds
  digitalWrite(triggerPin, HIGH);
```

```
  delayMicroseconds(10);
  digitalWrite(triggerPin, LOW);
  pinMode(echoPin, INPUT);
  // Reads the echo pin, and returns the sound wave travel time in microseconds
  return pulseIn(echoPin, HIGH);
}

Servo servo_7;

void setup()
{
   Serial.begin(9600);              //initialize serial communication
  pinMode(A0, INPUT);           //LDR
  pinMode(A1,INPUT);            //gas sensor
  pinMode(13, OUTPUT);                  //connected to relay
  servo_7.attach(7, 500, 2500); //servo motor

  pinMode(8,OUTPUT);            //signal to piezo buzzer
  pinMode(9, INPUT);            //signal to PIR
  pinMode(10, OUTPUT);                  //signal to npn as switch
  pinMode(4, OUTPUT);           //Red LED
  pinMode(3, OUTPUT);           //Green LED
```

```
}

void loop()
{

    //------light intensity control ----- //
//_____________________________________________-
   int val1 = analogRead(LDR);
  if (val1 > 500)
        {
        digitalWrite(13, LOW);
   Serial.print("Bulb ON = ");
   Serial.print(val1);
        }
  else
        {
        digitalWrite(13, HIGH);
    Serial.print("Bulb OFF = ");
   Serial.print(val1);
        }

//_____________________________________________-
       //------ light & fan control ------- //
```

```
//_____________________________________________-
  sen2Value = digitalRead(9);
  if (sen2Value == 0)
        {
        digitalWrite(10, LOW); //npn as switch OFF
        digitalWrite(4, HIGH); // Red LED ON,indicating no motion
        digitalWrite(3, LOW); //Green LED OFF, since no Motion detected
    Serial.print("     || NO Motion Detected    " );
        }

  if (sen2Value == 1)
        {
        digitalWrite(10, HIGH);//npn as switch ON
    delay(5000);
        digitalWrite(4, LOW); // RED LED OFF
        digitalWrite(3, HIGH);//GREEN LED ON , indicating motion detected
     Serial.print("       || Motion Detected!      " );
        }


//_____________________________________________
      // ------- Gas Sensor ------- //
//_____________________________________________
```

```
int val = analogRead(gas_sensor);      //read sensor value
  Serial.print("|| Gas Sensor Value = ");
  Serial.print(val);                              //Printing in serial monitor
//val = map(val, 300, 750, 0, 100);
  if (val > limit)
          {
          tone(8, 650);
          }
          delay(300);
          noTone(8);

 //_____________________________________________
      //-------  servo motor --------- //
 //_____________________________________________-
  sen1Value = 0.01723 * readUltrasonicDistance(6, 6);

  if (sen1Value < 100)
          {
          servo_7.write(90);
    Serial.print("        || Door Open!  ; Distance = ");
    Serial.print(sen1Value);
   Serial.print("\n");
```

```
        }
  else
        {
        servo_7.write(0);
    Serial.print("        || Door Closed! ; Distance =  ");
    Serial.print(sen1Value);
    Serial.print("\n");
  }
  delay(10); // Delay a little bit to improve simulation performance
}
```