Assignment -3

Python Programming

Assignment Date	19 November 2022
Student Name	SUDHARSAN R
Student Roll Number	PNT2022TMID18648
Maximum Marks	2 Marks

Question-1:

Write a Python code for Blinking LED and Traffic Light for Raspberry Pi

Solution:

Blinking Of an LED For Raspberry

```
import RPi.GPIO as GPIO # Import Raspberry Pi GPIO library

from time import sleep # Import the sleep function from the time module



GPIO.setwarnings(False) # Ignore warning for now

GPIO.setmode(GPIO.BOARD) # Use physical pin numbering

GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set in
itial value to low (off)



while True: # Run forever

 GPIO.output(8, GPIO.HIGH) # Turn on

 sleep(1) # Sleep for 1 second

 GPIO.output(8, GPIO.LOW) # Turn off

 sleep(1) # Sleep for 1 second
```

Traffic Light for Raspberry Pi

```
import RPi.GPIO as GPIO
import time
import signal
import sys

# Setup
GPIO.setmode(GPIO.BCM)
GPIO.setup(9, GPIO.OUT)
GPIO.setup(10, GPIO.OUT)
GPIO.setup(11, GPIO.OUT)

# Turn off all lights when user ends demo
def allLightsOff(signal, frame):
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, False)
    GPIO.cleanup()
    sys.exit(0)
signal.signal(signal.SIGINT, allLightsOff)

# Loop forever
while True:
    #  Red
    GPIO.output(9, True)
    time.sleep(3)
    # Red and amber
    GPIO.output(10, True)
    time.sleep(1)
    #  Green
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, True)
    time.sleep(5)
    # Amber
    GPIO.output(11, False)
    GPIO.output(10, True)
    time.sleep(2)
    # Amber off (red comes on at top of loop)
    GPIO.output(10, False)
```