

NAME: KOUSHIK CHOUDARY BHUMA

REGISTER NUMBER: 111519106075

\*\*\*\*\*

## Write A Python Code For Blinking Led For Raspberry Pi.

```
import RPi.GPIO as GPIO # Import Raspberry Pi GPIO library

from time import sleep # Import the sleep function from the time module

GPIO.setwarnings(False) # Ignore warning for now

GPIO.setmode(GPIO.BOARD) # Use physical pin numbering

GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set initial value to low (off)

while True: # Run forever

    GPIO.output(8, GPIO.HIGH) # Turn on

    sleep(1) # Sleep for 1 second

    GPIO.output(8, GPIO.LOW) # Turn off

    sleep(1) # Sleep for 1 second
```

## Write A Python Code For Traffic Lights For Raspberry Pi.

```
import RPi.GPIO as GPIO

import time

try:

    def lightTraffic(led1, led2, led3, delay ):

        GPIO.output(led1, 1)

        time.sleep(delay)

        GPIO.output(led1, 0)

        GPIO.output(led2, 1)

        time.sleep(delay)

        GPIO.output(led2, 0)
```

```
GPIO.output(led3, 1)

time.sleep(delay)

GPIO.output(led3, 0)

GPIO.setmode(GPIO.BCM)

button = 19

GPIO.setup(button, GPIO.IN, pull_up_down=GPIO.PUD_UP)

ledGreen = 16

ledYellow = 12

ledRed = 23

GPIO.setup(ledGreen, GPIO.OUT)

GPIO.setup(ledYellow, GPIO.OUT)

GPIO.setup(ledRed, GPIO.OUT)

while True:

    input_state = GPIO.input(button)

    if input_state == False:

        print('Button Pressed')

        lightTraffic(ledGreen, ledYellow, ledRed, 1)

    else:

        GPIO.output(ledGreen, 0)

        GPIO.output(ledYellow, 0)

        GPIO.output(ledRed, 0)

except KeyboardInterrupt:

    print "You've exited the program"

finally:

    GPIO.cleanup()
```