Project Development

Delivery Of Sprint-2

Date	09 Nov. 22
Team Id	PNT2022TMID51073
Project Name	SmartFarmer - IoT Enabled Smart Farming Application

PROGRAM

```
#include <Adafruit_LiquidCrystal.h> //Includes the library for LCD Display

#include <Wire.h>          //Includes the library for connections

#include <Servo.h>          //Includes the library for Servo Motor




Servo s;

int e = 4;

int t = 5;

int r = 12;

int b = 11;

int g = 10;

int sec = 0;

int Sensor = 0;

int soil = 0;

int motorPin = 9;

Adafruit_LiquidCrystal lcd(0);




void setup()

{
```

```
  Wire.begin();

  pinMode(A0, INPUT);      // Temperature Sensor

  pinMode(A1, INPUT);      // Soil Moisture Sensor

  pinMode(t, OUTPUT);      // Ultra sonic Trigger


  pinMode(e, INPUT);       // Ultra sonic Echo

  pinMode(b, OUTPUT);      // GREEN light for LED

  pinMode(g, OUTPUT);      // BLUE light for LED

  pinMode(r, OUTPUT);      // RED light for LED

  pinMode(motorPin, OUTPUT);      // DC motor

  s.attach(3);          // Servo Motor

  lcd.begin(16, 2);  // LCD 16x2 Display

  lcd.setBacklight(0);

  Serial.begin(9600);

}



float readDistanceCM()

{

digitalWrite(t, LOW);

delayMicroseconds(2);

digitalWrite(t, HIGH);

delayMicroseconds(10);

digitalWrite(t, LOW);

int duration = pulseIn(e, HIGH);

return duration * 0.034 / 2;

}



void loop()
```

```
{
// Soil Moisture:

Sensor = analogRead(A1);            // Reads data from Soil Moisture    sensor

soil = map(Sensor, 0, 1023, 0, 117);


// Low analog value indicates HIGH moisture level and High analog value indicates LOW moisture level

// data = map(analogValue,fromLOW,fromHIGH,toLOW,toHIGH)

Serial.print("Soil Moisture value:");

Serial.println(soil);

//'data = 0' indicates total wetness and 'data = 100' indicates total dryness



// Temperature:

double a = analogRead(A0);          // Reads data from Temperature sensor

double t = (((a / 1024) * 5) - 0.5) * 100;

Serial.print("Temperature value:"); //Temperature value in Celsius

Serial.println(t);



// Ultrasonic sensor:

float distance = readDistanceCM(); //Reads data from Ultrasonic sensor

Serial.print("Measured distance: ");

Serial.println(readDistanceCM());



// LCD Display:

lcd.setBacklight(1);          //ON the background light in LCD

lcd.clear();


// Conditions:
```

/*If the temperature is Greater than 20 and less than 35 and also the moisture of soil is less than 60 then the GREEN light will be turned ON indicating the Normal condition */

```
if (t >= 20 && t < 35 && soil >= 40 && soil < 50)

{

digitalWrite(b, 0);

digitalWrite(g, 1);

digitalWrite(r, 0);

s.write(90);


digitalWrite(motorPin, HIGH);

lcd.setCursor(3, 0);

lcd.print("ON MOTOR");

delay(1000);

lcd.clear();

Serial.println("Water Partially Flows");

}
```

/*If the temperature is Greater than 35 and less than 45, then the BLUE light will be turned ON indicating the Intermediate risk condition due to slightly warm weather */

```
else if (t >= 35 && t < 45)

{

digitalWrite(b, 1);

digitalWrite(g, 0);

digitalWrite(r, 0);

s.write(90);

digitalWrite(motorPin, HIGH);

lcd.setCursor(3, 0);
```

```
lcd.print("ON MOTOR");

delay(1000);

lcd.clear();

Serial.println("Water Partially Flows");

}
```

/*If the temperature is Greater than 45 or the moisture of soil is less than 30, then the RED light will be turned ON indicating the Critical condition due to highly warm weather or the low moisture content in soil */

```
else if (t >= 45 || soil < 30)

{

digitalWrite(b, 0);

digitalWrite(g, 0);

digitalWrite(r, 1);

s.write(180);

digitalWrite(motorPin, HIGH);

Serial.println("Water Fully Flows");

lcd.setCursor(2, 0);

lcd.print("ON MOTOR!!!");

lcd.setCursor(3, 1);

lcd.print("Low Water");

delay(1000);

lcd.clear();

}
```

/*If the level of water is MORE in the field it will be indicated by distance sensor for less than 10cm and also the moisture of soil is greater than 80, then the

YELLOW light will be turned ON indicating the high water level */

```
else if (distance<10 && soil> 80)
```

```
{

digitalWrite(b, 0);

digitalWrite(g, 1);

digitalWrite(r, 1);

s.write(0);

digitalWrite(motorPin, LOW);

Serial.println("Water Does Not Flow");

lcd.clear();

lcd.setCursor(3, 0);

lcd.print("OFF MOTOR");

delay(1000);

lcd.clear();

lcd.setCursor(1, 0);

lcd.print("DRAIN WATER!!!");

delay(1000);

lcd.clear();


}




else

{

digitalWrite(b, 1);

digitalWrite(g, 1);

digitalWrite(r, 0);

s.write(0);

digitalWrite(motorPin, LOW);

lcd.setCursor(3, 0);

lcd.print("OFF MOTOR");
```

```
delay(1000);

lcd.clear();

Serial.println("Water Does Not Flow");

}




lcd.setCursor(0, 0);

lcd.print("Temp:");

lcd.print(t);

lcd.print("degree");

lcd.setCursor(0, 1);

lcd.print("SoilWetness:");

lcd.print(soil);

lcd.print("%");




Serial.println("   ");

delay(1000);

}
```

COMPONENTS

S.NO	COMPONENTS	QUANTITY
1	Arduino uno r3	1
2	Micro servo	1
3	Led rgb	1
4	200 Ω Resistor	3
5	Soil Moisture Sensor	1
6	DC Motor	1
7	240Ω Resistor	1
8	Temperature sensor(TMP36)	1
9	Ultrasonic Distance sensor	1
10	32 LCD 16 x 2 (I2C)	1
11	DIP Switch DPST	1

CIRCUIT CONNECTION