

B3-3M5E

ASSIGNMENT-3

PYTHON CODE FOR BLINKING LED AND TRAFFIC LIGHTS FOR RASPBERRY PI

For LED:

```
import RPi.GPIO as GPIO                                # Import Raspberry Pi GPIO
library                                                  library
from time import sleep                                  #Import sleep function from the
time module                                              time module
GPIO.setwarnings(False)                                #Ignore warning for now
GPIO.setmode(GPIO.BOARD)                               #Use physical pin numbering
GPIO.setup(8,GPIO.OUT,initial=GPIO.LOW)
#Set pin 8 to be an output pin and set initial value to low(off)
while True:                                             #Run forever
    GPIO.output(8,GPIO.HIGH)                             #Turn on
    sleep(1)                                              #Sleep for 1 second
    GPIO.output(8,GPIO.LOW)                             #Turn off
    sleep(1)                                              #Sleep for 1 second
```

For Traffic Lights:

```
import Rpi.GPIO as GPIO
import time
import signal
import sys
```

```
#Setup
GPIO.setmode(GPIO.BCM)
GPIO.setup(9,GPIO.OUT)
GPIO.setup(10,GPIO.OUT)
GPIO.setup(11,GPIO.OUT)

#Turn off all lights when user ends demo
def allLightsOff(signal,framer):
    GPIO.output(9,False)
    GPIO.output(10,False)
    GPIO.output(11,False)
    GPIO.cleanup()
    sys.exit(0)
signal.signal(signal.SIGINT,allLightsOff)

#Loop forever
while True:
    #Red
    GPIO.output(9,True)
    Time.sleep(3)
    #Red and amber
    GPIO.output(10,True)
    Time.sleep(1)
```

#Green

GPIO.output(9,False)

GPIO.output(10,False)

GPIO.output(11,True)

Time.sleep(5)

#Amber

GPIO.output(11,False)

GPIO.output(10,True)

Time.sleep(2)

#Amber off(red comes on at top of loop)

GPIO.output(10,False)