

Assignment-4

Distance Detection Using Ultrasonic Sensor

Assignment Date	02 November2022
Student Name	Mr.R. Akilan
Student Roll Number	112719205002
Maximum Marks	2 Marks

Question-1:

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100cms send "alert" to ibm cloud and display in device recent events.

WOKWI LINK : <https://wokwi.com/projects/34719485237133371>

CODE:

```
#include <WiFi.h>
#include <PubSubClient.h>

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);

#define ORG "f59trs"
#define DEVICE_TYPE "ultrasonicsensor"
#define DEVICE_ID "distancedetection"
#define TOKEN "AlGMGaaF01nawa1QA3"
String data3;
float dist;

char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char subscribetopic[] = "iot-2/cmd/test/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;

WiFiClient wifiClient;
PubSubClient client(server, 1883, callback ,wifiClient);

int LED = 4;
int trig = 5;
int echo = 18;
void setup()
{
  Serial.begin(115200);
  pinMode(trig,OUTPUT);
```

```

pinMode(echo, INPUT);
pinMode(LED, OUTPUT);
delay(10);
wificonnect();
mqttconnect();
}
void loop()
{
    digitalWrite(trig, LOW);
    digitalWrite(trig, HIGH);
    delayMicroseconds(10);
    digitalWrite(trig, LOW);
    float dur = pulseIn(echo, HIGH);
    float dist = (dur * 0.0343)/2;
    Serial.print("Distance in cm :");
    Serial.println(dist);

    PublishData(dist);
    delay(1000);
    if (!client.loop()) {
        mqttconnect();
    }
}

void PublishData(float dist) {
    mqttconnect();
    String object;
    if (dist < 100)

```

```

if (dist < 100)
{
    digitalWrite(LED, HIGH);
    Serial.println("object is near");
    object = "Near";
}
else
{
    digitalWrite(LED, LOW);
    Serial.println("no object found");
    object = "No";
}

String payload = "{\"distance\": ";
payload += dist;
payload += ", \"object\": \"";
payload += object;
payload += "\"}";

    Serial.print("Sending payload: ");
    Serial.println(payload);

    if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish ok");
    } else {
        Serial.println("Publish failed");
    }
}

void mqttconnect() {
    if (!client.connected()) {

```

```

        Serial.print("Reconnecting client to ");
        Serial.println(server);
        while (!client.connect(clientId, authMethod, token)) {
            Serial.print(".");
            delay(500);
        }
        initManagedDevice();
        Serial.println();
    }
}

void wificonnect()
{
    Serial.println();
    Serial.print("Connecting to ");
    WiFi.begin("Wokwi-GUEST", "", 6);
    while (WiFi.status() != WL_CONNECTED) {
        delay(500);
        Serial.print(".");
    }
    Serial.println("");
    Serial.println("WiFi connected");
    Serial.println("IP address: ");
    Serial.println(WiFi.localIP());
}

void initManagedDevice() {
    if (client.subscribe(subscribetopic)) {
        Serial.println((subscribetopic));
        Serial.println("subscribe to cmd OK");
    } else {
        Serial.println("subscribe to cmd FAILED");
    }
}

```

OUTPUT:

```

        Serial.println("subscribe to cmd FAILED");
    }
}

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{
    Serial.print("callback invoked for topic: ");
    Serial.println(subscribetopic);
    for (int i = 0; i < payloadLength; i++) {
        data3 += (char)payload[i];
    }
    data3="";
}

```

When object is not near to the ultrasonic sensor

WOKWI

SAVE

SHARE

Docs


M

sketch.ino diagram.json libraries.txt Library Manager

```
1 #include <WiFi.h>
2 #include <PubSubClient.h>
3
4 void callback(char* subscribetopic, byte* payload, unsigned int payloadlength);
5
6 #define ORG "f59trs"
7 #define DEVICE_TYPE "ultrasonicsensor"
8 #define DEVICE_ID "distancedetection"
9 #define TOKEN "AlGKGaaf0inawaiQA3"
10 String data3;
11 float dist;
12
13 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
14 char publishTopic[] = "iot-2/evt/Data/fmt/json";
15 char subscribetopic[] = "iot-2/cmd/test/fmt/String";
16 char authMethod[] = "use-token-auth";
17 char token[] = TOKEN;
18 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
19
20
21 WiFiClient wifiClient;
22 PubSubClient client(server, 1883, callback, wifiClient);
23
24 int LED = 4;
25 int trig = 5;
26 int echo = 18;
27 void setup()
28 {
29   Serial.begin(115200);
30   pinMode(trig, OUTPUT);
```

Simulation

00:12.360 79%



no object found
Sending payload: {"distance":403.49,"object":"No"}
Publish ok
Distance in cm :403.49
no object found
Sending payload: {"distance":403.49,"object":"No"}
Publish ok

Browse Action Device Types Interfaces

Add Device

distancedetection Connected ultrasonicsensor Device Oct 19, 2022 11:56 AM

Identity Device Information Recent Events State Logs

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"distance":235.02,"object":"No"}	json	a few seconds ago
Data	{"distance":235.02,"object":"No"}	json	a few seconds ago
Data	{"distance":235.02,"object":"No"}	json	a few seconds ago
Data	{"distance":235.02,"object":"No"}	json	a few seconds ago
Data	{"distance":235.02,"object":"No"}	json	a few seconds ago

0 Simulations running

Data sent to the IBM cloud device when the object is far

When object is nearer to the ultrasonic sensor

WOKWI

SAVE

SHARE

Docs

M

sketch.ino

diagram.json

libraries.txt

Library Manager

```

1 #include <WiFi.h>
2 #include <PubSubClient.h>
3
4 void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);
5
6 #define ORG "f59trs"
7 #define DEVICE_TYPE "ultrasonicsensor"
8 #define DEVICE_ID "distancedetection"
9 #define TOKEN "AlGMGaaF0Inawa1QA3"
10 String data3;
11 float dist;
12
13 char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
14 char publishTopic[] = "iot-2/evt/Data/fmt/json";
15 char subscribetopic[] = "iot-2/cmd/test/fmt/String";
16 char authMethod[] = "use-token-auth";
17 char token[] = TOKEN;
18 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
19
20
21 WiFiClient wifiClient;
22 PubSubClient client(server, 1883, callback ,wifiClient);
23
24 int LED = 4;
25 int trig = 5;
26 int echo = 18;
27 void setup()
28 {
29   Serial.begin(115200);
30   pinMode(trig,OUTPUT);

```

Simulation

00:54.571 100%

Editing Ultrasonic Distance Sensor

Distance: 52cm

object is near

Sending payload: {"distance":52.44,"object":"Near"}

Publish ok

Distance in cm :52.44

object is near

Sending payload: {"distance":52.44,"object":"Near"}

Publish ok

Data sent to the IBM cloud device when the object is near

Browse

Action

Device Types

Interfaces

Add Device

Device ID	Status	Device Type	Class ID	Date Added	Descriptive Location
distancedetection	Connected	ultrasonicsensor	Device	Oct 19, 2022 11:56 AM	

Identity

Device Information

Recent Events

State

Logs

The recent events listed show the live stream of data that is coming and going from this device.

Event	Value	Format	Last Received
Data	{"distance":91.77,"object":"Near"}	json	a few seconds ago
Data	{"distance":91.75,"object":"Near"}	json	a few seconds ago
Data	{"distance":91.77,"object":"Near"}	json	a few seconds ago
Data	{"distance":91.79,"object":"Near"}	json	a few seconds ago
Data	{"distance":91.8,"object":"Near"}	json	a few seconds ago

0 Simulations running

<https://wokwi.com/projects/347194852371333714>