Assignment -4

BATCH NO : B9-3A5E

Assignment Date	19 October 2022
Student Name	Ajith B
Student Roll Number	962219205003
Maximum Marks	2 Marks

WokWi Link : https://wokwi.com/projects/347843333031199315

Program :

```
#include <WiFi.h>
#include <PubSubClient.h>
#include <ArduinoJson.h>

WiFiClient wifiClient;

#define ORG "7h1uma"
#define DEVICE_TYPE "eps32"
#define DEVICE_ID "12345"
#define TOKEN "123456789"
#define speed 0.034

char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char topic[] = "iot-2/cmd/home/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
void publishData();

const int trigpin=5;
const int echopin=18;
String command;
String data="";

long duration;
int dist;

void setup()
{
  Serial.begin(115200);
  pinMode(trigpin, OUTPUT);
```

```
  pinMode(echopin, INPUT);
  wifiConnect();
  mqttConnect();
}

void loop() {

  publishData();
  delay(500);

  if (!client.loop()) {
    mqttConnect();
  }
}

void wifiConnect() {
  Serial.print("Connecting to "); Serial.print("Wifi");
  WiFi.begin("Wokwi-GUEST", "", 6);
  while (WiFi.status() != WL_CONNECTED) {
    delay(500);
    Serial.print(".");
  }
  Serial.print("WiFi connected, IP address: ");
Serial.println(WiFi.localIP());
}

void mqttConnect() {
  if (!client.connected()) {
    Serial.print("Reconnecting MQTT client to "); Serial.println(server);
    while (!client.connect(clientId, authMethod, token)) {
      Serial.print(".");
      delay(1000);
    }
    initManagedDevice();
    Serial.println();
  }
}

void initManagedDevice() {
  if (client.subscribe(topic)) {
     Serial.println(client.subscribe(topic));
    Serial.println("subscribe to cmd OK");
  } else {
    Serial.println("subscribe to cmd FAILED");
  }
}
void publishData()
{
```

```
  digitalWrite(trigpin,LOW);
  digitalWrite(trigpin,HIGH);
  delayMicroseconds(10);
  digitalWrite(trigpin,LOW);
  duration=pulseIn(echopin,HIGH);
  dist=duration*speed/2;

  if(dist<100){
    DynamicJsonDocument doc(1024);
    String payload;
    doc["AlertDistance:"]=dist;
    serializeJson(doc, payload);
    delay(3000);
    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if (client.publish(publishTopic, (char*) payload.c_str())) {
      Serial.println("Publish OK");
    } else {
      Serial.println("Publish FAILED");
    }
  }
}
```

Output :




St. Xavier's Catholic College of Er
Search results - lijishdon@gmail
New ESP32 Project - Wokwi Simu
IBM Watson IoT Platform
7h1uma.internetofthings.ibmcloud.com/dashboard/devices/drilldown/eps32:12345?returnTo=/devices/browse
IBM Watson IoT Platform
lijish.501926@sxcce.edu.in
ID: 7h1uma
Back
Device Drilldown - 12345
Connection Information
Recent Events
State
Device Information
Metadata
Diagnostics
Connection Logs
Device Actions
Recent Events
The recent events listed show the live stream of data that is coming and going from this device.
Event
Value
Format
Last Received
Data
{"AlertDistance:":52}
json
a few seconds ago
Data
{"AlertDistance:":52}
json
a few seconds ago
Data
{"AlertDistance:":51}
json
a few seconds ago
Data
{"AlertDistance:":51}
json
a few seconds ago
Data
{"AlertDistance:":51}
json
a few seconds ago
Activate Windows
Go to Settings to activate Windows.
3:24 PM
11/9/2022