ASSIGNMENT-3

Date	14-10-2022
Team ID	PNT2022TMID45219
Project Name	Industry-specific intelligent fire management system
Maximum Marks	2 Marks

NAME: MUTHUSELVAN G

TOPIC: Write python code for blinking LED and Traffic lights for Raspberry pi.

CODE:

1) PYTHON CODE FOR BLINKING LED

```
import RPi.GPIO as GPIO # Import Raspberry Pi GPIO library from

time import sleep # Import the sleep function from the time module

GPIO.setwarnings(False) # Ignore warning for now

GPIO.setmode(GPIO.BOARD) # Use physical pin numbering

GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set initial value to low

(off)

while True: # Run forever

GPIO.output(8, GPIO.HIGH) # Turn on

sleep(1) # Sleep for 1 second
```

2) PYTHON CODE FOR TRAFFIC LIGHT

```
GPIO.output(8, GPIO.LOW) # Turn off

Sleep (1) # Sleep for 1 second import
```

```
RPi.GPIO as GPIO import time import
signal import sys

# Setup
GPIO.setmode(GPIO.BCM)
GPIO.setup(9, GPIO.OUT)
GPIO.setup(10, GPIO.OUT)
GPIO.setup(11, GPIO.OUT)


# Turn off all lights when user ends demo
def allLightsOff(signal, frame):
GPIO.output(9, False)

GPIO.output(10, False)
GPIO.output(11, False)
GPIO.cleanup() sys.exit(0)

signal.signal(signal.SIGINT, allLightsOff)


# Loop forever while
True:

# Red
GPIO.output(9, True)
time.sleep(3)
# Red and amber
GPIO.output(10, True)
time.sleep(1) # Green

GPIO.output(9, False)
```

```
GPIO.output(10, False)
GPIO.output(11, True) time.sleep(5)

# Amber
GPIO.output(11, False)
GPIO.output(10, True) time.sleep(2)

# Amber off (red comes on at top of loop)
GPIO.output(10, False)
```