

## **ASSIGNMENT 3**

**MAHENDRA ENGINEERING COLLEGE FOR  
WOMEN**

**NAME:P.SOBIYA**

**CLASS:4 YEAR CSE**

**SUBJECT:IBM**

**REGISTER NO:611419104082**

**Question-1:**

Write python code for blinking LED and Traffic lights for Raspberry pi.

**Solution:**

```
import RPi.GPIO as GPIO
import time
import signal
import sys

# Setup
GPIO.setmode(GPIO.BCM)
GPIO.setup(9, GPIO.OUT)
GPIO.setup(10, GPIO.OUT)
GPIO.setup(11, GPIO.OUT)

# Turn off all lights when user ends demo
def allLightsOff(signal, frame):
    GPIO.output(9, False)
    GPIO.output(10, False)
    GPIO.output(11, False)
    GPIO.cleanup()
    sys.exit(0)

signal.signal(signal.SIGINT, allLightsOff)

# Loop forever
while True:
    # Red
    GPIO.output(9, True)
    time.sleep(3)

    # Red and amber
    GPIO.output(10, True)
    time.sleep(1)

    # Green
```

```
GPIO.output(9, False)
GPIO.output(10, False)
GPIO.output(11, True)
time.sleep(5)
```

```
# Amber
GPIO.output(11, False)
GPIO.output(10, True)
time.sleep(2)
```

```
# Amber off (red comes on at top of loop)
GPIO.output(10, False)
```