

PYTHON CODE FOR LED BLINKING FOR RASPBERRY PI

```
import RPi.GPIO as GPIO

import time

LED_PIN = 17

GPIO.setmode(GPIO.BCM)

GPIO.setup(LED_PIN, GPIO.OUT)

while True:

    GPIO.output(LED_PIN, GPIO.HIGH)

    time.sleep(1)

    GPIO.output(LED_PIN, GPIO.LOW)

    time.sleep(1)

GPIO.cleanup()
```

PYTHON CODE FOR TRAFFIC LIGHTS FOR RASPBERRY PI

```
import RPi.GPIO as GPIO

import time


try:

    def lightTraffic(led1, led2, led3, delay ):

        GPIO.output(led1, 1)

        time.sleep(delay)

        GPIO.output(led1, 0)

        GPIO.output(led2, 1)

        time.sleep(delay)

        GPIO.output(led2, 0)
```

```
GPIO.output(led3, 1)
time.sleep(delay)
GPIO.output(led3, 0)
GPIO.setmode(GPIO.BCM)
button = 19
GPIO.setup(button, GPIO.IN, pull_up_down=GPIO.PUD_UP)
ledGreen = 16
ledYellow = 12
ledRed = 23
GPIO.setup(ledGreen, GPIO.OUT)
GPIO.setup(ledYellow, GPIO.OUT)
GPIO.setup(ledRed, GPIO.OUT)
while True:
    input_state = GPIO.input(button)
    if input_state == False:
        print('Button Pressed')
        lightTraffic(ledGreen, ledYellow, ledRed, 1)
    else:
        GPIO.output(ledGreen, 0)
        GPIO.output(ledYellow, 0)
        GPIO.output(ledRed, 0)
except KeyboardInterrupt:
    print "You've exited the program"
finally:
    GPIO.cleanup()
```