

ASSIGNMENT-4

DISTANCE DETECTION USING ULTRASONIC SENSOR

| | |
|---------------------|------------------|
| Date | 30 October 2022 |
| Team ID | PNT2022TMID10957 |
| Name | AJAY KUMAR B |
| Student Roll Number | 811519106007 |
| Maximum Marks | 2 Marks |

Question1 :

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100 cms send "alert" to ibm cloud and display in device recent events.

WOKWI LINK :

<https://wokwi.com/projects/305566932847821378>

```
1  #include <WiFi.h> //library for wifi
2  #include <PubSubClient.h> //library for MQTT
3
4
5  void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);
6
7  //-----credentials of IBM Accounts-----
8
9  #define ORG "4hn0jp" //IBM ORGANITION ID
10 #define DEVICE_TYPE "ULTRASON" //Device type mentioned in ibm watson IOT Platform
11 #define DEVICE_ID "DISTANCEDETECT" //Device ID mentioned in ibm watson IOT Platform
12 #define TOKEN "wuo5s7PR)ZSegV&R&x" //Token
13 String data3;
14 float dist;
15
16
17 //----- Customise the above values -----
18 char server[] = ORG ".messaging.internetofthings.ibmcloud.com"; // Server Name
19 char publishTopic[] = "iot-2/evt/Data/fmt/json"; // topic name and type of event perform and format in which data to be send
20 char subscribetopic[] = "iot-2/cmd/test/fmt/String"; // cmd REPRESENT command type AND COMMAND IS TEST OF FORMAT STRING
21 char authMethod[] = "use-token-auth"; // authentication method
22 char token[] = TOKEN;
23 char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID; //client id
24
25
26 //-----
27 WiFiClient wificlient; // creating the instance for wificlient
28 PubSubClient client(server, 1883, callback ,wificlient); //calling the predefined client id by passing parameter like server id,portand wificredential
29
30 int LED = 4;
31 int trig = 5;
32 int echo = 18;
33 void setup()
34 {
35   Serial.begin(115200);
```

CODE :

```
36  pinMode(trig,OUTPUT);
37  pinMode(echo,INPUT);
38  pinMode(LED, OUTPUT);
39  delay(10);
40  wificonnect();
41  mqttconnect();
42  }
43  void loop()// Recursive Function
44  {
45
46      digitalWrite(trig,LOW);
47      digitalWrite(trig,HIGH);
48      delayMicroseconds(10);
49      digitalWrite(trig,LOW);
50      float dur = pulseIn(echo,HIGH);
51      float dist = (dur * 0.0343)/2;
52      Serial.print ("Distancein cm");
53      Serial.println(dist);
54
55
56      PublishData(dist);
57      delay(1000);
58      if (!client.loop()) {
59          mqttconnect();
60      }
61  }
62
63
64
65  /*.....retrieving to Cloud.....*/
66
67  void PublishData(float dist) {
68      mqttconnect();//function call for connecting to ibm
69      /*
70      |   creating the String in in form JSON to update the data to ibm cloud
```

```

70 | | creating the String in in form JSON to update the data to ibm cloud
71 */
72 String object;
73 if (dist <100)
74 {
75     digitalWrite(LED,HIGH);
76     Serial.println("object is near");
77     object = "Near";
78 }
79 else
80 {
81     digitalWrite(LED,LOW);
82     Serial.println("no object found");
83     object = "No";
84 }
85
86 String payload = "{\"distance\":";
87 payload += dist;
88 payload += "," " \"object\":";
89 payload += object;
90 payload += "\"}";
91
92
93 Serial.print("Sending payload: ");
94 Serial.println(payload);
95
96
97
98

```


```
98
99   if (client.publish(publishTopic, (char*) payload.c_str())) {
100       Serial.println("Publish ok");// if it sucessfully upload data on the cloud then it will print publish ok in Serial monitor or else it will print publish failed
101   } else {
102       Serial.println("Publish failed");
103   }
104
105   }
106   void mqttconnect() {
107       if (!client.connected()) {
108           Serial.print("Reconnecting client to ");
109           Serial.println(server);
110           while (!client.connect(clientId, authMethod, token)) {
111               Serial.print(".");
112               delay(500);
113           }
114
115           initManagedDevice();
116           Serial.println();
117       }
118   }
119   void wificonnect() //function defination for wificonnect
120   {
121       Serial.println();
122       Serial.print("connecting to ");
123
124       WiFi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish the connection
125       while (WiFi.status() != WL_CONNECTED) {
126           delay(500);
127           Serial.print(".");
128       }
129       Serial.println("");
130       Serial.println("Wifi connected");
131       Serial.println("IP address: ");
132       Serial.println(WiFi.localIP());
```

```
123
124   WiFi.begin("Wokwi-GUEST", "", 6); //passing the wifi credentials to establish the connection
125   while (WiFi.status() != WL_CONNECTED) {
126       delay(500);
127       Serial.print(".");
128   }
129   Serial.println("");
130   Serial.println("WiFi connected");
131   Serial.println("IP address: ");
132   Serial.println(WiFi.localIP());
133 }
134
135 void initManagedDevice() {
136     if (client.subscribe(subscribetopic)) {
137         Serial.println(subscribetopic);
138         Serial.println("subscribe to cmd OK");
139     } else {
140         Serial.println("subscribe to cmd FAILED");
141     }
142 }
143
144 void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
145 {
146
147     Serial.print("callback invoked for topic: ");
148     Serial.println(subscribetopic);
149     for (int i = 0; i < payloadLength; i++) {
150         //Serial.print((char)payload[i]);
151         data3 += (char)payload[i];
152     }
153
154     // Serial.println("data: "+ data3);
155     // if(data3=="Near")
156     // {
157     // Serial.println(data3);
158     // Serial.print("data: "+ data3);
159 }
```




```
esp32-blink.ino • diagram.json • libraries.txt • Library Manager ▼
142     }
143
144 void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
145 {
146
147     Serial.print("callback invoked for topic: ");
148     Serial.println(subscribetopic);
149     for (int i = 0; i < payloadLength; i++) {
150         //Serial.print((char)payload[i]);
151         data3 += (char)payload[i];
152     }
153
154     // Serial.println("data: "+ data3);
155     // if(data3=="Near")
156     // {
157     // Serial.println(data3);
158     // digitalWrite(LED,HIGH);
159
160     // }
161
162     // else
163     // {
164     // Serial.println(data3);
165     // digitalWrite(LED,LOW);
166
167     // }
168     data3="";
169
170
171 }
```

OUTPUT:



Data send to the IBM cloud device when the object is far



when object is near to the ultrasonic sensor


wokwi.com/projects/305566932847821378

esp32-arduino.ino
by urish

Simulation

00:12.028

Start the simulation



object is near
Sending payload: {"distance":97.82,"object":"Near"}
Publish ok
Distance in cm 97.82
object is near
Sending payload: {"distance":97.82,"object":"Near"}
Publish ok

Data sent to the IBM Cloud Device when the object is near

4hn0jp.internetofthings.ibmcloud.com/dashboard/devices/browse

IBM Watson IoT Platform

110119106007@aallmec.ac.
ID: 4hn0jp

Browse Action Device Types Interfaces

ADD DEVICE

DistanceDETECT Disconnected ULTRASON Device Oct 20, 2022 9:46 AM

Identity Device Information Recent Events State Logs

The recent events listed show the live stream of data that is coming and going from this device.

| Event | Value | Format | Last Received |
|-------|------------------------------------|--------|-------------------|
| Data | {"distance":79.66,"object":"Near"} | json | a few seconds ago |
| Data | {"distance":79.64,"object":"Near"} | json | a few seconds ago |
| Data | {"distance":79.66,"object":"Near"} | json | a few seconds ago |
| Data | {"distance":79.64,"object":"Near"} | json | a few seconds ago |
| Data | {"distance":79.66,"object":"Near"} | json | a few seconds ago |

Items per page 50 | 1-2 of 2 items

1 of 1 page

<https://wokwi.com/projects/305566932847821378>