

Recessed Mini Door / Window Sensor

Wireless, Supervised Sensor

- Easy to install.
- Easy to “Learn” into 319 or 345 MHz wireless control panels.
- Compact size: 2.25” L x .75” Dia.
- Signals: supervisory, tamper, and low battery.
- Effective with vertical or horizontal mount.
- Replaceable extra long-life lithium battery: 1-CR123A.
- Smaller and narrow switch package.
- Superior RF range and performance, even on steel surfaces.
- Wireless sensors and detectors built with MaxOut™ Technology for maximum Radio Frequency (RF) security sensor reliability. MaxOut high performance sensors deliver the maximum FCC allowable output for maximum signal strength and range.

The Recessed Mini Door/Window Sensor is a supervised, wireless sensor that detects the opening and closing of doors or windows. New, high-powered Microchip delivers exceptional range; 360° with no dead spots or signal drop-offs.



Specifications

Model Number:	RF-RDWS-319-NN RF-RDWS-345-NN
RF Frequency:	319.5 MHz 345 MHz
Compatibility:	319.5 MHz control panels. Interlogix® GE®, ITI® and Qolsys® 345 MHz control panels. Honeywell® and 2GIG®
Battery Type: (Requires 1)	3-VDC Lithium Battery, Varta or Panasonic CR123A
Operating Temperature Range:	32 to 120°F (0-49°C)
Storage Temperature Range:	-30 to 140°F (-34 to 60°C)
Relative Humidity:	95% Non-Condensing
Dimensions: (L x Diameter)	Sensor: 2.25 in. x .75 in. Magnet: 1 in. x .7/8 in.



12075 43rd Street NE., Suite 500
St Michael, MN 55110

Web: MaxOuttech.com | Phone: 612-615-8448 | Email: info@MaxOutTech.com