Decimal code	Opc (3-bit)	*Argo type*	Src (3-bit)	*Args type*	Arg pnt (2-bit)	Arg reg (2-bit)	Arg cnd (2-bit)	Arg part (2-bit)	Arg act (2-bit)	ALU cin (1-bit)	ALU mode (1-bit)	ALU arithmetic mode (4-bit)	ALU logic mode (4-bit)
0	PF	*PNT*	PF	*PNT*	PCI (PNT 0)	R0 (B)	NEG	X	X	YES	ARITHMETIC	A+CIN	!A
1	A	*X*	X	*X*	API (PNT 1)	R1 (C)	CO	LOW	RST	NO	LOGIC	A||B+CIN	!(A||B)
2	RF	*REG*	RF	*REG*	PC (PNT 2)	R2 (D)	EQU	HIGH	SET	-	-	A||(!B)+CIN	(!A)&&B
3	SF	*PNT*	SF	*PNT*	AP (PNT 3)	R3 (E)	INTM	BOTH	(INVALID)	-	-	-1+CIN	LOW
4	CMP	*CND*	X	*X*	-	-	-	-	-	-	-	A+(A&&(!B))+CIN	!(A&&B)
5	DVR	*PART*	DVR	*X*	-	-	-	-	-	-	-	(A||B)+(A&&(!B))+CIN	!B
6	ADRD	*X*	ADRD	*X*	-	-	-	-	-	-	-	A-B-1+CIN	A^B
7	INTC	*ACT*	INTB	*X*	-	-	-	-	-	-	-	(A&&(!B))-1+CIN	A&&(!B)
8	-	-	-	-	-	-	-	-	-	-	-	A+(A&&B)+CIN	(!A)||B
9	-	-	-	-	-	-	-	-	-	-	-	A+B+CIN	!(A^B)
10	-	-	-	-	-	-	-	-	-	-	-	(A||(!B))+(A&&B)+CIN	B
11	-	-	-	-	-	-	-	-	-	-	-	(A&&B)-1+CIN	A&&B
12	-	-	-	-	-	-	-	-	-	-	-	A+A+CIN	HIGH
13	-	-	-	-	-	-	-	-	-	-	-	(A||B)+A+CIN	A||(!B)
14	-	-	-	-	-	-	-	-	-	-	-	(A||(!B))+A+CIN	A||B
15	-	-	-	-	-	-	-	-	-	-	-	A-1+CIN	A