Due to network constraints and limited manpower on our side, we have not been able to conduct tests on picoreplayer for the time being. We would like to express our sincere appreciation to user **Eric Retail** for sharing his detailed configuration process. On behalf of our company and our team, we extend our heartfelt thanks to him.

Here is the detailed information he shared:

1. This post by 'paul-' has the critical essentials;
https://forums.lyrion.org/forum/user-forums/linux-unix/108457-announce-picoreplayer-6-0-0/page80?111787-ANNOUNCE-piCorePlayer-6-0-0=#post1449623
However, some things were far from obvious. Some other references and specific details of note include

2. use SSH to access your running picoreplayer's terminal console and then mount the boot partition, where you can then edit the config.txt file and
   a. remove 'spi=on'
   b. change 'dtparm=audio=on' to 'dtparm=audio=off'
Refer to below link:
https://docs.picoreplayer.org/how-to/edit_config_txt/

3. the Squeezelite settings need to be
   a. Set audio output to Merus Audio Amp, reboot as required
   b. accept the provided Output Setting ('hw:CARD=sndrpimerusamp')
   c. in the ALSA setting's 3rd box, put '24' to set the bitrate for sample format
   d. in the Max sample rate box, enter '48000'
   e. Save settings

4. I think i rebooted before returning to the 'ALSA Mixer' settings, maybe this would work before step 3. In any case, the ALSA configuration is still odd to me and there might be a bug in the picoreplayer implementation, because the UI continues to revert to the same default values after reportedly saving changes. I didn't know what to set, but according to the forum post's recommendation to reduce the threshold limit, I Dropped those values to lower values than they started and changed the master volume level to about half. I checked the values via SSH amixer commands and I think i saw levels of threshold volume limit levels for left and right at 35 which is 50%. I don't know if those were the originals or not, but the device is working with those levels now. I have tested with a single 4ohm speaker on the left channel and intend to connect other speakers tomorrow and may experiment with other values for the mixer.

Note: 'speaker-test' via the console has not worked, reporting 'device or resource is busy'. I didn't have that issue when using the DAC hat, btw. But what's important for the AMP hat is picoreplayer's squeezebox is operational with at (and LMS plays through it nicely)