

COMPRESSOR



- The electric motor and valve are made of strong and rust resistant materials
- Equipped with a two-way ball-valve
- Equipped with a pressure valve and two pressure gauges
- The air filter is made of metal



INCLUDE : User Manual, Warranty Card, Oil Machine, Cover Engine Oil, Air Filter

SPECIFICATION	RCP 75-1 (3/4 HP)	RCP 100-1 (1.0 HP)	RCP 200-1 (2 HP)	RCP 250-1 (2.5 HP)
CURRENT	< 2.27 A	< 3.40 A	< 6.81 A	< 8.63 A
INPUT POWER	< 500 Watt	< 750 Watt	< 1500 Watt	< 1900 Watt
ROTATE SPEED	2800 ± 10% rpm	2800 ± 10% rpm	2850 ± 10% rpm	2850 ± 10% rpm
POWER CABLE	> 180 mm	> 180 mm	> 180 mm	> 180 mm
GAS ON TIME	55s ± 5	90s ± 5	100s ± 5	190s ± 5
SWITCH MACHINE DOWNTIME	0.8 ± 0.02 Mpa	0.8 ± 0.02 Mpa	0.8 ± 0.02 Mpa	0.8 ± 0.02 Mpa
RESTORING BOOT PRESSURE SWITCH	0.5 ± 0.02 Mpa	0.5 ± 0.02 Mpa	0.5 ± 0.02 Mpa	0.5 ± 0.02 Mpa
TANK CAPACITY	10 L	25 L	35 L	50 L
PIECE ROTOR PLATE	80 Pc	100 Pc	130 Pc	130 Pc
DIAMETER PISTON	42 mm	42 mm	47 mm	47 mm
STROKE	32	35	38	38