PRACTICAL 3

1️⃣ Devices Required

- 1 Router
- 1 Switch
- 2 PCs
- 1 Server (for Syslog / NetFlow monitoring)

2️⃣ Device Connections

Use **Copper Straight-Through cable**.

Device	Port	Connect To	Port
PC-1	FastEthernet0	Switch	Fa0/1
PC-2	FastEthernet0	Switch	Fa0/2
Router	Fa0/0	Switch	Fa0/3
Server	FastEthernet0	Switch	Fa0/4

Topology:

```
PC1 ----\
        \
         Switch ---- Router
        /
PC2 ----/
         |
        Server
```

3️⃣ IP Addressing

PC1

IP: 192.168.1.2
Mask: 255.255.255.0
Gateway: 192.168.1.1

PC2

IP: 192.168.1.3
Mask: 255.255.255.0
Gateway: 192.168.1.1

Router

enable
configure terminal
interface GigabitEthernet0/0
ip address 192.168.1.1 255.255.255.0
no shutdown

Server

IP: 192.168.1.10
Mask: 255.255.255.0
Gateway: 192.168.1.1

4️⃣ SPAN Configuration (Switch)

Mirror traffic from PC1 port to monitoring port.

enable
configure terminal
monitor session 1 source interface fa0/1
monitor session 1 destination interface fa0/4

5️⃣ SNMP Configuration

On Router:

enable
configure terminal
snmp-server community public ro
snmp-server community private rw

6️⃣ Syslog Configuration

logging 192.168.1.10
service timestamps log datetime msec

7️⃣ NetFlow Configuration

interface GigabitEthernet0/0
ip flow ingress
ip flow egress

ip flow-export destination 192.168.1.10 9995
ip flow-export source GigabitEthernet*0/0*

8️⃣ Test

PC1 se PC2 ping karo:

ping 192.168.1.3

Traffic generate hoga aur **SPAN / SNMP / NetFlow monitor karega**.