Appendix G - Per-CPU Opcode Quick Reference

One table per CPU. Each table is a single-line summary of every mnemonic; the full encoding, addressing modes, flag effects, and timing notes are in the per-CPU chapter (Chapters 24-29). This appendix is for the reader who has the chapter open already and only needs to look up "is this mnemonic spelled this way" or "what does this opcode do at a glance".

The byte-entry crib under each CPU is deliberately small. It covers the encodings used by the chapter example so a reader can type, disassemble, and check the machine-code program directly in IE Mon.

G.1 IE64 (Chapter 24)

Fixed `8`-byte instruction, 32 GPRs `R0`-`R31`, `R0 = 0`, `R31 = SP`. Compare-and-branch ISA; no separate flag register.

Group	Mnemonics
ALU	`ADD`, `SUB`, `MULU`, `MULS`, `DIVU`, `DIVS`, `MOD`, `MODS`, `AND`, `OR`, `EOR`, `NOT`, `NEG`, `LSL`, `LSR`, `ASR`, `ROL`, `ROR`, `CLZ`, `CTZ`, `POPCNT`, `BSWAP`.
Load / store	`LOAD.B/.W/.L/.Q`, `STORE.B/.W/.L/.Q`. Address modes: register indirect, register plus displacement, and absolute.
Immediate	`MOVE.Q rd, #imm32`, `MOVT rd, #imm32`, `MOVEQ rd, rs`, `LEA rd, disp(rs)`.
Branch	`BRA`, `JSR`, `RTS`, `JMP`, `BEQ`, `BNE`, `BLT`, `BLE`, `BGT`, `BGE`, `BHI`, `BLS`. Conditional forms compare two GPRs and a target.
FPU	`FADD`, `FSUB`, `FMUL`, `FDIV`, `FMOD`, `FNEG`, `FABS`, `FSQRT`, `FCMP`, `FCVTIF`, `FCVTFI`, single and double precision.
System	`SYSCALL`, `HALT`, `WAIT`, `MTCR`, `MFCR`, `ERET`, `TLBFLUSH`, `TLBINVAL`, `SMODE`.

Byte-entry crib for Chapter 24:

Bytes	Meaning	Hand-entry note
`01 17 00 00 ii ii ii ii`	`MOVE.Q R2,#imm32`	Byte `1` is `(2 << 3) | (3 << 1) | 1`; the immediate is little-endian.
`01 0F 00 00 ii ii ii ii`	`MOVE.Q R1,#imm32`	Byte `1` is `(1 << 3) | (3 << 1) | 1`; use this for small values before a store.
`11 08 10 00 dd dd dd dd`	`STORE.B R1,disp(R2)`	Byte `1` selects `R1` and byte size; byte `2` selects base register `R2`; displacement is little-endian.
`11 0C 10 00 dd dd dd dd`	`STORE.L R1,disp(R2)`	Same register fields, size code `L`; used for `32`-bit frequency or address registers.
`40 06 00 00 dd dd dd dd`	`BRA disp32`	The Chapter 24 example uses displacement `0`, which branches back to the branch instruction itself.

G.2 IE32 (Chapter 25)

`8`-byte instruction, 16 named registers `A,X,Y,Z,B,C,D,E,F,G,H,S,T,U,V,W`, no MMU, no FPU.

Group	Mnemonics
ALU	`ADD`, `SUB`, `MUL`, `DIV`, `MOD`, `AND`, `OR`, `XOR`, `NOT`, `NEG`, `SHL`, `SHR`.

Group	Mnemonics
Load / store	LDA/LDX/LDY/LDZ, LDB-LDW, STA/STX/STY/STZ, STB-STW, plus generic LOAD/STORE.
Immediate	Immediate addressing mode on load and ALU instructions.
Branch	JMP, JSR, RTS, JZ, JNZ, JGT, JGE, JLT, JLE.
Stack	PUSH rA, POP rA.
Timing	WAIT n delays for n cycles.

Byte-entry crib for Chapter 25:

Bytes	Meaning	Hand-entry note
`20 00 00 00 vv vv vv vv`	`LDA A,#imm32`	Opcode $20, register A, immediate mode, little-endian value.
`24 00 04 00 aa aa aa aa`	`STA A,M:addr32`	Opcode $24, register A, direct-memory mode, little-endian address.
`06 00 00 00 aa aa aa aa`	`JMP addr32`	Opcode $06; the Chapter 25 example jumps to its own address to keep the tone alive.

G.3 6502 (Chapter 26)

A, X, Y, S, P, PC. Addressing modes: implied, accumulator, immediate, zero-page (+ X, + Y), absolute (+ X, + Y), indirect, (indirect,X), (indirect),Y, relative.

Group	Mnemonics
Load / store	LDA, LDX, LDY, STA, STX, STY.
Transfer	TAX, TAY, TXA, TYA, TSX, TXS.
Arith / log	ADC, SBC, AND, ORA, EOR, BIT, CMP, CPX, CPY.
Inc / dec	INC, DEC, INX, INY, DEX, DEY.
Shift	ASL, LSR, ROL, ROR.
Branch	BCC, BCS, BEQ, BNE, BMI, BPL, BVC, BVS.
Jump / sub	JMP, JSR, RTS, RTI.
Flag	CLC, SEC, CLD, SED, CLI, SEI, CLV.
Stack	PHA, PLA, PHP, PLP.
System	BRK, NOP.
Undoc	LAX, SAX, DCP, ISC, RLA, RRA, SLO, SRE, ANC, ARR, ASR, AXS, XAA.

Flag register P: bit 0 C, 1 Z, 2 I, 3 D, 4 B, 5 -, 6 V, 7 N (silicon convention used by this chip).

Byte-entry crib for Chapter 26:

Bytes	Meaning	Hand-entry note
`A9 nn`	`LDA #nn`	Immediate load into accumulator.
`8D ll hh`	`STA $hhll`	Absolute store; address operand is low byte then high byte.

Bytes	Meaning	Hand-entry note
`4C ll hh`	`JMP $hhll`	Absolute jump; the Chapter 26 example jumps to its own address to leave POKEY sounding.

G.4 Z80 (Chapter 27)

Main: `A,F,B,C,D,E,H,L`; alt: `A',F',B',C',D',E',H',L'`; index: `IX`, `IY`; refresh / interrupt: `I`, `R`; stack: `SP`. Prefixes: `CB` (bit / rotate), `ED` (extended), `DD` / `FD` (IX / IY).

Group	Mnemonics
8-bit load	`LD r, r'`, `LD r, n`, `LD r, (HL)`, `LD r, (IX+d)`, `LD A, (BC)/(DE)/(nn)`.
16-bit load	`LD rp, nn`, `LD rp, (nn)`, `LD (nn), rp`, `PUSH rp`, `POP rp`.
Block	`LDI`, `LDIR`, `LDD`, `LDDR`, `CPI`, `CPIR`, `CPD`, `CPDR`.
Arith / log	`ADD`, `ADC`, `SUB`, `SBC`, `AND`, `OR`, `XOR`, `CP`, `INC`, `DEC`.
16-bit ALU	`ADD HL,rp`, `ADC HL,rp`, `SBC HL,rp`, `ADD IX,rp`, `ADD IY,rp`.
Rotate / shift	`RLCA`, `RLA`, `RRCA`, `RRA`, `RLC`, `RL`, `RRC`, `RR`, `SLA`, `SRA`, `SRL`, `SLL` (undoc).
Bit	`BIT b,r`, `SET b,r`, `RES b,r`.
Jump / call	`JP`, `JR`, `CALL`, `RET`, with condition codes `NZ`, `Z`, `NC`, `C`, `PO`, `PE`, `P`, `M`. `DJNZ`.
I/O	`IN A,(n)`, `IN r,(C)`, `OUT (n),A`, `OUT (C),r`, `INI`, `OUTI`, `INIR`, `OTIR`, `IND`, `OUTD`, `INDR`, `OTDR`.
Interrupt	`EI`, `DI`, `IM 0`, `IM 1`, `IM 2`, `RETI`, `RETN`.
Misc	`NOP`, `HALT`, `EX`, `EXX`, `DAA`, `CPL`, `NEG`, `CCF`, `SCF`.

Flag register: `S`, `Z`, `Y` (bit 5 undoc), `H`, `X` (bit 3 undoc), `P/V`, `N`, `C`.

Byte-entry crib for Chapter 27:

Bytes	Meaning	Hand-entry note
`3E nn`	`LD A,nn`	Immediate load into accumulator.
`32 ll hh`	`LD ($hhll),A`	Direct memory store; address operand is low byte then high byte.
`D3 pp`	`OUT (pp),A`	Immediate port output; Chapter 27 uses PSG ports `$F0` and `$F1`.
`C3 ll hh`	`JP $hhll`	Absolute jump; address operand is low byte then high byte.

G.5 M68K (MC68020-Class, Chapter 28)

`D0-D7`, `A0-A7`, `PC`, `SR`. CCR low byte: X N Z V C. Big-endian, byte-addressable, full 32-bit client path on the Intuition Engine bus.

Group	Mnemonics
Move	`MOVE`, `MOVEA`, `MOVEM`, `MOVEP`, `MOVEQ`, `EXG`, `SWAP`, `LEA`, `PEA`.
Arith	`ADD`, `ADDA`, `ADDI`, `ADDQ`, `ADDX`, `SUB`, `SUBA`, `SUBI`, `SUBQ`, `SUBX`, `NEG`, `NEGX`, `CMP`, `CMPA`, `CMPI`, `CMPM`, `CLR`, `EXT`, `EXTB`.
Mul / div	`MULU`, `MULS`, `DIVU`, `DIVS`; MC68020 long forms `MULU.L`, `MULS.L`, `DIVUL`, `DIVSL`.

Group	Mnemonics
Logical	AND, ANDI, OR, ORI, EOR, EORI, NOT.
Shift / rot	ASL, ASR, LSL, LSR, ROL, ROR, ROXL, ROXR.
Bit	BTST, BSET, BCLR, BCHG.
Bit field	BFTST, BFSET, BFCLR, BFCHG, BFEXTS, BFEXTU, BFINS, BFFFO.
Branch	BRA, BSR, Bcc (HI, LS, CC, CS, NE, EQ, VC, VS, PL, MI, GE, LT, GT, LE), DBcc, Scc, JMP, JSR, RTS, RTR, RTD.
BCD	ABCD, SBCD, NBCD.
Multiprocessor	TAS, CAS, CAS2.
System	TRAP #n, TRAPV, CHK, CHK2, STOP, RESET, ILLEGAL, NOP, LINK, UNLK, MOVE USP, MOVEC, MOVES, BKPT, RTE.
FPU	68881-style FMOVE, FADD, FSUB, FMUL, FDIV, FSQRT, FABS, FNEG, FCMP, FTST, FBcc, FDBcc, FScc, FMOVEM, and control-register moves.
Line A/F	unassigned opcode trap.

Byte-entry crib for Chapter 28:

Bytes	Meaning	Hand-entry note
`13 FC 00 vv aa aa aa aa`	`MOVE.B #vv,$aaaaaaaa`	Opcode and extension words are big-endian; the byte immediate sits in the low byte of the `$00vv` extension word.
`60 00 dd dd`	`BRA.W disp16`	Signed big-endian displacement from the following word; Chapter 28 uses `$FFFE` for a self-loop.

G.6 x86 (Chapter 29, 8086 base + 386 extensions)

EAX, EBX, ECX, EDX, ESI, EDI, EBP, ESP, plus 16-bit and 8-bit subregisters. Segments CS, DS, ES, FS, GS, SS. Real-mode only.

Group	Mnemonics
Move	MOV, MOVZX, MOVSX, LEA, XCHG, XLAT, PUSH, POP, PUSHA, POPA, PUSHAD, POPAD, PUSHF, POPF, PUSHFD, POPFD.
Arith	ADD, ADC, SUB, SBB, INC, DEC, CMP, NEG, MUL, IMUL, DIV, IDIV, DAA, DAS, AAA, AAS, AAM, AAD, CBW, CWD, CWDE, CDQ.
Logical	AND, OR, XOR, NOT, TEST.
Shift / rot	SHL, SHR, SAR, SAL, ROL, ROR, RCL, RCR, SHLD, SHRD.
Bit	BT, BTS, BTR, BTC, BSF, BSR, SETcc.
Branch	JMP, Jcc (JE, JNE, JL, JG, JLE, JGE, JB, JA, JBE, JAE, JO, JNO, JS, JNS, JP, JNP, JCXZ, JECXZ), CALL, RET, RETF, LOOP, LOOPE, LOOPNE, INT n, INTO, IRET.
String	MOVS, CMPS, SCAS, LODS, STOS, INS, OUTS, prefixes REP, REPE, REPNE.
I/O	IN, OUT.
Flag	STC, CLC, CMC, STD, CLD, STI, CLI, LAHF, SAHF.
Segment	LDS, LES, LFS, LGS, LSS.
System	HLT, WAIT, NOP, ESC, LOCK.
386 extras	BSWAP, MOVSX, MOVZX, dword forms of 16-bit ops via 66h / 67h prefixes.

Omitted (Chapter 29): all protected-mode opcodes (`LGDT`, `LIDT`, `LLDT`, `LTR`, `LMSW`, `SMSW`, `ARPL`, `LAR`, `LSL`, `VERR`, `VERW`, `STR`, `SLDT`), `CR` and `DR` register moves, `INVLPG`, `WBINVD`, `INVD`.

Byte-entry crib for Chapter 29:

Bytes	Meaning	Hand-entry note
`B0 nn`	`MOV AL,nn`	Immediate load into `AL`.
`A2 aa aa aa aa`	`MOV [addr32],AL`	Absolute store from `AL`; address operand is little-endian.
`EB dd`	`JMP SHORT disp8`	Signed displacement from the next byte; `$FE` loops to the jump instruction itself.