

Chapter 51 - One Effect, Six CPUs

The rotozoomer is a good comparison effect because the hardware job does not change. The VideoChip still owns Mode 7. The blitter still receives the same registers. The front buffer, texture, back buffer, and VBlank rhythm stay on the same bus. What changes is the CPU idiom.

51.1 The Common Contract

Every version must do these jobs:

1. Enable VideoChip.
2. Place or build a texture.
3. Start its chosen audio engine.
4. Advance angle and scale state.
5. Convert table values into six Mode 7 parameters.
6. Establish RGBA32 pixels and compatible COPY state.
7. Start the blitter.
8. Wait for completion and present the frame.

That is the contract. A CPU chapter teaches how to execute instructions. This chapter teaches what remains the same after the instruction set changes.

51.2 CPU Comparison

CPU	Rotozoomer idiom	Main lesson
IE64	Wide native registers and fixed instruction width.	Keep many addresses and fixed-point values live at once.
IE32	Compact RISC-style code with explicit fixed-point helpers.	A small native CPU can still drive the same MMIO contract.
6502	Banked access, byte arithmetic, helper routines.	Use the hardware blitter because software pixels are not practical.
Z80	Register pairs, table copies, banked ranges.	Keep the bus contract visible through the adapter.
M68K	Orthogonal addressing and 68020-class integer work.	Use clean longword MMIO writes and table arithmetic.
x86	Flat 32-bit addressing and signed multiply.	Use familiar integer instructions against IE's bus.

The table is not a ranking. It is a reading guide.

51.3 The Same Blitter Writes

Each CPU eventually performs this sequence:

```

BLT_OP          = 5
BLT_SRC         = texture address
BLT_DST         = back buffer address
BLT_WIDTH       = 640
BLT_HEIGHT      = 480
BLT_SRC_STRIDE  = 1024
BLT_DST_STRIDE  = 2560
VIDEO_COLOR_MODE = 0
BLT_FLAGS       = 0
BLT_MODE7_U0    = computed U origin
BLT_MODE7_V0    = computed V origin
BLT_MODE7_DU... = computed deltas
BLT_CTRL        = 1

```

The 6502 may reach those registers through an adapter. The Z80 may use its own mapped view. M68K and x86 may use absolute long addresses. The device is still the same VideoChip.

The standalone versions begin from reset state, where the colour mode and blitter flags are already zero. The 6502 and Z80 sources also write those values explicitly so an earlier CLUT8 or raster-operation setting cannot leak into Mode 7. That explicit setup is the safer pattern when the effect is part of a larger programme.

51.4 Different Audio Choices

The shipped rotozoomers deliberately vary the sound engine. The point is the same as the video comparison: the audio engines are cards on the same machine.

CPU version	Example audio path
IE64	POKEY/SAP-style playback path.
IE32	AHX playback path.
6502	PSG/AY playback path.
Z80	SID-style path through the shared audio block.
M68K	TED playback path.
x86	PSG playback path.

The CPU does not have to mix samples itself. It starts an audio engine and returns to video work.

51.5 Reading A Port

When reading a port to another CPU, use this order:

1. Find the constants: framebuffer, texture, back buffer, stride.
2. Find the initialisation: video mode, framebuffer base, audio start.
3. Find the table lookups: angle, scale, sine, reciprocal.
4. Find the six Mode 7 parameters.
5. Find the blitter-completion wait and presentation step.
6. Find the accumulator advance.

Only after that should you study the CPU-specific tricks.

The IE64, IE32, 6502, Z80, M68K, and x86 versions render into an off-screen buffer, wait for completion, wait for a VBlank edge, and change VIDEO_FB_BASE. This is different from copying a back buffer into the displayed framebuffer. The VBlank edge is a presentation point, not a guarantee that every loop sustains 60 frames per second.

The 6502 and Z80 versions load their texture through the File I/O device. Their names are resolved beneath the guest File I/O root described in Chapter 35.

51.6 What The Comparison Proves

The six versions are not six separate machines. They are six views of one shared hardware contract. If you understand the BASIC version and the Mode 7 register block, you can read every port by asking one question:

How does this CPU compute and write the same six values?

Chapter 52 returns to BASIC and makes the source texture move before Mode 7 sees it.