

Appendix I - Error Message Index

The printable errors a running Intuition Engine produces. Grouped by source. Each entry has the exact text the machine prints, the numeric code the runtime uses internally, and a one-line explanation.

I.1 EhBASIC runtime errors

The format on the screen is the message text, a space, the literal word `ERROR`, then (when raised from a running program rather than from direct mode) `IN` followed by the line number.

Code	Printed text	Meaning
1	SYNTAX	The tokeniser or parser cannot make sense of the statement.
2	DIVISION BY ZERO	A /, \, or MOD operator saw a zero denominator.
3	UNDEFINED LINE	GOTO, GOSUB, THEN, or RESTORE referenced a line that does not exist.
4	NEXT WITHOUT FOR	NEXT did not match a pending FOR.
5	RETURN WITHOUT GOSUB	RETURN did not match a pending GOSUB.
6	OUT OF MEMORY	The program, variable, array, or string area is full.
7	ILLEGAL QUANTITY	A function received an argument outside its domain (negative <code>SQR</code> , non-positive <code>LOG</code> , out-of-range <code>CHR\$</code>).
8	OVERFLOW	An arithmetic operation overflowed the 32-bit floating-point range.
9	TYPE MISMATCH	A numeric expression saw a string, or vice versa.
10	FC	Illegal function call. Raised by <code>POKE</code> to an unaligned address, by a failed <code>HOST</code> action, and by other built-in helpers when they reject their argument shape.
11	REDIM	<code>DIM</code> named an array that already exists.

Additional message strings produced by specific verbs:

Verb context	Printed text
LOAD	?FILE NOT FOUND.
SAVE	?FILE ERROR (printed as a soft error; <code>SAVE</code> does not raise into the runtime).

I.2 Machine monitor (IE Mon)

The monitor prints short, lowercase-prefixed messages. Every unrecognised command prints `unknown command`. The common ones:

Printed text	Meaning
?	Generic syntax error in a monitor command line.
unknown command	The first token did not name a command.
bad address	An address argument was outside the addressable range.

Printed text	Meaning
bad range	An end address was lower than its start address.
bad value	A value argument did not parse as a number.
no breakpoint at <addr>	bc was given an address with no breakpoint.
breakpoint list full	The breakpoint table cannot hold another entry.
cpu frozen	An operation tried to step a frozen CPU; thaw it first.
file error	A save or load sidecar command failed.

The monitor's h (hunt) and c (compare) commands print addresses of matches rather than diagnostic messages. The disassembler prints ??? for an unknown opcode.

I.3 File I/O block

When the File I/O block (Chapter 35) fails, FILE_STATUS reads 1 and FILE_ERROR_CODE is one of:

Code	Meaning
0	OK (paired with FILE_STATUS = 0).
1	Not found.
2	Permission.
3	Path traversal.

For a read whose name passes path validation but whose file cannot be opened, FILE_RESULT_LEN is cleared to 0. A program should still test FILE_STATUS first and then read FILE_ERROR_CODE.

I.4 HOST appliance block

The status byte at \$F1408 (Chapter 36) reads one of:

Code	Meaning
0	Running.
1	OK (terminal).
2	Error (terminal).
3	Cancelled by user (terminal).
4	Disabled (the system-action bridge is off).
5	Idle (no command has been fired).

A non-zero exit code at \$F140C after a terminal status of 2 gives the underlying action's exit value; the meaning is action-specific and is not normalised across subverbs.

I.5 RUN loader block

The RUN loader block (RUN "<name>", Chapter 35) reports status:

Code	Meaning
0	Idle.
1	Loading.
2	Running.
3	Error.

On error, the error register reports:

Code	Meaning
0	OK.
1	Not found.
2	Unsupported type.
3	Path invalid.
4	Load failed.

RUN translates a non-zero result into ?FILE ERROR for the file-error cases and ?FC ERROR for the unsupported cases.

I.6 Media loader

The media loader (SOUND PLAY, Chapter 23) reports status:

Code	Meaning
0	Idle.
1	Loading.
2	Playing.
3	Error.

On error, MEDIA_ERROR reports:

Code	Meaning
0	OK.
1	File not found.
2	Bad format or read failure.
3	Unsupported extension.
4	Invalid filename.
5	File too large for the staging buffer.

For MIDI/MUS, bad SMF headers, unsupported SMF type 2, SMPTE timing, bad MUS score ranges, and unsupported MUS event types all report as bad format.

I.7 Coprocessor

COSTATUS (Chapter 32) reports:

Code	Constant	Meaning
0	COPROC_TICKET_PENDING	Queued, not yet started.
1	COPROC_TICKET_RUNNING	Worker is processing.
2	COPROC_TICKET_OK	Completed successfully.
3	COPROC_TICKET_ERROR	Worker returned an error.
4	COPROC_TICKET_TIMEOUT	Wait deadline expired.
5	COPROC_TICKET_WORKER_DOWN	Worker is no longer running.

COWAIT blocks until the ticket reaches a terminal state or the timeout expires; call `COSTATUS(ticket)` afterwards to read the final code.

I.8 Raised by the CPU itself

Per CPU, the chapter (Ch 25-30) lists the trap and exception vectors and their meanings. The monitor's `r` command displays the current trap source when a CPU has stopped at one. Common cross-CPU shapes:

- Division by zero raises the CPU's divide-by-zero exception on M68K (vector 5) and x86 (INT 0). IE32 stops with a division-by-zero error. IE64 integer divide and modulo by zero write 0 and do not trap; IE64 floating-point divide-by-zero is reported in the FPU status register.
- An unaligned 32-bit access on the IE64 raises an alignment fault; the address that caused it is in CR_FAULT_ADDR.
- An undefined opcode raises the CPU's illegal-instruction vector (M68K vector 4, x86 INT 6, Z80 silently re-executes on most undocumented prefixes, 6502 documents the undocumented opcodes - see Chapter 27).