

Design Overlay

Columns: 1- 74

Control Source overlay STATIONERY
*...+...1...+...2...+...3...+...4...+...5...+...6...+...7...
001
002
003
004
005 %L002 -----
006
007
008
009
010
011
012

Define Line

More...

Mark : *L002
Start position . . Across 19 Down 5
End position . . Across 50 Down 5

F3=Exit F4=Detail F6=Change measurement method
F12=Cancel F24=More keys

The following table explains each field in this display.

Field Name	Description
Control	You can move the list view window by entering one of the following commands in this field and pressing Enter. -n Backward The image area moves n lines toward the top line of the overlay, the record layout, or the page layout. +n Forward The image area moves n lines toward the bottom line of the overlay, the record layout, or the page layout. W-n Left The image area moves n columns toward the first column of the overlay, the record layout, or the page layout. W+n Right The image area moves n columns toward the last column of the overlay, the record layout, or the page layout. n The image area moves to the nth line. Wn The image area moves to the nth column. *TOP The image area moves to the top line. *BOT The image area moves to the bottom line.
Mark	The element mark is displayed in this field. It could be either a system-assigned mark or a user-assigned name.
Measurement method	This field shows the measurement method used to specify the position. You may change this field by pressing the F6 key.
Start position	The position parameter consists of across and down values. These values specify the horizontal and vertical start position of the element being defined.