

FaceStation F2

Fusion Multimodal Terminal

Product Specification



Category	Feature	FSF2-DB	FSF2-AB	FSF2-ODB
Credential	Biometric	Face		Face, Fingerprint
	RF Option	125kHz EM & 13.56MHz MIFARE, MIFARE Plus, DESFire EV1/EV2/EV3 ⁽¹⁾ , FeliCa	125kHz EM, HID Prox & 13.56MHz MIFARE, MIFARE Plus, DESFire EV1/EV2/EV3 ⁽¹⁾ , FeliCa, iCLASS SE/SR/Seos	125kHz EM & 13.56MHz MIFARE, MIFARE Plus, DESFire EV1/EV2/EV3 ⁽¹⁾ , FeliCa
	RF Read Range ⁽²⁾	EM/MIFARE/DESFire : 50 mm (2"), FeliCa: 30 mm (1.2")		
	Mobile	NFC, BLE		
General	CPU	1.8 GHz Dual Core + 1.4 GHz Quad Core		
	Memory	16GB Flash + 2GB RAM		
	Crypto Chip	Supported		
	LCD Type	7" IPS color LCD		
	LCD Resolution	800 x 1280 pixels		
	Sound	16 bit		
	Operating Temperature	-20°C ~ 50°C (-4°F ~ 122°F)		
	Operating Humidity	0% ~ 80%, non-condensing		
	Dimension (W x H x D, mm)	119.8 x 233 x 23.5 (4.7" x 9.1" x 0.9")		119.8 x 268.3 x 49.6 (4.7" x 10.5" x 1.9")
	Weight	Device	585g	670g
		Bracket (Including washer and bolt)	181g	205g
	Ingress Protection (IP)	IP65		
	Certificates	CE, FCC, KC, RoHS, REACH, WEEE		
Face	Recognition Distance	0.5m ~ 1.3m (19.7" ~ 51.2")		
	Recognition Height	140cm ~ 190cm (55.1" ~ 74.8")		
	Matching Speed	Less than 0.5 sec		
	Live Face Detection (Anti-Spoofing)	Supported		
Fingerprint	Image Dimension	N/A		300 x 400 pixels
	Resolution			500 dpi
	Template			SUPREMA / ISO19794-2, ANSI-378
	Extractor / Matcher			MINEX certified and compliant
	Sensor Certificates			FBI PIV and FBI Mobile ID FAP20
	Live Fingerprint Detection			Supported (SW-based)
Capacity	Max. User (1:1) * Based on one face/fingerprint enrollment per user	100,000		
	Max. User (1:N) * Based on one face/fingerprint enrollment per user	Face: 50,000		Face: 50,000 Fingerprint: 100,000
	Max. Text Log	5,000,000		
	Max. Image Log	50,000		
Interface	Ethernet	10/100 Mbps, auto MDI/MDI-X		
	RS-485	5ch		
	RS-485 Communication Protocol	OSDP V2 Compliant		
	Wiegand	1ch Input or Output (Selectable)		
	TTL Input	2ch Inputs		
	Relay	1 Relay		
	USB	USB 2.0 (Host)		
	Tamper	Supported		
Power		DC 12V 1.9A, DC 24V 1A * Use a DC 24V 1A adapter. Must follow the product manual when using a DC 12V adapter.		

⁽¹⁾ DESFire EV2/EV3 cards are supported by having backward compatibility of DESFire EV1 cards. CSN and smart card functions are compatible with FaceStation F2.

⁽²⁾ RF read range will vary depending on the installation environment.