

This is unreleased documentation for Serverpod **Next** version.

For up-to-date documentation, see the [latest version](#) (4.0.0).

3..55

CONFIGURATION REFERENCE

 Copy as Markdown

Configuration reference

Every configuration option Serverpod's core library reads. Options come from three sources: the `config/<run-mode>.yaml` files, environment variables, and the `ServerpodConfig` Dart object. Environment variables override the YAML files. If you pass a `ServerpodConfig` to the `Serverpod` constructor, the server ignores the YAML files and environment variables. Command-line options such as `--mode` still override the values in your `ServerpodConfig`. For how to choose between them, see [Configuration](#).

Run options

Set the run mode, server role, and boot behavior. Declare each per run mode in the matching `config/<mode>.yaml`, or as an environment variable.

Environment variable	Command line option	Config file option	Default	Description
SERVERPOD_RUN_MODE	<code>--mode</code>	N/A	development	Configures the mode of the server instance. Valid options are <code>development</code> , <code>staging</code> , <code>production</code> and <code>test</code> .
SERVERPOD_SERVER_ID	<code>--server-id</code>	serverId	default	Configures the id of the server instance.
SERVERPOD_SERVER_ROLE	<code>--role</code>	role	monolith	Configures the role of the server. Valid options are <code>monolith</code> , <code>serverless</code> and <code>maintenance</code> .



Environment variable	Command line option	Config file option	Default	Description
SERVERPOD_LOGGING_MODE	<code>--logging</code>	logging	normal	Configures the logging level. Valid options are <code>normal</code> , and <code>verbose</code> .
SERVERPOD_APPLY_MIGRATIONS	<code>--apply-migrations</code>	applyMigrations	false	Configures if migrations should be applied when the server starts.
SERVERPOD_APPLY_REPAIR_MIGRATION	<code>--apply-repair-migration</code>	applyRepairMigration	false	Configures if repair migrations should be applied when the server starts.

Server and services

Ports, hosts, and connection settings for the API, Insights, and web servers, the database, Redis, session logs, and future calls, plus a few options that exist only on the Dart config object or as environment variables.

Environment variable	Config file	Default	Description
SERVERPOD_API_SERVER_PORT	apiServer.port	8080	The port number for the API server
SERVERPOD_API_SERVER_PUBLIC_HOST	apiServer.publicHost	localhost	The public host address of the API server
SERVERPOD_API_SERVER_PUBLIC_PORT	apiServer.publicPort	8080	The public port number for the API server

Environment variable	Config file	Default	Description
SERVERPOD_API_SERVER_PUBLIC_SCHEME	apiServer.publicScheme	http	The public scheme (http/https) for the API server
SERVERPOD_INSIGHTS_SERVER_PORT	insightsServer.port	-	The port number for the Insights server
SERVERPOD_INSIGHTS_SERVER_PUBLIC_HOST	insightsServer.publicHost	-	The public host address of the Insights server
SERVERPOD_INSIGHTS_SERVER_PUBLIC_PORT	insightsServer.publicPort	-	The public port number for the Insights server
SERVERPOD_INSIGHTS_SERVER_PUBLIC_SCHEME	insightsServer.publicScheme	-	The public scheme (http/https) for the Insights server
SERVERPOD_INSIGHTS_SERVER_ENABLE_DATABASE_ACCESS	insightsServer.enableDatabaseAccess	false	Whether the Insights server serves the direct database access endpoints (used by custom service client tooling, not the Insights app)
SERVERPOD_WEB_SERVER_PORT	webServer.port	-	The port number for the Web server

Environment variable	Config file	Default	Description
SERVERPOD_WEB_SERVER_PUBLIC_HOST	webServer.publicHost	-	The public host address of the Web server
SERVERPOD_WEB_SERVER_PUBLIC_PORT	webServer.publicPort	-	The public port number for the Web server
SERVERPOD_WEB_SERVER_PUBLIC_SCHEME	webServer.publicScheme	-	The public scheme (http/https) for the Web server
SERVERPOD_WEB_SERVER_STATIC_CACHE_CONTROL	N/A	-	The <code>Cache-Control</code> header for <code>StaticRoute</code> responses without a <code>cacheControlFactory</code> . See Static files .
SERVERPOD_WEB_SERVER_SPA_CACHE_CONTROL	N/A	-	The <code>Cache-Control</code> header for <code>SpaRoute</code> responses without a <code>cacheControlFactory</code> . Never applies to the fallback file. See Single-page apps .
SERVERPOD_WEB_SERVER_FLUTTER_CACHE_CONTROL	N/A	-	The <code>Cache-Control</code> header for <code>FlutterRoute</code> responses without a <code>cacheControlFactory</code> . See Flutter web .
SERVERPOD_DATABASE_HOST	database.host	-	The host address of the database

Environment variable	Config file	Default	Description
SERVERPOD_DATABASE_PORT	database.port	-	The port number for the database connection
SERVERPOD_DATABASE_NAME	database.name	-	The name of the database
SERVERPOD_DATABASE_USER	database.user	-	The user name for database authentication
SERVERPOD_DATABASE_SEARCH_PATHS	database.searchPaths	-	The search paths used for all database connections
SERVERPOD_DATABASE_REQUIRE_SSL	database.requireSsl	false	Indicates if SSL is required for the database
SERVERPOD_DATABASE_IS_UNIX_SOCKET	database.isUnixSocket	false	Specifies if the database connection is a Unix socket
SERVERPOD_DATABASE_MAX_CONNECTION_COUNT	database.maxConnectionCount	10	The maximum number of connections in the database pool. Set to 0 or a negative value for unlimited connections.
N/A	database.filePath	-	The SQLite database file path. Set this instead of host/port/name/user when using SQLite. Config file only.

Environment variable	Config file	Default	Description
N/A	database.dialect	Inferred	The database dialect. Valid options are <code>postgres</code> and <code>sqlite</code> . When unset, a <code>filePath</code> selects SQLite, and host/port/name/user select PostgreSQL. Config file only.
SERVERPOD_DATABASE_DATA_PATH	database.dataPath	-	Directory for the embedded PostgreSQL cluster, relative to the server package unless absolute. When set, Serverpod starts or attaches to the cluster before connecting. PostgreSQL only; ignored for SQLite.
SERVERPOD_REDIS_HOST	redis.host	-	The host address of the Redis server
SERVERPOD_REDIS_PORT	redis.port	-	The port number for the Redis server
SERVERPOD_REDIS_USER	redis.user	-	The user name for Redis authentication
SERVERPOD_REDIS_ENABLED	redis.enabled	true	Indicates if Redis is enabled. Defaults to <code>true</code> when a <code>redis</code> section is present; Redis is off when the section is absent or <code>enabled</code> is <code>false</code> .
SERVERPOD_REDIS_REQUIRE_SSL	redis.requireSsl	false	Indicates if SSL is required for the Redis connection
SERVERPOD_MAX_REQUEST_SIZE	maxRequestSize	524288	The maximum size of API requests in bytes. Also caps file uploads that post to the API server.
SERVERPOD_VALIDATE_HEADERS	validateHeaders	true	Validate HTTP headers using the typed API. Set to <code>false</code> to accept headers without the required formatting, for example an unwrapped token in the Authorization header.

Environment variable	Config file	Default	Description
SERVERPOD_ALLOWED_ORIGINS	allowed Origins	-	Browser origins allowed to make credentialed cross-origin calls, as <code>scheme://host[:port]</code> . A YAML list, or comma-separated in the environment variable. Required when <code>authCookie</code> is set. When set, browser WebSocket connections for streaming from other origins are also rejected, with or without <code>authCookie</code> . See Web authentication .
SERVERPOD_AUTH_COOKIE_NAME	authCookie.name	-	Name of the auth cookie. Defaults to <code>serverpod_auth</code> . Setting any <code>authCookie</code> field enables cookie auth for web clients; an empty <code>authCookie</code> section is read as unset.
SERVERPOD_AUTH_COOKIE_REFRESH_NAME	authCookie.refreshName	-	Name of the JWT refresh cookie. Defaults to <code><name>_refresh</code> .
SERVERPOD_AUTH_COOKIE_DOMAIN	authCookie.domain	-	Cookie <code>Domain</code> attribute. Defaults to host-only; set to share the cookie across subdomains.
SERVERPOD_AUTH_COOKIE_PATH	authCookie.path	/	Cookie <code>Path</code> attribute.
SERVERPOD_AUTH_COOKIE_SECURE	authCookie.secure	true	Whether the cookie is only sent over https. Set to <code>false</code> only for <code>http://localhost</code> development.
SERVERPOD_AUTH_COOKIE_SAMESITE	authCookie.sameSite	lax	Cookie <code>SameSite</code> attribute. Valid options are <code>lax</code> , <code>strict</code> , and <code>none</code> (<code>none</code> requires <code>secure</code>).
SERVERPOD_SESSION_PERSISTENT_LOGS	sessionLogs.persistent	-	Enables or disables logging session data to the database. Defaults to <code>true</code> if a database is configured, otherwise <code>false</code> .

Environment variable	Config file	Default	Description
OG_ENABLE_D	rsistent Enabled		
SERVERPOD_SESSION_LOG_CLEANUP_INTERVAL	session Logs.cleanupInterval	-	How often to run the log cleanup job. Duration string, for example <code>24h</code> or <code>2d</code> . Set to null to disable automated purging. Defaults to <code>24h</code> only when <code>sessionLogs</code> is not configured at all. See Purge old records .
SERVERPOD_SESSION_LOG_RETENTION_PERIOD	session Logs.retentionPeriod	-	How long to keep session log entries. Duration string, for example <code>30d</code> or <code>60d</code> . Set to null to disable time-based cleanup. Defaults to <code>90d</code> only when <code>sessionLogs</code> is not configured at all. See Purge old records .
SERVERPOD_SESSION_LOG_RETENTION_COUNT	session Logs.retentionCount	-	Maximum number of session log entries to keep. Set to null to disable count-based cleanup. Defaults to <code>100000</code> only when <code>sessionLogs</code> is not configured at all. See Purge old records .
SERVERPOD_SESSION_CONSOLE_LOG_ENABLED	session Logs.consoleEnabled	-	Enables or disables logging session data to the console. Defaults to <code>true</code> if no database is configured or the run mode is <code>development</code> , otherwise <code>false</code> .
SERVERPOD_SESSION_CONSOLE_LOG_FORMAT	session Logs.consoleLogFormat	-	The format for console logging of session data. Valid options are <code>text</code> and <code>json</code> . Defaults to <code>text</code> for run mode <code>development</code> , otherwise <code>json</code> .
SERVERPOD_FUTURE_CALL_EXECUTION_ENABLED	futureCallExecutionEnabled	true	Enables or disables the execution of future calls.
SERVERPOD_FUTURE_CALL_CONCURRENCY	futureCallConcurrency	1	The maximum number of concurrent future calls allowed. If the value is negative or null, no limit is applied.

Environment variable	Config file	Default	Description
RRENCY_LIMIT	urrency Limit		
SERVERPOD_FUTURE_CALL_SCAN_INTERVAL	futureCall.scanInterval	5000	The interval in milliseconds for scanning future calls
SERVERPOD_FUTURE_CALL_CHECK_BROKEN_CALLS	futureCall.checkBrokenCalls	-	Enables or disables the automatic check for broken future calls on startup. By default, the server performs an automatic check if there are less than 1000 calls in the database.
SERVERPOD_FUTURE_CALL_DELETE_BROKEN_CALLS	futureCall.deleteBrokenCalls	false	Enables or disables the deletion of broken future calls when running the check on startup.
SERVERPOD_WEBSOCKET_PING_INTERVAL	websocketPingInterval	30	The interval in seconds between WebSocket ping messages sent to keep streaming connections alive. Must be a positive integer.

Dart-only options

These options have no environment variable or config-file key. Set them on the `ServerpodConfig` Dart object passed to the `Serverpod` constructor.

ServerpodConfig field	Default	Description
healthCheckInterval	1m	How often the server collects health metrics. Set to zero to disable health checks.

ServerpodConfig field	Default	Description
experimentalDiagnosticHandlerTimeout	30s	The timeout for diagnostic event handlers .

Password environment variables

Secrets are read from `config/passwords.yaml` and can be overridden per secret through environment variables; see [Manage secrets](#). Two forms exist, and when both are set for the same secret, the `SERVERPOD_PASSWORD_*` form wins:

Environment variable	Overrides passwords-file key
<code>SERVERPOD_PASSWORD_<name></code>	Any secret; the prefix is stripped (<code>SERVERPOD_PASSWORD_database</code> → <code>database</code>).
<code>SERVERPOD_DATABASE_PASSWORD</code>	database
<code>SERVERPOD_SERVICE_SECRET</code>	serviceSecret
<code>SERVERPOD_REDIS_PASSWORD</code>	redis

Code generation

Options for `config/generator.yaml`, which configures `serverpod generate`.

Option	Type	Default	Description
type	string	server	The package type. Valid options are <code>server</code> , <code>module</code> , or <code>internal</code> .
nickname	string	-	For modules only. Defines how the module is referenced in code.

Option	Type	Default	Description
client_package_path	string	../[name]_client	Path to the client package relative to the server.
server_test_tools_path	string	test/integration/test_tools	Path where test tools are generated. Remove this to disable test tools generation.
shared_packages	list	-	Paths to shared packages containing models usable by both server and client.
modules	map	-	Module dependencies with optional nicknames.
extraClasses	list	-	List of custom serializable classes to include in code generation.
serialize_as_jsonb_by_default	boolean	false	When true, all serializable fields default to <code>jsonb</code> storage instead of <code>json</code> .
features	map	{database: true}	Feature flags. Currently only <code>database</code> is supported.
experimental_features	map	-	Experimental features. Available keys: <code>databaseSync</code> (enables <code>database: sync</code>) and <code>all</code> .

Related

- [Configuration](#): how the three configuration sources work, run modes, secrets, and package types.
- [Redis](#): enabling Redis, the password, and connecting a GUI.
- [Running your server](#): the run mode and files the server loads on start.