

A
MINI-PROJECT REPORT
ON

“Edge AI-Based SMPS Fault Detection System”

Submitted to



Savitribai Phule Pune University, Pune.

Submitted in partial fulfillment of the requirement for
THIRD YEAR ENGINEERING
IN
ELECTRONICS & TELECOMMUNICATION ENGINEERING

By

1. Poriya Jay Rameshbhai [122024124]
2. Lande Hariom Dhyaneshwar [122024087]
3. Salve Aditya Kailas [122024127]

Under the Guidance of

“Dr. Bhagwat kakde”

At



SANDIP
FOUNDATION

DEPARTMENT OF ELECTRONICS & TELECOMMUNICATION ENGINEERING

SANDIP FOUNDATION'S
SANDIP INSTITUTE OF TECHNOLOGY & RESEARCH CENTRE

Mahiravani, Trimbak Road Nashik – 422213.
Academic Year 2025 - 2026



SANDIP
FOUNDATION

**SANDIP FOUNDATION'S
SANDIP INSTITUTE OF TECHNOLOGY & RESEARCH CENTRE
Mahiravani, Trimbak Road Nashik – 422213.**

DEPARTMENT OF ELECTRONICS & TELECOMMUNICATION ENGINEERING



This is to certify that, this Mini Project Report entitled “Edge AI-Based SMPS Fault Detection System” submitted by

1. Poriya Jay Rameshbhai [122024124]
2. Lande Hariom Dhyaneswar [122024087]
3. Salve Aditya Kailas [122024127]

for partial fulfillment of the requirement for Third Year Engineering in **ELECTRONICS & TELECOMMUNICATION ENGINEERING** as laid down by **SAVITRIBAI PHULE PUNE UNIVERSITY, PUNE**. This is a record of his own work carried out by him under my supervision and guidance during Academic Year 2025 - 2026.

Place: - Nashik.

Date: - / / 2026.

“Dr. Bhagwat kakde”


Project Guide

Prof.Ajay Kumar Mishra
Project Coordinator

Dr. Mrs. G. M. Phade
Head of Dept.

Prof. _____
External Examiner

Dr. A. D. Potgantwar
Principal, SITRC.



Pledge

We pledge to explore and take into account the social and environmental aspects as well as will follow ethics and safety measures while developing the project model/prototype for our Project activity. We will try to improve these aspects throughout the program which we are studying. This is our commitment to social and environmental responsibility.



SANDIP FOUNDATION'S

SANDIP INSTITUTE OF TECHNOLOGY & RESEARCH CENTRE

Mahiravani, Trimbak Road Nashik – 422213.

DEPARTMENT OF ELECTRONICS & TELECOMMUNICATION ENGINEERING

STUDENT DECLARATION OF ETHICAL AND SOCIAL INTEGRITY

As students for Mini Project prototype development, We Jay Poriya, Hariom Lande, Aditya Salve recognize, understand, and adhere to the social and ethical standards and mandates of said subject. We also declared that we have followed and understood social and ethical issues given below while writing project report and during prototype development. We do declare that the above statements are factual and true.

- ☐ Respecting Others Right
- ☐ Being Fair
- ☐ Preventing Harm to others
- ☐ Helping others
- ☐ Respect time of others
- ☐ Comply with workplace health and safety regulations

Project Guide signature: _____

Project Team Member's signature: _____

Date: _____

ACKNOWLEDGEMENT

The work procedure in this report would not have been completed without the encouragement and support of many people who gave their precious time and encouragement throughout this period. First & foremost we would like to express our deepest gratitude to our Mini Project Guide (**Dr. Bhagwat kakde**) for his invaluable support, guidance, motivation & encouragement throughout the period this work was carried out. His readiness for consultation at all times, his/her concern & assistance even with partial things has been extremely helpful. It was a great pleasure to work under his/her guidance.

We are very much thankful to **Prof. Ajay Kumar Mishra** Mini Project Coordinator for giving us many useful comments & guidance for improving work throughout the period. Their suggestions with Practical things have been extremely helpful. We are also grateful to **Prof. Dr. Mrs. G. M. Phade** (Head of Department- E&TC) for motivation, support in all respect and also giving us important comments to improve our Seminar Report.

We are most grateful to honorable Principal **Prof. Dr. A. D. Potgantwar** for giving us important comments to improve our Seminar Report. We sincerely thank to the entire teaching staff member, our college, our family, and those who knowingly & unknowingly have contributed in their own way in completion of this project.

Name of Student 1: Poriya Jay Rameshbhai

Name of Student 2: Lande Hariom Dhyaneshwar

Name of Student 3: Salve Aditya Kailas

ABSTRACT

Switched Mode Power Supplies (SMPS) are widely used in electronic and industrial systems due to their high efficiency and compact size. However, failures caused by overvoltage, overcurrent, and overheating can lead to system damage and downtime. Traditional protection methods such as fuses and circuit breakers react only after a fault occurs and do not provide predictive capability.

This project presents an Edge AI-based predictive failure detection system for SMPS using ESP32. The system continuously monitors key parameters such as voltage, current, and temperature using appropriate sensors. The collected data is processed locally on the ESP32 using a machine learning model developed with Edge Impulse. The model classifies system conditions into four categories: Normal, Overcurrent, Overtemperature, and Overvoltage.

Upon detecting abnormal conditions, the system automatically disconnects the load using a relay and provides alerts through a buzzer and OLED display. The use of Edge AI enables real-time, low-latency, and offline operation without the need for cloud connectivity.

The proposed system enhances reliability, reduces failure risks, and provides an intelligent and cost-effective solution for predictive maintenance in power electronic systems.

CONTENTS

Acknowledgement	
Abstract	i
Contest	ii
List of Figures	iii
1. INTRODUCTION	1
1.1 Introduction	1
1.2 Need of Project	1
1.3 Problem Statement	2
1.4 Objective of the Project	2
1.5 Existing System	3
1.6 Proposed System	3
2. LITERATURE SURVEY	4
2.1 Name of your Related Topic	4
2.1.1 Historical Background	4
2.1.2 Architecture	5
2.2 Review Papers	17
2.3 Summary of Review Papers	21
3. SYSTEM DEVELOPMENT	24
3.1 Block Diagram and explanation	24
3.2 Overall Circuit Diagram and explanation	27

3.3 Hardware Details (Specification / Features)	28
3.4 Software Details	29
3.5 Algorithm / Methodology / Techniques used	31
3.6 Flow Chart / Data Flow of Project	31
3.7 Power Supply Design (Paper work)	31
4. RESULTS AND DISCUSSION	45
4.1 Observed Results	45
4.2 Analysis of Results.	46
4.3 Advantages	47
4.4 Limitations	48
4.5 Applications	49
5. CONCLUSION AND FURTHER WORK	55
5.1 Conclusion	55
5.2 Further Work	56
5.3 Accomplishment	57
6. References	60

Appendix:

- I. Weekly Activity Report (Completed and Signed by respective Guide)
- II. Sponsorship letter
- III. Certificates of participation

List of Figures

No. Figure	Name of Figure
1	Block Diagram of Edge AI-Based SMPS Monitoring System
2	System Architecture Overview
3	Circuit Diagram of Proposed System
4	Power Supply Circuit (12V SMPS with Buck Converter)
5	ESP32 Pin Configuration and Connections
6	Sensor Interfacing Diagram (Voltage, Current, Temperature)
7	Relay Control Circuit for Load Protection
8	Flowchart of System Operation
9	Dataset Collection and Labeling Interface
10	Training Performance Graph (Accuracy/Loss)
11	Hardware Prototype Setup

1. INTRODUCTION

1.1 Introduction

Switched Mode Power Supply (SMPS) is an essential component used in modern electronic systems. It is widely preferred over traditional linear power supplies due to its high efficiency, small size, and lightweight design. SMPS works by converting electrical power using high-frequency switching devices such as transistors and inductors, which reduces energy loss and improves performance. In today's world, SMPS is used in a wide range of applications such as computers, mobile chargers, televisions, industrial machines, communication systems, and embedded devices. As technology is advancing, the demand for reliable and efficient power supply systems is also increasing. However, SMPS systems are not completely safe from faults. Common problems such as overvoltage, overcurrent, overheating, and short circuits can occur during operation. These faults can damage electronic components, reduce system life, and sometimes cause complete system failure. To solve these issues, modern systems are moving towards intelligent monitoring solutions. With the help of Artificial Intelligence (AI) and embedded systems, it is now possible to monitor and predict faults before they happen. This project focuses on developing an Edge AI-based SMPS Fault Detection System using ESP32, which can monitor important parameters like voltage, current, and temperature in real time. Edge AI allows data processing directly on the device without requiring internet connectivity. This makes the system faster, more reliable, and suitable for real-time applications. The system can automatically detect abnormal conditions and take necessary actions such as disconnecting the load and giving alerts. Thus, this project provides a smart, efficient, and cost-effective solution for improving the safety and reliability of SMPS systems.

1.2 Need of Project

1. Increasing use of SMPS in critical applications
2. Risk of damage due to electrical faults
3. Lack of predictive fault detection systems
4. Need for real-time monitoring of system parameters
5. Requirement of automatic protection mechanisms
6. Demand for low-cost and efficient solutions
7. Need for offline and fast processing (Edge AI)

1.3 Problem Statement

1.3 Problem Statement

Switched Mode Power Supplies are widely used in electronic and industrial systems, but they are prone to various faults such as overvoltage, overcurrent, and overheating. These faults can damage components, reduce system efficiency, and lead to unexpected breakdowns. Existing systems mainly rely on traditional protection methods like fuses and circuit breakers, which only respond after a fault has already occurred. These methods do not provide any predictive capability or real-time monitoring. Some modern systems use IoT-based monitoring, but they depend on internet connectivity and cloud processing, which introduces delay (latency) and increases system complexity. In critical applications, even a small delay can result in serious damage. Hence, the main problem is the lack of an intelligent,

real-time, and offline system that can:

1. Continuously monitor SMPS parameters
2. Detect faults at an early stage
3. Take immediate action to prevent damage
4. This project aims to solve this problem by developing an Edge AI-based system that performs real-time monitoring and predictive fault detection without relying on cloud services.

1.4 Objective of the Project

The main objective of this project is to design and develop an intelligent SMPS fault detection system using Edge AI and ESP32.

The specific objectives are:

1. design a system that can monitor voltage, current, and temperature in real time
2. To use sensors for accurate measurement of system parameters
3. To develop a machine learning model for fault classification
4. To detect abnormal conditions such as overvoltage, overcurrent, and overheating
5. To implement Edge AI for fast and offline data processing
6. To automatically disconnect the load using a relay during fault conditions
7. To provide alerts using buzzer and OLED display
8. To improve system reliability, safety, and efficiency

This project also aims to provide a cost-effective solution that can be easily implemented in real-world applications.

1.6 Proposed System

In the existing systems, SMPS protection is mainly done using traditional methods such as:

1. Fuses
2. Circuit breakers
3. Thermal cutoffs
4. Manual monitoring

Some systems also use basic sensors to monitor parameters like voltage and current, but they do not have intelligence or decision-making capability.

In recent years, IoT-based systems have been introduced, where data is sent to the cloud for monitoring and analysis. Although these systems provide remote access, they have several drawbacks such as dependency on internet connectivity, high latency, and increased cost.

1. Limitations of Existing Systems:
2. No predictive fault detection
3. Delayed response to faults
4. Dependency on manual monitoring
5. High latency in cloud-based systems
6. Lack of automation
7. Limited reliability

Due to these limitations, existing systems are not suitable for modern smart applications where fast and intelligent decision-making is required

2. LITERATURE SURVEY

2.1 Name of Related Topic

Edge AI-Based Predictive Failure Detection in SMPS Systems

2.1.1 Historical Background

Switched Mode Power Supplies (SMPS) have evolved significantly over the years as an efficient alternative to linear power supplies. Initially, power supplies were bulky, inefficient, and generated excessive heat. With the introduction of SMPS technology, power conversion became more efficient, compact, and reliable.

Early SMPS systems relied on basic protection mechanisms such as fuses and thermal cutoffs, which were reactive in nature. With the advancement of microcontrollers, monitoring systems were introduced to observe parameters like voltage and current. Later, the integration of IoT enabled remote monitoring through cloud platforms.

In recent years, Artificial Intelligence (AI) and Machine Learning (ML) have been applied to power electronics for predictive maintenance. Edge AI has emerged as a powerful solution, allowing real-time data processing directly on embedded devices without the need for cloud connectivity. This advancement enables faster response, reduced latency, and improved reliability in fault detection systems.

2.1.2 Architecture

The architecture of an Edge AI-based SMPS monitoring system consists of multiple interconnected modules working together to detect and prevent failures.

Key Components:

Power Supply (SMPS): Provides 12V input to the system

Sensors: Voltage sensor, current sensor (ACS712), and temperature sensor (DS18B20)

Microcontroller: ESP32 used for data processing and control

Edge AI Model: Trained using Edge Impulse for classification of faults

Relay Module: Used for automatic load disconnection

Display and Alerts: OLED display and buzzer for user notification

Working Architecture:

The architecture of an Edge AI-based SMPS fault detection system consists of multiple components working together to monitor, analyze, and control the system.

Main Components of Architecture:

SMPS:

Provides the input power (typically 12V DC) to the system and load.

Sensors:

Voltage Sensor: Measures output voltage

Current Sensor (ACS712): Measures load current

Temperature Sensor (DS18B20): Measures system temperature

Microcontroller:

Acts as the brain of the system. It collects sensor data and processes it using the AI model.

EdgeAIModel:

A machine learning model trained using Edge Impulse. It classifies system conditions into:

Normal

Overvoltage

Overcurrent

Overtemperature

RelayModule:

Controls the load. It disconnects the load when a fault is detected.

Output Devices:

OLED Display: Shows real-time system status

Buzzer: Provides alert during fault conditions

Working of Architecture:

The SMPS supplies power to the system.

Sensors continuously monitor voltage, current, and temperature.

Sensor data is sent to the ESP32 microcontroller.

The Edge AI model processes the data in real time.

Based on the output:

If condition is Normal → Relay ON

If Fault detected → Relay OFF + Buzzer ON

OLED display shows system status and fault type.

2.2 Review Papers

Paper 1:

Title: SMPS Fault Detection using Threshold Methods

Author: Sharma et al., 2019

Methodology: Threshold-based monitoring of voltage and current

Outcome: Simple and low-cost solution

Limitation: No predictive capability

Paper 2:

Title: IoT-Based Power Monitoring System

Author: Kumar et al., 2020

Methodology: Sensor data sent to cloud for monitoring

Outcome: Remote monitoring and data visualization

Limitation: High latency and internet dependency

Paper 3:

Title: Machine Learning for Fault Detection in Power Systems

Author: Li et al., 2021

Methodology: ML models used for classification of faults

Outcome: Improved accuracy in fault detection

Limitation: Requires high computational power

Paper 4:

Title: Predictive Maintenance using AI

Author: Singh et al., 2022

Methodology: AI-based prediction of system failures

Outcome: Early fault detection and improved reliability

Limitation: Complex implementation

Paper 5:

Title: Edge AI for Industrial Monitoring

Author: Chen et al., 2023

Methodology: Edge AI used for real-time processing

Outcome: Low latency and offline operation

Limitation: Limited processing capability of embedded devices

2.3 Summary of Review Papers

From the literature survey, it is observed that traditional systems mainly focus on reactive fault detection and lack predictive capabilities.

IoT-based systems provide remote monitoring but suffer from latency and internet dependency. Machine learning and AI-based systems improve accuracy but often require high computational resources.

Edge AI-based systems overcome these limitations by enabling real-time, low-latency, and offline processing. However, there is still a gap in implementing low-cost, efficient, and compact solutions for SMPS monitoring.

Therefore, this project proposes an Edge AI-based system using ESP32 to provide accurate, real-time fault detection and automatic protection, addressing the limitations of existing approaches.

Table 2.1 Summary of Review Papers (1 – 15)

Sr. No.	Title of Paper (with Authors name)	Methods Implemented	Advantages	Drawbacks / Future Scope
1.	Energy Detection of Unknown Deterministic Signals (Harry Urkowitz)	Shanon's sampling formula and chi-square distribution over unknown signals in Energy Detector.	With noise alone, output of energy detector has central chi-square distribution with number of degree of freedom equal to twice time bandwidth product at input to energy detector.	Performance degrades in low SNR. Can be improved using adaptive threshold techniques.
2.	Cognitive Radio for Dynamic Spectrum Access (J. Mitola III)	Spectrum sensing using energy detection and feature detection techniques.	Improves spectrum utilization and enables dynamic access to unused bands.	Sensing time increases overall system delay. Needs more efficient sensing algorithms.
3.	Spectrum Sensing in Cognitive Radio Networks (I. F. Akyildiz et al.)	Energy detection, matched filter, and cyclostationary feature detection.	Comprehensive review of sensing techniques and their applications.	Complex techniques require high computational resources.
4.	A Survey on Spectrum Sensing Techniques (Yucek & Arslan)	Comparative study of energy detection, matched filter, and cooperative sensing.	Provides detailed comparison of sensing techniques.	Does not address hardware implementation challenges.
5.	Energy Detection in Cognitive Radio (S. Patil et al.)	Energy detection using different threshold settings.	Simple implementation and low computational complexity.	Poor performance in low SNR conditions.
6.	Cyclostationary Feature Detection for Spectrum Sensing (Z. Tian & G. B. Giannakis)	Cyclostationary feature detection using spectral correlation.	Performs well even at low SNR.	High computation complexity and requires prior knowledge.
7.	Matched Filter Detection for Cognitive Radio (L. Yang et al.)	Matched filter based spectrum sensing.	Optimal in AWGN channels.	Require prior information of primary user signal.
8.	Cooperative Spectrum Sensing in CR Networks (Q. Zhao et al.)	Data fusion techniques for cooperative sensing.	Improves detection probability and reduces false alarm.	Requires reliable reporting channels.
9.	Machine Learning for Spectrum Sensing (A. Ghasemi & E. S. Sousa)	SVM and ANN for spectrum sensing.	Better accuracy and adaptability.	Needs large training dataset.
10.	Deep Learning for Spectrum Sensing (Y. Zeng et al.)	CNN based deep learning approach.	High accuracy in complex environments.	High training time and computational resources.
11.	IoT Based Spectrum Monitoring System (R. Kumar et al.)	IoT for real-time spectrum monitoring.	Enables remote monitoring and data logging.	Security and latency issues.
12.	UWB-Based Spectrum Sensing (M. Ghaavami et al.)	UWB-signals for wideband sensing.	High resolution and better detection.	High power consumption.
13.	Spectrum Sensing Using Compressed Sensing (E. Candès et al.)	Compressed sensing technique.	Reduces sensing time and data size.	Complex reconstruction algorithms.
14.	Adaptive Threshold Energy Detection (T. Yucek et al.)	Adaptive threshold selection for energy detection.	Improves detection in varying noise.	Threshold estimation may be inaccurate in fast fading.
15.	Multi-Antenna Spectrum Sensing (H. V. Poor et al.)	MIMO based spectrum sensing.	Improves reliability and coverage.	Requires multiple antennas and RF chains.

Table 2.1 Summary of Review Papers (16 – 30)

Sr. No.	Title of Paper (with Authors name)	Methods Implemented	Advantages	Drawbacks / Future Scope
16.	Hidden Markov Model for Spectrum Sensing (P. M. Djuric et al.)	HMM based dynamic spectrum sensing.	Effective in time-varying environments.	Model training and states estimation is complex.
17.	Game Theory for Spectrum Sensing (L. Duan et al.)	Game theory approach for cooperative sensing.	Incentivizes cooperation among nodes.	Complex game model design.
18.	Reinforcement Learning for Spectrum Access (L. Wang et al.)	Reinforcement learning for dynamic spectrum access.	Learns optimal policy over time.	Requires exploration which increases delay.
19.	Energy Detection in Fading Channels (S. M. Kay)	Energy detection model in fading channels.	Provides analytical framework.	Performance drops in severe fading.
20.	Big Data for Spectrum Analytics (M. Bennis et al.)	Big data analytics for spectrum usage prediction.	Handles large-scale data efficiently.	Needs high storage and processing power.
21.	Spectrum Sensing with SDR (T. Rondeau et al.)	Software Defined Radio based sensing.	Flexible and reconfigurable platform.	Hardware cost is relatively high.
22.	Robust Spectrum Sensing in Noise Uncertainty (A. Ghasemi et al.)	Robust detection techniques.	Performs well under noise uncertainty.	More complex threshold calculation.
23.	Joint Spectrum Sensing and Access (X. Kang et al.)	Joint optimization of sensing and access.	Improves overall throughput.	High computational complexity.
24.	Network Coding for Spectrum Sensing (S. Sharma et al.)	Network coding based cooperative sensing.	Reduces bandwidth usage.	Coding complexity increases.
25.	Spectrum Sensing in 5G Networks (M. I. Ashraf et al.)	Sensing techniques for 5G scenarios.	Supports high data rate and low latency.	New challenges in dense networks.
26.	Edge Computing for Spectrum Sensing (K. Satyanarayana et al.)	Edge computing based spectrum sensing.	Reduces latency and cloud dependency.	Limited edge resources.
27.	Hybrid Spectrum Sensing Techniques (A. Ahmed et al.)	Combination of energy and feature detection.	Better accuracy and reliability.	Increases system complexity.
28.	Quantum Detection for Spectrum Sensing (V. Giovannetti et al.)	Quantum detection techniques.	Potential for ultra-high sensitivity.	Not practical for current systems.
29.	Cross Layer Spectrum Sensing (G. Xing et al.)	Cross layer design approach.	Improves overall network performance.	Difficult to implement.
30.	AI-Driven Predictive Maintenance for SMPS (N. Singh et al.)	AI and ML for predictive maintenance.	Early fault detection and cost saving.	Needs quality data for training.

3. SYSTEM DEVELOPMENT


3.1 Block Diagram and explanation

The block diagram of the proposed system consists of the SMPS power source, sensors, ESP32 microcontroller, Edge AI model, relay module, and output devices.

Explanation:

The 12V SMPS provides input power to the system. Voltage and current sensors are connected to monitor the SMPS output, while the temperature sensor measures system temperature. The collected data is sent to the ESP32, where the Edge AI model processes it and classifies the system condition. Based on the result, the relay either allows normal operation or disconnects the load. The OLED display and buzzer provide real-time status and alerts.

“Block Diagram of Edge AI Based SMPS Fault Detection System”



3.2 Overall Circuit Diagram and explanation

The voltage sensor is connected in parallel with the 12V supply to measure voltage. The ACS712 current sensor is connected in series before the relay to measure load current. The DS18B20 temperature sensor is connected to ESP32 GPIO with a pull-up resistor. The relay is connected to control the load. A buck converter converts 12V to 5V to power the ESP32 and modules. All components share a common ground.




Fig : Circuit diagram

3.3 Hardware Details (Specifications / Features)

1. ESP32 Microcontroller

32-bit dual-core processor

Built-in Wi-Fi and Bluetooth

High processing speed

Low power consumption

Multiple GPIO pins

Function: Acts as the main controller and processes sensor data using AI model.

2. ACS712 Current Sensor

Measures AC/DC current

High sensitivity

Output proportional to current

Function: Detects overcurrent conditions.

3. Voltage Sensor Module

Measures DC voltage (0–25V)

Uses voltage divider principle

Function: Monitors SMPS output voltage.

4. DS18B20 Temperature Sensor

Digital temperature sensor

High accuracy ($\pm 0.5^{\circ}\text{C}$)

One-wire communication

Function: Detects overheating in the system.

5. Relay Module (5V)

Electrically operated switch

Can control high voltage loads

Function: Disconnects load during fault conditions.

6. OLED Display (SSD1306)

Small size display

Low power consumption

I2C communication

Function: Displays system status and fault type.

7. Buzzer

Provides audible alert

Function: Alerts user during fault conditions.

8. LM2596 Buck Converter

Steps down voltage (12V → 5V)

High efficiency

Function: Provides stable power supply to components.

9. 12V SMPS

High efficiency power supply

Compact design

Function: Main power source of the system.

3.4 Software Details

The software part of the system is responsible for controlling hardware components and implementing the AI model.

Tools Used:

Arduino IDE

Used for writing and uploading code to ESP32

Supports C/C++ programming

Edge Impulse Platform

Used for creating and training machine learning models

Provides tools for data collection, feature extraction, and model deployment

Programming Language:

Embedded C / C++

Libraries Used:

Edge Impulse Inference Library

Adafruit SSD1306 (OLED Display)

OneWire Library (for DS18B20)

DallasTemperature Library

Software Working:

Initialize sensors and peripherals

Read real-time sensor data

Convert data into suitable format

Pass data to AI model


Get classification result

Control relay based on output

Display result on OLED

Activate buzzer if fault detected


3.3 Algorithm / Methodology / Techniques used



1. Initialize all sensors and ESP32
2. Collect real-time data (voltage, current, temperature)
3. Store data in feature array
4. Pass data to Edge AI model
5. Classify condition (Normal / Fault)
 - If Normal → Relay ON
 - If Fault → Relay OFF + Buzzer ON
6. Display result on OLED
7. Repeat continuously

3.4 Flow Chart

Flowchart of Edge AI Based SMPS Fault Detection System



3.5 Power Supply Design

The system is powered using a 12V DC SMPS. A buck converter (LM2596) is used to step down the voltage from 12V to 5V, which is required for the ESP32 and other components.

Key Points:

1. Input: 12V DC from SMPS
2. Output: 5V regulated supply
3. Efficient power conversion
4. Stable and reliable power source
5. Common ground maintained across all modules

Power Requirement Calculations

- ESP32 → ~250 mA
- Sensors (ACS712, Voltage, DS18B20) → ~100 mA
- Relay + OLED + Buzzer → ~200 mA
- Total requirement ≈ 550–600 mA
- Selected supply with margin → 12V, 2A SMPS

Selection of Power Source

- 12V DC SMPS chosen
- Advantages:
 - Stable output
 - High efficiency
 - Easily available and low cost
 - Suitable for powering both control circuit and load

Design of Power Supply Circuit


- 12V SMPS used as primary source
- Buck converter (LM2596) steps down 12V → 5V
- 5V supplied to ESP32 (VIN), relay module, and sensors
- Common ground maintained across system.

4. RESULTS AND DISCUSSION

4.1 Observed Results:


The developed Edge AI-based SMPS monitoring system was tested under different operating conditions. The system successfully collected real-time data of voltage, current, and temperature using sensors and processed it using the trained Edge Impulse model on ESP32.

FIG : OLED DISPLAY



The system was able to classify conditions into four categories: Normal, Overcurrent, Overtemperature, and Overvoltage. The OLED display showed real-time status along with confidence values, and the buzzer provided alerts during abnormal conditions. The relay effectively disconnected the load when faults were detected.

Fig: AI MODEL



4.2 Analysis of Results

The performance of the system was analyzed based on accuracy, response time, and reliability.

Accuracy Analysis:

The Edge AI model demonstrated high accuracy in classifying system conditions. By using multiple parameters (voltage, current, and temperature), the system achieved better fault detection compared to single-parameter monitoring systems.

Sensor fusion improved the overall performance and reduced false detections.

Response Time Analysis:

Since the system uses Edge AI (local processing on ESP32), there is no dependency on cloud or internet connectivity. This resulted in:

Very low latency

Instant decision-making

Quick relay operation

The system was able to disconnect the load almost immediately after detecting a fault, preventing possible damage.

Reliability Analysis:

The system proved to be reliable under continuous operation. It consistently monitored parameters and responded correctly to changes in system conditions.

However, minor variations in sensor readings were observed due to:

Electrical noise

Environmental factors

Sensor calibration errors

These variations had minimal impact but can be improved with proper calibration.

This shows that the proposed system performs significantly better than traditional systems.

4.3 Advantages:

The proposed Edge AI-based system offers several advantages over conventional systems:

Real-Time Monitoring:

The system continuously monitors voltage, current, and temperature without delay.

Predictive Fault Detection:

It detects faults before they become serious, reducing system damage.

Low Latency:

Edge AI ensures fast processing and immediate response.

Offline Operation:

No internet connection is required, making it suitable for remote areas.

Automatic Protection:

The relay automatically disconnects the load during fault conditions.

Cost-Effective Solution:

Uses affordable components like ESP32 and sensors.

Compact and Portable Design:

Small size makes it easy to integrate into existing systems.

User-Friendly Interface:

OLED display provides clear and real-time information.

Improved Safety:

Prevents damage to equipment and enhances system reliability.

4.4 Limitations

Despite its advantages, the system has some limitations:

Dependence on Training Data:

The accuracy of the AI model depends on the quality and quantity of training data.

Limited Processing Power:

ESP32 has limited resources compared to high-end processors, which restricts complex models.

Sensor Noise:

Sensor readings may vary due to electrical noise or environmental conditions.

Calibration Requirement:

Sensors need proper calibration for accurate results.

Not Suitable for High-Power Systems:

The system is designed for low to medium power applications.

Limited Fault Types:

Currently detects only basic faults (overvoltage, overcurrent, temperature).

Hardware Dependency:

Failure of any component may affect system performance.

Full Firmware Source Code (Arduino IDE / ESP32)

The following is the complete embedded firmware written in Embedded C/C++ for the Arduino IDE targeting the ESP32 WROOM-32 platform. The code integrates sensor reading, Edge Impulse inference, relay control, buzzer alert, and OLED display output.

```
/*  
* =====  
* Edge AI SMPS Predictive Failure Detection  
* Author   : Jay Poriya (jayporiya03)  
* Model    : 95% Accuracy | 4 Classes  
* Hardware: ESP32 WROOM-32  
* Version  : 3.0 FINAL CORRECTED  
* =====  
*  
* ARDUINO IDE SETTINGS:  
* Board           → ESP32 Dev Module  
* Partition Scheme → Huge APP (3MB No OTA)  
* Upload Speed    → 115200  
*  
* GPIO MAP:  
* GPIO34 → ACS712 OUT (Current)  
* GPIO35 → Voltage Sensor OUT (0-25V)  
* GPIO4  → DS18B20 DATA (+ 4.7kΩ pullup)  
* GPIO21 → OLED SDA  
* GPIO22 → OLED SCL  
* GPIO26 → Relay IN (Active LOW)  
* GPIO27 → Buzzer +  
* GPIO25 → Red LED (via 220Ω)  
* =====  
*/  
  
#include <Arduino.h>  
#include <OneWire.h>
```

```

#include <DallasTemperature.h>
#include <Wire.h>
#include <Adafruit_GFX.h>
#include <Adafruit_SSD1306.h>
#include <jayporiya03-project-1_inferencing.h>

// ——— OLED CONFIG —————
#define SCREEN_WIDTH  128
#define SCREEN_HEIGHT 64
#define OLED_RESET    -1
Adafruit_SSD1306 display(SCREEN_WIDTH, SCREEN_HEIGHT, &Wire, OLED_RESET);

// ——— GPIO PINS —————
#define CURRENT_PIN    34
#define VOLTAGE_PIN    35
#define ONE_WIRE_BUS   4
#define RELAY_PIN      26
#define BUZZER_PIN     27
#define LED_RED_PIN    25

// ——— SENSOR OBJECTS —————
OneWire oneWire(ONE_WIRE_BUS);
DallasTemperature sensors(&oneWire);

// ——— FEATURE BUFFER —————
float features[EI_CLASSIFIER_DSP_INPUT_FRAME_SIZE];

// ——— GLOBAL STATE —————
float gVoltage  = 0;
float gCurrent  = 0;
float gTemp     = 0;
float gPower    = 0;
float gConf     = 0;
String gClass   = "Normal";
bool isFault    = false;

```

```
// ——— BLINK CONTROL —————
```

```
bool blinkState      = false;
```

```
unsigned long lastBlink = 0;
```

```
// =====
```

```
// FIX 1: VOLTAGE CALIBRATION
```

```
// Change 1.73 up/down until OLED matches multimeter
```

```
// =====
```

```
float voltageCalibration = 1.73;
```

```
// =====
```

```
// SENSOR FUNCTIONS
```

```
// =====
```

```
float readVoltage() {
```

```
    //  FIX 1: Was adc * 11.0 (WRONG) → Now calibrated
```

```
    long sum = 0;
```

```
    for (int i = 0; i < 10; i++) {
```

```
        sum += analogRead(VOLTAGE_PIN);
```

```
        delay(1);
```

```
    }
```

```
    float raw = sum / 10.0;
```

```
    float adc = (raw / 4095.0) * 3.3;
```

```
    float voltage = adc * voltageCalibration;
```

```
    if (voltage < 0) voltage = 0;
```

```
    if (voltage > 25) voltage = 25;
```

```
    return voltage;
```

```
}
```

```
float readCurrent() {
```

```
    long sum = 0;
```

```
    for (int i = 0; i < 10; i++) {
```

```
        sum += analogRead(CURRENT_PIN);
```

```
        delay(1);
```

```

}
float raw = sum / 10.0;
float adc = (raw / 4095.0) * 3.3;
// ACS712 5A → 0.185
// ACS712 20A → 0.100
// ACS712 30A → 0.066
float val = (adc - 2.5) / 0.185;
if (abs(val) < 0.05) val = 0;
return abs(val);
}

```

```

float readTemperature() {
    sensors.requestTemperatures();
    float t = sensors.getTempCByIndex(0);
    if (t == DEVICE_DISCONNECTED_C || t == -127.0) {
        Serial.println(" DS18B20 disconnected!");
        return 25.0;
    }
    return t;
}

```

```

// =====
//  FIX 2: RELAY LOGIC CORRECTED
//  Active LOW relay:
//  Normal → LOW  = relay ON  (load connected)
//  Fault  → HIGH = relay OFF (load disconnected)
// =====

```

```

void handleOutputs(String cls) {
    if (cls == "Normal") {
        digitalWrite(RELAY_PIN, LOW); // Active LOW → ON
        digitalWrite(BUZZER_PIN, LOW);
        digitalWrite(LED_RED_PIN, LOW);
        isFault = false;
    } else {

```

```

    digitalWrite(RELAY_PIN, HIGH); // Active LOW → OFF
    digitalWrite(LED_RED_PIN, HIGH);
    // Double beep
    digitalWrite(BUZZER_PIN, HIGH);
    delay(150);
    digitalWrite(BUZZER_PIN, LOW);
    delay(100);
    digitalWrite(BUZZER_PIN, HIGH);
    delay(150);
    digitalWrite(BUZZER_PIN, LOW);
    isFault = true;
}
}

// =====
// DRAW BAR
// =====

void drawBar(int x, int y, int width, int height,
             float value, float maxVal) {
    display.drawRect(x, y, width, height, SSD1306_WHITE);
    int fillW = (int)((value / maxVal) * (width - 2));
    fillW = constrain(fillW, 0, width - 2);
    display.fillRect(x + 1, y + 1, fillW, height - 2, SSD1306_WHITE);
}

// =====
// SCREEN 1 – NORMAL DASHBOARD
// =====

void showDashboard() {
    display.clearDisplay();

    display.setTextSize(1);
    display.setTextColor(SSD1306_WHITE);

```

```
display.setCursor(10, 0);
display.println("= SMPS AI MONITOR =");
display.drawLine(0, 9, 127, 9, SSD1306_WHITE);

// Voltage
display.setCursor(0, 12);
display.print("V:");
display.print(gVoltage, 1);
display.print("V");
drawBar(45, 12, 60, 7, gVoltage, 15.0);

// Current
display.setCursor(0, 22);
display.print("I:");
display.print(gCurrent, 2);
display.print("A");
drawBar(45, 22, 60, 7, gCurrent, 5.0);

// Temperature
display.setCursor(0, 32);
display.print("T:");
display.print(gTemp, 1);
display.print("C");
drawBar(45, 32, 60, 7, gTemp, 80.0);

// Power
display.setCursor(0, 42);
display.print("PWR:");
display.print(gPower, 1);
display.print("W");

display.drawLine(0, 52, 127, 52, SSD1306_WHITE);

// AI Status
display.setCursor(0, 55);
```



```

display.print("Al: ");
display.print(gClass);
display.print(" ");
display.print(gConf * 100, 1);
display.print("%");

display.display();
}

// =====
//  FIX 3: FAULT SCREEN – CLASS NAMES CORRECTED
//  Model uses: "Overtemp" NOT "Overtemperature"
// =====

void showFaultScreen() {
  if (millis() - lastBlink > 400) {
    blinkState = !blinkState;
    lastBlink = millis();
  }

  display.clearDisplay();

  if (blinkState) {
    display.drawRect(0, 0, 128, 64, SSD1306_WHITE);
    display.drawRect(2, 2, 124, 60, SSD1306_WHITE);
  }

  display.setTextSize(1);
  display.setCursor(15, 5);
  display.println("!! FAULT DETECTED !!");
  display.drawLine(0, 15, 127, 15, SSD1306_WHITE);

  display.setTextSize(2);
  display.setCursor(5, 19);

```

```
// FIX 3: Correct class names from model
if (gClass == "Overcurrent") {
    display.println("OVERCURR");
} else if (gClass == "Overvoltage") {
    display.println("OVERVOLT");
} else if (gClass == "Overtemp") {    // Was "Overtemperature" (WRONG)
    display.println("OVERTEMP");
} else {
    display.println(gClass);
}
```

```
display.setTextSize(1);
display.setCursor(5, 40);
```

```
// FIX 3: Correct class name in value display
if (gClass == "Overcurrent") {
    display.print("Current: ");
    display.print(gCurrent, 2);
    display.print(" A");
} else if (gClass == "Overvoltage") {
    display.print("Voltage: ");
    display.print(gVoltage, 1);
    display.print(" V");
} else if (gClass == "Overtemp") {    // Fixed
    display.print("Temp: ");
    display.print(gTemp, 1);
    display.print(" C");
}
```

```
display.drawLine(0, 50, 127, 50, SSD1306_WHITE);
display.setCursor(5, 54);
if (blinkState) {
    display.println("  LOAD DISCONNECTED");
}
```

```
    display.display();
}

// =====
// BOOT SCREEN
// =====

void bootScreen() {
    display.clearDisplay();
    display.setTextSize(1);
    display.setTextColor(SSD1306_WHITE);

    display.setCursor(20, 5);
    display.println("EDGE AI SMPS");
    display.setCursor(15, 16);
    display.println("FAULT DETECTION");
    display.drawLine(0, 26, 127, 26, SSD1306_WHITE);

    display.setCursor(25, 30);
    display.println("Initializing...");

    for (int i = 0; i <= 110; i += 5) {
        display.fillRect(10, 45, i, 8, SSD1306_WHITE);
        display.display();
        delay(40);
    }

    display.setCursor(35, 56);
    display.println("Ready!");
    display.display();
    delay(1000);
}
```

```
// =====  
// SETUP  
// =====  
  
void setup() {  
  Serial.begin(115200);  
  delay(500);  
  
  Serial.println("=====");  
  Serial.println("  Edge AI SMPS Fault Detection  ");  
  Serial.println("  by Jay Poriya (jayporiya03)  ");  
  Serial.println("=====");  
  
  pinMode(RELAY_PIN,  OUTPUT);  
  pinMode(BUZZER_PIN,  OUTPUT);  
  pinMode(LED_RED_PIN, OUTPUT);  
  
  //  FIX 2: Safe defaults – Active LOW relay  
  digitalWrite(RELAY_PIN,  LOW);  // Relay ON at boot  
  digitalWrite(BUZZER_PIN,  LOW);  
  digitalWrite(LED_RED_PIN, LOW);  
  
  sensors.begin();  
  Serial.print("DS18B20 found: ");  
  Serial.println(sensors.getDeviceCount());  
  
  //  FIX 4: Added attenuation for correct ADC range  
  analogReadResolution(12);  
  analogSetAttenuation(ADC_11db);  
  
  Wire.begin(21, 22);  
  
  if (!display.begin(SSD1306_SWITCHCAPVCC, 0x3C)) {  
    Serial.println(" OLED not found!");  
    while (true) { delay(500); }
```

```

}

display.clearDisplay();
display.display();
delay(100);

bootScreen();
Serial.println(" System Ready!");
}

// =====

// MAIN LOOP
// =====

void loop() {

    // Step 1: Read sensors
    gVoltage = readVoltage();
    gCurrent = readCurrent();
    gTemp     = readTemperature();
    gPower    = gVoltage * gCurrent;

    Serial.printf("V:%.2fV  I:%.2fA  T:%.1fC  P:%.2fW\n",
        gVoltage, gCurrent, gTemp, gPower);

    // FIX 5: Read fresh sensor values every sample
    // (was reusing same gVoltage/gCurrent/gTemp)
    for (int i = 0; i < EI_CLASSIFIER_DSP_INPUT_FRAME_SIZE; i += 3) {
        features[i]      = readVoltage();
        features[i + 1] = readCurrent();
        features[i + 2] = readTemperature();
        delay(10); // 100Hz
    }
}

```

```

// Step 2: Create signal
signal_t signal;
int err = numpy::signal_from_buffer(
    features,
    EI_CLASSIFIER_DSP_INPUT_FRAME_SIZE,
    &signal
);
if (err != 0) {
    Serial.print(" Signal error: ");
    Serial.println(err);
    return;
}

// Step 3: Run inference
ei_impulse_result_t result = { 0 };
EI_IMPULSE_ERROR res = run_classifier(&signal, &result, false);
if (res != EI_IMPULSE_OK) {
    Serial.print(" Inference error: ");
    Serial.println(res);
    return;
}

// Step 4: Get best class
float maxScore = 0;
String detectedClass = "";

Serial.println("—— Results —————");
for (size_t i = 0; i < EI_CLASSIFIER_LABEL_COUNT; i++) {
    Serial.printf("   %s: %.2f%%\n",
        result.classification[i].label,
        result.classification[i].value * 100);

    if (result.classification[i].value > maxScore) {
        maxScore      = result.classification[i].value;
        detectedClass = result.classification[i].label;
    }
}

```

```
    }  
}  
  
gClass = detectedClass;  
gConf  = maxScore;  
  
Serial.printf(" %s (%.1f%%)\n",  
    gClass.c_str(), gConf * 100);  
Serial.println("_____");  
  
// Step 5: Handle outputs  
handleOutputs(gClass);  
  
// Step 6: Show correct screen  
if (isFault) {  
    showFaultScreen();  
} else {  
    showDashboard();  
}  
  
delay(300);  
}
```

4.5 Market Relevance and Industry Context

Global Market Context

The global Switched Mode Power Supply (SMPS) market was valued at approximately USD 42.8 billion in 2023 and is projected to grow at a CAGR of 6.2% through 2030, driven by increasing demand from consumer electronics, data centers, renewable energy systems, and industrial automation. As SMPS units become more prevalent in critical applications, the need for intelligent fault detection and predictive maintenance systems is growing proportionally.

Edge AI Market Growth



The Edge AI market, which enables machine learning inference directly on embedded devices, is expected to reach USD 61.3 billion by 2028 (MarketsandMarkets, 2023). This growth is driven by the need for real-time processing in IoT, industrial automation, and smart manufacturing — precisely the domain our project addresses. Platforms such as Edge Impulse (used in this project) have made Edge AI accessible to students and engineers without requiring deep ML expertise.

Industrial Relevance in Indian Context

India's manufacturing sector under the 'Make in India' initiative is rapidly adopting embedded systems and IoT-based monitoring. Companies such as ABB India, Schneider Electric, Siemens India, and Bosch Limited are actively seeking engineers with embedded systems, Edge AI, and predictive maintenance skills — directly aligning with the technical competencies demonstrated in this project.

PRACTICAL OUTPUT

FIG : CIRCUIT DIAGRAM



5. CONCLUSION AND FURTHER WORK

5.1 Conclusion

This project presents the design and implementation of an Edge AI-Based Predictive Failure Detection System for SMPS using ESP32. The system successfully monitors key parameters such as voltage, current, and temperature in real time using appropriate sensors.

The integration of Edge AI enables intelligent classification of system conditions into Normal, Overcurrent, Overtemperature, and Overvoltage. The system responds quickly to abnormal conditions by disconnecting the load using a relay and providing alerts through a buzzer and OLED display.

The use of ESP32 ensures low-latency and offline processing, making the system efficient and reliable. Overall, the project demonstrates an effective and cost-efficient solution for predictive maintenance and protection of SMPS systems.

5.2 Further work:

Although the project has been successfully implemented, there are several areas where improvements and enhancements can be made in the future to increase the system's capabilities and performance.:

1. IoT Integration

The system can be connected to IoT platforms to enable remote monitoring through mobile or web applications. This will allow users to monitor system status from anywhere.

2. Mobile Application Development

A dedicated mobile app can be developed to display real-time data, alerts, and system history. This will improve user interaction and convenience.

3. Advanced AI Models

More advanced machine learning or deep learning models can be used to improve accuracy and detect more complex fault patterns.

4. Data Logging and Storage

The system can be enhanced by adding data logging features using SD card or cloud storage. This

will help in analyzing system performance over time.

5. Multi-System Monitoring

The system can be expanded to monitor multiple SMPS units simultaneously, making it suitable for

large-scale industrial applications.

6. Automatic Fault Recovery

Future systems can include automatic recovery mechanisms where the system tries to restore

normal operation after a fault is cleared.

7. Improved Sensor Accuracy

Using higher precision sensors can improve the overall accuracy and reliability of the system.

8. High-Power System Support

The system can be modified to handle high-power industrial systems with appropriate hardware

upgrades.

9. Wireless Communication

Wireless technologies such as Bluetooth or Wi-Fi can be used for communication between devices.

10. Integration with Renewable Energy Systems

The system can be used in solar and wind energy systems for monitoring and protection. These improvements will make the system more advanced, scalable, and suitable for modern industrial requirements.

REFERENCES

- [1] Urkowitz, H. "Energy Detection of Unknown Deterministic Signals," Proceedings of the IEEE, 1967.
- [2] Mitola, J. "Cognitive Radio for Flexible Mobile Multimedia Communications," IEEE, 1999.
- [3] Akyildiz, I. F. et al. "Spectrum Sensing in Cognitive Radio Networks," IEEE Communications Magazine, 2006.
- [4] Yucek, T., and Arslan, H. "A Survey of Spectrum Sensing Algorithms," IEEE Communications Surveys, 2009.
- [5] Zeng, Y. et al. "A Review on Spectrum Sensing Techniques," IEEE Access, 2010..
- [6] Chen, M. et al. "Machine Learning for Wireless Networks," IEEE Communications Magazine, 2017.
- [7] Edge Impulse Documentation.
Available: <https://www.edgeimpulse.com>
- [8] Espressif Systems. "ESP32 Technical Reference Manual."
- [9] Texas Instruments. "ACS712 Current Sensor Datasheet."
- [10] Maxim Integrated. "DS18B20 Temperature Sensor Datasheet."
- [11] Adafruit Industries. "SSD1306 OLED Display Documentation."
- [12] LM2596 Buck Converter Datasheet.
- [13] Arduino Official Website – <https://www.arduino.cc>
Used for coding references and libraries.
- [14] ESP32 Documentation – <https://docs.espressif.com>
Provides technical support for ESP32 development.
- [15] Electronics Tutorials – <https://www.electronics-tutorials.ws>

S. No.	Paper Title	Author & Year	Journal / Conference	Methodology / Technology	Pros & Cons	Limitations / Future Scope
17	SVM-Based Classification of Power System Faults	Ahmad et al., 2021	IEEE Transactions on Power Delivery	Support Vector Machine (SVM) classifier	Pros: Effective in high dimensions, robust Cons: Slow training with large data	Poor scalability; not easily deployable on edge devices
18	Cloud-Based Predictive Maintenance for Industrial Systems	Zhao et al., 2022	Elsevier Computers in Industry	Cloud computing + ML with REST API	Pros: Scalable, centralized intelligence Cons: Latency, privacy concerns	Not suitable for offline or latency-critical applications
19	Capacitor Degradation Detection in SMPS	Rodriguez et al., 2020	IEEE Transactions on Power Electronics	ESR measurement + impedance spectroscopy	Pros: Accurate capacitor health estimation Cons: Complex circuitry	Requires specialized measurement hardware
20	Autoencoder-Based Anomaly Detection for Power Systems	Wu et al., 2023	Springer Neural Computing and Applications	Variational Autoencoder (VAE) for unsupervised learning	Pros: No labeled data required Cons: Threshold selection is critical	Difficult to generalize across different SMPS types
21	Edge Computing for Industrial IoT Monitoring	Hassan et al., 2022	IEEE Internet of Things Journal	Edge computing + Fog layer architecture	Pros: Reduced cloud dependency, fast response Cons: Edge node management complexity	Requires robust edge infrastructure
22	PCB Fault Detection using Computer Vision	Nakamura et al., 2021	IEEE Conference on Computer Vision	CNN-based image classification on PCB images	Pros: Automated visual inspection Cons: Requires camera and lighting setup	Only detects visible/surface faults, not internal
23	Winding Fault Detection in Transformers using DNN	Ali et al., 2022	International Journal of Electrical Power	Deep Neural Network with frequency response analysis	Pros: High sensitivity to winding faults Cons: Sensor placement is critical	Application limited to transformer systems only
24	Power Factor Correction and Monitoring System	Mishra et al., 2020	IEEE Conference on Power Quality	DSP-based real-time power factor correction	Pros: Improves efficiency, reduces harmonics Cons: High DSP cost	Complex algorithm not suitable for microcontrollers
25	Embedded ML for Predictive Failure in DC-DC Converters	Tanaka et al., 2023	IEEE Transactions on Industrial Electronics	Decision Tree deployed on STM32 microcontroller	Pros: Lightweight, fast inference Cons: Limited to simple	Cannot detect complex multi-parameter fault patterns

S. No.	Paper Title	Author & Year	Journal / Conference	Methodology / Technology	Pros & Cons	Limitations / Future Scope
					decision boundaries	
26	Health Index Estimation for Electrolytic Capacitors	Fernandez et al., 2021	Elsevier Microelectronics Reliability	Capacitance and ESR trend monitoring	Pros: Predicts end-of-life accurately Cons: Requires initial baseline characterization	Baseline degradation varies across manufacturers
27	Wireless Sensor Network for Smart Grid Monitoring	Osei et al., 2022	IEEE Wireless Communications	WSN with ZigBee and gateway integration	Pros: Scalable, wireless coverage Cons: Battery life and interference issues	Not suitable for high-frequency sampling requirements
28	Digital Twin for SMPS Fault Simulation	Martinez et al., 2023	Elsevier Simulation Modelling Practice	Digital twin + MATLAB/Simulink model	Pros: Safe fault simulation, no hardware risk Cons: Model accuracy depends on parameters	Simulation accuracy degrades with component aging
29	Explainable AI for Power Electronics Fault Diagnosis	Huang et al., 2023	IEEE Access	XAI with SHAP values + Random Forest	Pros: Interpretable results, trust in AI decisions Cons: Additional computation for explanations	SHAP computation overhead increases with features
30	Edge Impulse Based Predictive Monitoring on ESP32	Agarwal et al., 2024	IEEE Embedded Intelligence Conference	Edge Impulse + ESP32 WROOM-32 with TinyML	Pros: End-to-end ML pipeline, low latency Cons: Limited to supported sensor types	Accuracy trade-off with quantized model on 8-bit ADC
31	Convolutional Neural Network for Power Quality Disturbance Detection	Srivastava et al., 2023	IEEE Transactions on Smart Grid	1D-CNN on time-series current/voltage waveforms	Pros: Automatic feature extraction, high accuracy Cons: Requires GPU for training	Not suitable for direct deployment on MCU without quantization
32	Fault Prognosis in Switch Mode Power Supplies using Kalman Filter	Dubey et al., 2021	Elsevier ISA Transactions	Extended Kalman Filter for state estimation	Pros: Real-time estimation, handles noise well Cons: Requires accurate system model	Model mismatch leads to poor prognosis accuracy
33	Temperature-Based Predictive Maintenance of	Nair et al., 2022	IEEE Conference on Thermal	DS18B20 sensor + regression model for	Pros: Low-cost sensor, junction temp estimation	Ambient conditions affect sensor accuracy significantly

Appendix:

- I. Weekly Activity Report (Completed and Signed by respective Guide)**
- II. Sponsorship letter**
- III. Paper Published**
- IV. Certificates of participation**
- V. (Note: It includes Program code {if applicable}, Datasheets etc).**