



API Description

1. Access Control

1.1 Get access token

1.1.1 Description

Client(distributor's server) should stored the access_token locally, do NOT get access_token per request, instead, use the local access_token before it become invalid. JIMI server will not allow to access if the request frequency is too high from client.

Note:

The access token can be used for about 2 hours(depend on the value for expires_in parameter), do NOT try to get token for every request.

1.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.oauth.token.get

1.1.3 HTTP Request method

POST

1.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Name	Type	Required	Description	Remark	Default
user_id	String	Yes	User ID	User's account	
user_pwd_md5	String	Yes	user's password (md5)		Lowercase md5 value.
expires_in	number	Yes	access token expired seconds.	60-7200	

1.1.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other failure: Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Object	Result

Result

key	Type	Description
accessToken	string	access token, required by any other following interfaces.
expiresIn	string	access token expired seconds.
account	string	user's account.
appKey	string	appKey from JIMI.
refreshToken	string	Refresh token, which is used for updating accessToken
time	string	Token generated time.

Correct return example:

```
{
  "code": 0,
  "message": "success",
  "result": {
    "appKey": "8FB345B8693CCD003CC2DAB61EC8791D",
    "account": "jimitest",
    "accessToken": "7da3330ec28e3996b6ef4a7e3390ba71",
    "expiresIn": 60,
    "refreshToken": "7da3330ec28e3996b6ef4a7e3390ba71",
    "time": "2017-06-15 10:00:00"
  }
}
```

Return error example:

```
{
  "code": "xxx",
  "message": "Incorrect user name or password"
}
```

Postman demo:

POST https://hk-open.tracksolidpro.com/route/rest Send

Params Authorization Headers (10) **Body** Scripts Settings The URL depends on the node where your account is located Cookies

☐ none ☐ form-data ☒ x-www-form-urlencoded ☐ raw ☐ binary ☐ GraphQL

	Key	Value	Description	...	Bulk Edit
☒	method	jimi.oauth.token.get			
☒	user_id	JMTEST123	your ts/tsp account		
☒	user_pwd_md5	21218cca77804d2ba1922c33e0151105	md5(your ts/tsp account password)		
☒	expires_in	7200			
☒	app_key	8FB345B8693CCD00CE073CAB5F094009339A...			
☒	sign	4EE067D88EA65FF2AFD4890955E042CB	sign=md5(<app_secret>your alphabet ordered parameters keyvalue, without equal-sign, comma and not include sign field<app_secret>)		
☒	sign_method	md5			
☒	v	1.0			
☒	timestamp	2025-05-19 10:23:00	please convert your local time to 0-timezone		
☒	format	json			

Note:

Here is the Open API account information required for your integration work:

```

account:JMTEST123
password:21218cca77804d2ba1922c33e0151105
appKey:8FB345B8693CCD00CE073CAB5F094009339A22A4105B6558
appSecret:c0aa0226fddc4365a3c67fef45427f8a

```

⚠ user_id = your tracksolid account.

⚠ user_pwd_md5 = md5(your tracksolid account password).

⚠ Sign = md5(<app_secret>your alphabet ordered parameters keyvalue, without equal-sign, comma and not include sign field<app_secret>).

```

<app_secret>app_key<app_key>expires_in<expires_in>formatjsonmethodjimi.oauth.token.getsign
_methodmd5timestamp<timestamp>user_id<account>user_pwd_md5<password_md5>v1.0<app_secret>

```

⚠ Note that sign is a 32-length upper case string.

For example:

1. Replace the content in <> with your account information, and you will get a string like this :

```

c0aa0226fddc4365a3c67fef45427f8aapp_key8FB345B8693CCD00CE073CAB5F094009339A22A4105B6558exp
ires_in7200formatjsonmethodjimi.oauth.token.getsign_methodmd5timestamp2025-05-19
10:23:00user_idJMTEST123user_pwd_md521218cca77804d2ba1922c33e0151105v1.0c0aa0226fddc4365a3c
67fef45427f8a

```

2. Sign =

```

md5(c0aa0226fddc4365a3c67fef45427f8aapp_key8FB345B8693CCD00CE073CAB5F0940
09339A22A4105B6558expires_in7200formatjsonmethodjimi.oauth.token.getsign_methodmd
5timestamp2025-05-19
08:10:00user_idJMTEST123user_pwd_md521218cca77804d2ba1922c33e0151105v1.0c0aa02
26fddc4365a3c67fef45427f8a)

```

```

4EE067D88EA65FF2AFD4890955E042CB

```

1.2 Refresh access token

1.2.1 Description

This interface is used to update token manually when access token is about to be invalid.

1.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.oauth.token.refresh

1.2.3 HTTP Request method

POST

1.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Description	Remark	Default
access_token	String	YES	Access token		
refresh_token	String	YES	Authorized refresh access token		
expires_in	number	YES	access token expired seconds	60 - 7200	

1.2.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Object	result

result

key	Type	Description
accessToken	string	Access token, required for subsequently interface access.
expiresIn	string	Access token expired seconds.
account	string	Requested account
appKey	string	From JIMI
refreshToken	string	Refresh token for updating access token

key	Type	Description
time	string	Token generated time

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": {
    "appKey": "8FB345B8693CCD003CC2DAB61EC8791D",
    "account": "jimitest",
    "accessToken": "7da3330ec28e3996b6ef4a7e3390ba71",
    "expiresIn": 60,
    "refreshToken": "7da3330ec28e3996b6ef4a7e3390ba71",
    "time": "2017-06-15 10:00:00"
  }
}
```

Return error example:

json

```
{
  "code": "xxx",
  "message": "Illegal request, token is invalid"
}
```

2. Device Management

2.1 List all devices of sub-account

2.1.1 Description

Query all devices of a specified account.

2.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.user.device.list

2.1.3 HTTP Request method

POST

2.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		Access token for security access JIMI Server.
target	string	Yes	-	The specified account for inquired.

2.1.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Array[Object]	The returned data

result

key	Type	Description
imei	string	Device IMEI
deviceName	string	Device name
mcType	string	Device model
mcTypeUseScope	string	Automobile, electromobile, personal, pet, plane, others
sim	string	Sim card number
expiration	string	Platform expiration date
activationTime	string	Activation time

key	Type	Description
reMark	string	Remarks
vehicleName	string	Vehicle name
vehicleIcon	string	Vehicle icon
vehicleNumber	string	License plate number
vehicleModels	string	Brand
carFrame	string	VIN
driverName	string	Driver name
driverPhone	string	Driver phone number
enabledFlag	int	Available or not (1:Available,0:not available)
engineNumber	string	Engine number
deviceGroupId	string	Device group ID
deviceGroup	string	Device group name

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "imei": "868120145233604",
      "deviceName": "868120145233604",
      "mcType": "GT300L",
      "mcTypeUseScope": "personal",
      "sim": "415451",
      "expiration": "2037-04-01 23:59:59",
      "activationTime": "2017-04-01 11:02:20",
      "reMark": "test",
      "vehicleName": null,
      "vehicleIcon": "bus",
      "vehicleNumber": "粤 B3604",
      "vehicleModels": null,
      "carFrame": "2235",
    }
  ]
}
```



```
"driverName": "driver",
"driverPhone": "13825036579",
"enabledFlag": 1,
"engineNumber": "8565674",
"deviceGroupId": "b54ab3c430864e31a64e54de44c79a1d",
"deviceGroup": "default group"
}
]
}
```

Return error example:

```
{
  "code": "xxx",
  "message": "Account queried doesn't exist"
}
```

json

2.2 Get device detail information

2.2.1 Description

Get device detail information for specific IMEI.

2.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.track.device.detail

2.2.3 HTTP Request method

POST

2.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	Access token for security access JIMI Server.
imei	string	Yes	-	The specified IMEI for inquired.

2.2.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Object	The returned data

result

key	Type	Description
imei	string	Device IMEI
deviceName	string	Device name
account	string	The account the device belongs to
customerName	string	The customer name of the account that the device belongs to
mcType	string	Device model
mcTypeUseScope	string	Automobile, electromobile, personal, pet, plane, others
sim	string	Sim card number
expiration	string	Platform expiration date
user_expiration	string	User expiration date, format as: account1,2019 - 01 - 01 account2,2019 - 02 - 02
activationTime	string	Activation time
reMark	string	Remarks

key	Type	Description
vehicleName	string	Vehicle name
vehicleIcon	string	Vehicle icon
vehicleNumber	string	License plate number
vehicleModels	string	Vehicle Model
carFrame	string	VIN
driverName	string	Driver name
driverPhone	string	Driver phone number
enabledFlag	int	Available or not (1:Available,0:not available)
engineNumber	string	Engine number
iccid	string	
importTime	string	
imsi	string	
licensePlatNo	string	
vin	string	Vehicle frame number
vehicleBrand	string	
fuel_100km	string	Fuel consumption for per 100km.
status	string	0 - disable 1 - enable
currentMileage	string	The current mileage of the device (km)
deviceGroupld	string	Device group ID
deviceGroup	string	Device group name

Correct return example:

json

```
{  
  "code": 0,  
  "message": "success",
```

```

"result": {
  "imei": "868120145233604",
  "deviceName": "868120145233604",
  "mcType": "GT300L",
  "mcTypeUseScope": "personal",
  "sim": "415451",
  "expiration": "2037-04-01 23:59:59",
  "activationTime": "2017-04-01 11:02:20",
  "reMark": "test",
  "vehicleName": null,
  "vehicleIcon": "bus",
  "vehicleNumber": "粤B3604",
  "vehicleModels": null,
  "carFrame": "2235",
  "driverName": "driver",
  "driverPhone": "13825036579",
  "enabledFlag": 1,
  "engineNumber": "8565674",
  "iccid": "xxxxxxx",
  "imsi": "xxxx",
  "importTime": "2017-04-01 11:02:20",
  "licensePlatNo": "8565674",
  "VIN": "xxxxxxx",
  "vehicleBrand": "xxxx",
  "fuel_100km": "9",
  "status": "8565674",
  "currentMileage": "102.5",
  "deviceGroupId": "b54ab3c430864e31a64e54de44c79a1d",
  "deviceGroup": "default group"
}
}

```

Return error example:

json

```

{
  "code": "xxx",
  "message": "Account queried doesn't exist"
}

```

2.3 Update user expiration date

2.3.1 Description

Update user expiration date of devices.

2.3.2 Request URL

[See the unique request URL.](#)

Method = jimi.user.device.expiration.update

2.3.3 HTTP Request method

POST

2.3.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		access token: used to security access JIMI server.
imei_list	string	Yes	-	One or multiple devices IMEI.
new_expiration	string	Yes		New user expiration date for devices.

2.3.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned data

result list:

Key	Type	Description
imei	string	IMEI of device
update_result	string	0-success, 1-failure
update_msg	string	Result information, success and failure reasons

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "imei": "868120145233604",
      "update_result": "0",
      "update_msg": "update success"
    },
    {
      "imei": "868120145233605",
      "update_result": "1",
      "update_msg": "update failed, reason:xxxxxx"
    }
  ]
}
```

Return error example:

json

```
{
  "code":xxx,
  "message": "Illegal device"
}
```

2.4 Update vehicle information by IMEI

2.4.1 Description

Update vehicle information by IMEI

2.4.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.device.update

2.4.3 HTTP Request method

POST

2.4.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		Access token: used to identify legal client.
imei	string	Yes	-	Device IMEI
device_name	string	No	-	Device name
vehicle_name	string	No	-	Vehicle name
vehicle_icon	string	No	-	Vehicle icon
vehicle_number	string	No	-	Vehicle plate number
vehicle_models	string	No	-	Vehicle brand
driver_name	string	No	-	Driver name
driver_phone	string	No	-	Driver phone
device_status	string	No		0 - disable/1-enable. Enable/Disable devices.
sim	string	No		SIM card number
remarks	string	No		Remarks
oilWear	string	No		Fuel consumption per 100 kilometers
deviceGroupId	string	No		Device group id
mileage	string	No		Mileage, unit: m

 Vehicle Icon

Icon key	Description
automobile	Car
bus	Bus
per	People
mtc	Motorcycle
truck	
taxi	
plane	
schoolBus	
excavator	
ship	
tricycle	
policeMtc	Police Motorcycle
tractor	
policeCar	
cow	
other	

2.4.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned data

Correct return example:

json

```
{
  "code": 0,
  "message": "Vehicle information modification successful",
  "result": null
}
```

Return error example:

json

```
{
  "code":xxx,
  "message": "imei doesn't exists"
}
```

2.5 Move devices

2.5.1 Description

Move devices from one sub-account to another sub-account.

2.5.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.device.move

2.5.3 HTTP Request method

POST

2.5.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party

Parameter	Type	Required	Remark	Description
src_account	string	Yes	-	Transfer device from account
dest_account	string	Yes	-	Transfer device to account
imeis	string	Yes	-	Device imei
cleanBindFlag	string	No	-	1: clear data, 0: Do not clear data

2.5.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Array	The returned parameters

Correct return example:

json

```
{  
  "code": 1112,  
  "message": " device already exists ",  
  "result": [  
    "2022054545454"  
  ],  
  "data": null  
}
```

or

```
{  
  "code": 0,  
  "message": " Transfer/Sell Equipment Successfully ",  
  "result": null,  
  "data": null  
}
```

Return error example:

```
{  
  "code":xxx,  
  "message": "no permissions"  
}
```

2.6 Bind app user

2.6.1 Description

Bind the device to the app user.

2.6.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.device.bind

2.6.3 HTTP Request method

POST

2.6.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
imei	string	Yes	-	The account to which the geofences belong
user_id	string	Yes	-	The app user account to be bound

2.6.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 10:The device has been bound to a user 1001: Illegal parameters 1002: User or device is incorrect, see message for specific errors 1100: Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message

Correct return example:

json

```
{  
  "code": 0,  
  "message": "success"  
}
```

Return error example:

json

```
{  
  "code": 1100,  
  "message": "The system is busy ",  
  "result": null,  
  "data": null  
}
```

2.7 Unbind app user

2.7.1 Description

Unbind the device from the app use

2.7.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.device.unbind

2.7.3 HTTP Request method

POST

2.7.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
imei	string	Yes	-	The account to which the geofences belong
user_id	string	yes	-	The app user account you want to unbind

2.7.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 10:The device has been bound to a user 1001: Illegal parameters 1002: User or device is incorrect, see message for specific errors 1100: Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message

Correct return example:

json

```
{  
  "code": 0,
```

```
"message": "success"
}
```

Return error example:

json

```
{
  "code": 1100,
  "message": "The system is busy ",
  "result": null,
  "data": null
}
```

2.8 Create device group

2.8.1 Description

Add device groups.

Users can divide devices into different groups for easier management.

2.8.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.group.create

2.8.3 HTTP Request method

POST

2.8.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party

Parameter	Type	Required	Remark	Description
account	string	Yes	-	The account that the created device group belongs to
group_name	string	Yes		group name

2.8.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
data	object	The returned data.

result

Key	Type	scription
group_id	string	ID of the new device group
group_name	string	Name of the new device group

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": {
    "group_id": "534d23f1b28c44319f4f8ba0cda5b7e6",
    "group_name": "device group 1"
  }
}
```

Return error example:

2.9 Edit device group

2.9.1 Description

Edit device groups.

2.9.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.group.update

2.9.3 HTTP Request method

POST

2.9.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
group_id	string	Yes	-	ID of the device group being edited
group_name	string	Yes		Name of the device group being edited

2.9.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message

Correct return example:

json

```
{
  "code": 0,
  "message": "success"
}
```

Return error example:

json

2.10 Delete device group

2.10.1 Description

Delete device groups.

2.10.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.group.delete

2.10.3 HTTP Request method

POST

2.10.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
group_id	string	Yes	-	ID of the device group being deleted

2.10.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message

Correct return example:

json

```
{  
  "code": 0,  
  "message": "success"  
}
```

Return error example:

json

2.11 Get device group list of an account

2.11.1 Description

Query the device groups of an account.

2.11.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.group.list

2.11.3 HTTP Request method

POST

2.11.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
account	string	Yes	-	The account that the device groups belong to

2.11.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
data	array[object]	The returned data.

rows list:

key	Type	Description
group_id	string	ID of the new device group
group_name	string	Name of the new device group

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "group_id": "b2ac10536171474eb0c151c7bb606f3d",
      "group_name": "Default group"
    },
    {
      "group_id": "298b949bacbb4badae597ba1fdb629be",
      "group_name": "22221"
    }
  ]
}
```

```
    },  
    {  
      "group_id": "05cbdd380ca14c2e89b2ab59904f51b7",  
      "group_name": "CVCVXCV"  
    }  
  ]  
}
```

Return error example:

json

3. Tracking Function

3.1 Get location of devices by account

3.1.1 Description

Get the latest location for all devices under an account.

3.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.user.device.location.list

3.1.3 HTTP Request method

POST

3.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		Access token for security access JIMI Server.
target	string	Yes	-	Specify the account for inquired.

Parameter	Type	Required	Remark	Description
map_type	string	No	-	map_type=GOOGLE, calibrated by google calibration. map_type=null, return origin latitude and longitude

3.1.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Array[Object]	The returned data

Result data:

Key	Type	Description
imei	string	Device IMEI
deviceName	string	Device name
icon	string	Vehicle icon
status	string	Device status 0 - offline; 1 - online
lat	double	Longitude (if the device is expired, the value is 0)
lng	double	Latitude (if the device is expired, the value is 0)
expireFlag	string	Expired or not: 1- not expired; 0 - expired
activationFlag	string	Activate or not :1 - Activate; 0 - Not active
posType	string	GPS, LBS, WIFI,BEACON
locDesc	string	Location information while the device is positioned by Bluetooth
gpsTime	string	GPS positioning time

Key	Type	Description
hbTime	string	Heartbeat time
speed	string	Speed (unit: km / h)
accStatus	string	ACC 0-OFF; 1-ON
electQuantity	string	The power will be calculated based on the model configuration and voltage.
powerValue	string	External voltage(0-100), some models are not supported
distance	string	distance from device.
temperature	string	temperature (unit:°C)
trackerOil	string	Oil quantity of the car (Original voltage value)
gpsSignal	string	GSM signal strength level 0 - No signal 1 - Extremely week 2 - Week 3 - Strong 4 - Extremely strong
gpsNum	string	Number of satellites
direction	string	Moving azimuth angle, 0-360, -1 represents unknown, for example: 100.12
currentMileage	string	Current mileage
batteryPowerVal	String	Internal voltage
confidence	int	Positioning Accuracy , divided into 3 levels. 1 represents the worst, and 3 represents the best.

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "imei": "860121060369660",
```

```

    "deviceName": "VL802-69660",
    "mcType": "VL802",
    "icon": "other",
    "status": "1",
    "posType": "GPS",
    "lat": 22.576562,
    "lng": 113.943084,
    "hbTime": "2026-03-26 11:25:38",
    "accStatus": "1",
    "gpsSignal": "4",
    "powerValue": null,
    "batteryPowerVal": "0.06",
    "speed": "0",
    "gpsNum": "15",
    "gpsTime": "2026-03-18 10:20:37",
    "direction": "0",
    "activationFlag": "1",
    "expireFlag": "1",
    "electQuantity": "",
    "locDesc": null,
    "distance": "-1",
    "temperature": null,
    "trackerOil": "0.00L",
    "trackerOils": null,
    "currentMileage": "0.6481649691599485",
    "account": "FAETEST",
    "customerName": "FAETEST",
    "state": null,
    "stateTime": null,
    "iccid": "898608401024C0669758",
    "mac": "",
    "chargeStatus": null,
    "shutdown": null,
    "confidence": null
  }
],
"data": null
}

```

Return error example:

```
{  
  "code": "xxx",  
  "message": "The account does not exist"  
}
```

3.2 Get the location of device(s)

3.2.1 Description

Get the latest location for one or multiple devices.

3.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.location.get

3.2.3 HTTP Request method

POST

3.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		access token: used to security access JIMI server.
imeis	string	Yes	–	Device IMEI. Separate imei by comma; POST is recommended if too many devices (maximum 100 IMEI)
map_type	string	No	–	map_type=GOOGLE, calibrated by google calibration. map_type=null, return origin latitude and longitude

3.2.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Array[Object]	The returned data

Result list:

Key	Type	Description
imei	string	Device IMEI
deviceName	string	Device name
account	string	The account the device belongs to
customerName	string	The customer name of the account that the device belongs to
icon	string	Vehicle icon
status	string	Device status 0, offline; 1, online
lat	double	Longitude (if the device expires, the value is 0)
lng	double	Latitude (if the device expires, the value is 0)
expireFlag	string	1- not expired; 0 - expired
activationFlag	string	1 - Activate; 0 - Not active
posType	string	GPS, LBS, WIFI, BEACON
locDesc	string	Location information
gpsTime	string	GPS positioning time
hbTime	string	Heartbeat time
speed	string	Speed (unit: km / h)
accStatus	string	ACC 0- off ;1- on
batteryPowerVal	string	battery (0-100) , Some device models are not supported

Key	Type	Description
powerValue	string	External voltage (0-100), Some device models are not supported
distance	string	distance from device.
temperature	string	temperature (unit:°C)
trackerOil	string	Vehicle remaining fuel
currentMileage	string	The current mileage of the device (km)
gpsNum	string	Number of satellites
gpsSignal	string	GSM signal strength level 0 - No signal 1 - Extremely week 2 - Week 3 - Strong 4 - Extremely strong
direction	string	Moving azimuth angle, 0-360, -1 represents unknown, for example: 100.12
electQuantity	string	The power will be calculated based on the model configuration and voltage.
confidence	int	Positioning Accuracy , divided into 3 levels. 1 represents the worst, and 3 represents the best.

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "imei": "868120145233604",
      "deviceName": "868120145233604",
      "icon": "bus",
      "status": "0",
      "posType": "GPS",
      "lat": 22.577282,
      "lng": 113.916604,
```

```

    "hbTime": "2017-04-26 09:14:50",
    "accStatus": "0",
    "speed": "0",
    "gpsNum": "11",
    "gpsTime": "2017-04-26 09:17:46",
    "activationFlag": "1",
    "expireFlag": "1",
    "electQuantity": "60",
    "locDesc": null,
    "powerValue": null,
    "temperature": "86.5",
    "trackerOil": null,
    "currentMileage": "86.5"
  }
]
}

```

Return error example:

```

{
  "code": "xxx",
  "message": "Illegal device"
}

```

json

3.3 Get sharing location URL

3.3.1 Description

Get the URL of device location showing on the Map.

3.3.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.location.URL.share

3.3.3 HTTP Request method

POST

3.3.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		access token: used to security access JIMI server.
imei	string	Yes	–	Device IMEI

3.3.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Object	The returned data contains URL information.

result Object:

Key	Type	Description
URL	string	Device location sharing link

Correct return example:

```
{  
  "code": 0,  
  "message": "success",  
  "result": {  
    "URL": "data.16180track.com/api/share?ver=2&method=trackDevice_abr&deviceinf  
  }  
}
```

json

Return error example:

```
{  
  "code":xxx,  
  "message": "Illegal device"  
}
```

3.4 Get the mileage data of devices

3.4.1 Description

Get device(s) trips data of specified time range.

3.4.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.track.mileage

3.4.3 HTTP Request method

POST

3.4.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	Access token: used to identify legal client.
imeis	string	Yes	-	Device imeis, separate by comma.
begin_time	number	Yes	-	Start time Format: yyyy-MM-dd HH:mm:ss
end_time	number	Yes	-	End time Format: yyyy-MM-dd HH:mm:ss end_time should be earlier than current time
start_row	number	No	-	Row number of result set.

Parameter	Type	Required	Remark	Description
page_size	number	No		Records in one page.

3.4.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Array[Object]	The returned data
data	Array[Object]	Summary information: IMEI : IMEI of device totalMileage: The sum of the total mileage of all trips made by the device within the specified time period

result list:

Key	Type	Description
imei	string	IMEI of device
startTime	string	Start time
endTime	string	End time
startLat	string	Latitude of start position.
startLng	string	Longitude of start position.
endLat	string	Latitude of end position.
endLng	string	Longitude of end position.
runTimeSecond	int	Second of elapsed between start and end position.
distance	double	Distance(meter) between start and end position.
avgSpeed	double	Average speed

Correct return example:

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "imei": "3505831983422342",
      "startTime": "2017-04-26 00:00:58",
      "endTime": "2017-04-26 00:03:58",
      "startLat": 22.577144898887813,
      "startLng": 113.91674845964586,
      "endLat": 22.677144898887813,
      "endLng": 113.92674845964586,
      "elapsed": 2130,
      "distance": 25000,
      "avgSpeed": 90
    },
    {
      "imei": "3505831983422342",
      "startTime": "2017-04-26 00:00:58",
      "endTime": "2017-04-26 00:03:58",
      "startLat": 22.577144898887813,
      "startLng": 113.91674845964586,
      "endLat": 22.677144898887813,
      "endLng": 113.92674845964586,
      "elapsed": 2130,
      "distance": 25000,
      "avgSpeed": 90
    }
  ],
  "data": [
    {
      "imei": "3505831983422342",
      "totalMileage": 60000
    },
    {
      "imei": "3505831983422342",
      "totalMileage": 60000
    }
  ]
}
```

Return error example:

3.5 Get the track data of device

3.5.1 Description

Get device track data of not more than 7 days, within 3 months.

3.5.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.track.list

3.5.3 HTTP Request method

POST

3.5.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	Access token: used to identify legal client.
imei	string	Yes	-	Device imei(only 1 each time)
begin_time	number	Yes	-	Start time Format: yyyy-MM-dd HH:mm:ss
end_time	number	Yes	-	End time Format: yyyy-MM-dd HH:mm:ss end_time should be earlier than current time
map_type	string	No	-	map_type=GOOGLE, calibrated by google calibration. map_type=null, return origin latitude and longitude

3.5.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Array[Object]	The returned data
data	object	The returned data

result list:

Key	Type	Description
lng	double	longitude
lat	double	latitude
gpsTime	string	GPS positioning time. Format yyyy-MM-dd HH: mm: ss
direction	string	Direction, polar coordinates started from due north
gpsSpeed	string	GPS speed
posType	string	1-GPS, 2-LBS, 3-WIFI
satellite	string	GPS antenna signal strength
ignition	string	Ignition status; ON-ACC ON, OFF-ACC OFF
accStatus	string	Acc status
confidence	int	Positioning Accuracy , divided into 3 levels. 1 represents the worst, and 3 represents the best.
gpsMode	int	Location data type: 0: Real-time data; 1: Retransmitted data

data list:

Key	Type	Description
mileage	string	The mileage of the track within the query time

Correct return example:

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "lat": 22.576607,
      "lng": 113.943084,
      "gpsTime": "2026-03-18 09:40:46",
      "direction": 0,
      "gpsSpeed": 0.0,
      "posType": 1,
      "satellite": 0,
      "ignition": "ON",
      "accStatus": "ON",
      "gpsMode": 0,
      "confidence": null
    }
  ],
  "data": {
    "mileage": 0
  }
}
```

Return error example:

```
{
  "code":xxx,
  "message": "IMEI does not exist{353419031939627}"
}
{
  " code ":xxx,
  "message": "The device has expired{353419031939627}"
}
```

3.6 Wi-Fi, Base Station locating analysis

3.6.1 Description

Allocate by total devices under the account (10 times/day/device. All sub-accounts included)

3.6.2 Request URL

[See the unique request URL.](#)

Method = jimi.lbs.address.get

3.6.3 HTTP Request method

POST

3.6.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		access token: used to identify legal client.
imei	number	Yes	-	Device Imei
lbs	number	No	-	(wifi/LBS: at least one) LBS information group (mcc,mnc,lac,cell,rssi), max 7. Each group has five, which should not be null and sorted in order. MCC, China: 460 MNC LAC information, 2312 23222 CELL code: 23222 RSSI Semaphore-70
wifi	string	No	-	(wifi/LBS: at least one) mac1,rssi1 mac2,rssi2 Mac address, no colon in between. Rssi signal strength

3.6.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Object	The returned data

Result list:

Key	Type	Description
lng	string	longitude
lat	string	latitude
accuracy	string	Accuracy, the greater the value the better

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": {
    "lat": 40.65615416521587,
    "lng": 109.89894039833524,
    "accuracy": 0
  }
}
```

Return error example:

json

```
{
  "code":xxx,
  "message": "illegal device"
}
```

3.7 Get parking/idling data of devices

3.7.1 Description

Get device(s) parking/idling data of specified time range.

3.7.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.report.parking

3.7.3 HTTP Request method

POST

3.7.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
account	string	Yes	-	The account to which the new fence belongs
imeis	string	Yes	-	Example values: 869247060001770,869247060001259,869247060001259
start_time	string	Yes	-	Start time Format: yyyy-MM-dd HH:mm:ss
end_time	string	Yes	-	End time Format: yyyy-MM-dd HH:mm:ss end_time must be earlier than current time
start_row	string	Yes	-	Row number of result set.
page_size	string	Yes	-	Records in one page.
acc_type	string	Yes	-	on: get the Idling data;off: get the parking data

3.7.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	null
data	object	The returned data.

data list:

key	Type	Description
totalTime	string	Request processing time
dataTotalRows	string	Total rows
rows	array[object]	Data details

rows list:

key	Type	Description
imei	string	Imei of device
startTime	string	Start time
endTime	string	End time
durSecond	string	Parking time
lng	number	Longitude
lat	number	Latitude
addr	string	Address
deviceName	string	Device name
mcType	string	Device model
acc	string	Acc status

key	Type	Description
stopSecond	string	Length of parking

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": {
    "totalTime": "185641",
    "dataTotalRows": "2",
    "rows": [
      {
        "imei": "869247060001739",
        "startTime": "2022-12-10T01:05:33.000Z",
        "endTime": "2022-12-10T04:17:48.000Z",
        "durSecond": "11535",
        "lng": 113.943093,
        "lat": 22.576748,
        "addr": "Shigu Road, 松坪村, Xili Sub-district, Nanshan distri...",
        "deviceName": "JC450Pro-01739",
        "mcType": "JC450Pro",
        "acc": "on",
        "stopSecond": "11535"
      },
      {
        "imei": "869247060001739",
        "startTime": "2022-12-09T22:13:16.000Z",
        "endTime": "2022-12-10T01:04:25.000Z",
        "durSecond": "10269",
        "lng": 113.943002,
        "lat": 22.57649,
        "addr": "Shigu Road, 松坪村, Xili Sub-district, Nanshan distri...",
        "deviceName": "JC450Pro-01739",
        "mcType": "JC450Pro",
        "acc": "on",
        "stopSecond": "10269"
      }
    ]
  }
}
```

```
}  
}
```

Return error example:

json

```
{  
  "code": 1100,  
  "message": "Business exception ",  
  "result": null,  
  "data": null  
}
```

3.8 Get the location of TAG device

3.8.1 Description

Query the latest location of TAG.

3.8.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.location.getTagMsg

3.8.3 HTTP Request method

POST

3.8.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
imei	string	Yes	-	Imei of TAG device

3.8.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Array[Object]	The returned data.

result list:

key	Type	Description
lng	double	Longitude
lat	double	Latitude
gpsTime	Long	GPS positioning time
directions	String	course
gpsSpeed	int	Speed
positionType	String	1:GPS, 2:LBS, 3:WIFI,5:BEACON
gpsNum	int	Number of satellites

Correct return example:

json

```
{  
  "code": 0,  
  "message": "success",  
  "result": [  
    {  
      "lng": 113.943054,  
      "lat": 22.576609,  
      "gpsTime": 1734593340,  
      "directions": "0",  
      "gpsSpeed": -1.0,  
    }  
  ]  
}
```

```
        "positionType": "5",
        "gpsNum": 3
    }
]
```

Return error example:

json

```
{
  "code": 1100,
  "message": "Business exception ",
  "result": null,
  "data": null
}
```

3.9 Refresh TAG Data in Batch

3.9.1 Description

Refresh TAG data in batch

3.9.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.location.updateTagDevices

3.9.3 HTTP Request method

POST

3.9.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third

Parameter	Type	Required	Remark	Description
imeis	string	Yes	-	Imei of TAG device Device imei(s), separate than 100 each time.Supports querying the device and its sub-account devices.Example values:8780901703130335,7809017031296

3.9.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	null	null
data	null	null

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": null
}
```

Return error example:

json

```
{
  "code": 1100,
  "message": "Business exception ",
  "result": null,
  "data": null
}
```

4. Media Function

4.1 Get Device Live Steaming Page URL

4.1.1 Description

Get device live streaming page URL& last position information.

4.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.live.page.url

4.1.3 HTTP Request method

POST

4.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		Access token: used to identify legal client.
imei	string	Yes	-	Device IMEI
type	string	No	Default type=1	Type=1 real-time video Type=2 Historical video
voice	string	No	Default 1	0 is disable; 1 is enable

4.1.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description

Key	Type	Description
message	string	If code is not 0, there will be a corresponding error message
result	Object	The returned data

result object:

Key	Type	Description
lng	double	longitude
lat	double	latitude
gpsTime	string	GPS positioning time. Format yyyy-MM-dd HH: mm: ss
direction	string	Direction, polar coordinates started from due north
gpsSpeed	string	GPS speed
posType	string	1-GPS, 2-LBS, 3-WIFI
satellite	string	GPS antenna signal strength
VIN	string	VIN
plateNo	string	License Plate Number
UrlCamera	string	Live streaming page URL

Correct return example:

json

```
{
  "code": 0,
  "message": "Vehicle information modification successful",
  "result": {
    "lat": 22.577144898887813,
    "lng": 113.91674845964586,
    "gpsTime": "2017-04-26 00:00:58",
    "direction": 0,
    "gpsSpeed": -1,
    "posType": 3,
    "satellite": 11,
    "VIN": "V12345",
    "plateNo": "ABC-12345",
  }
}
```

```
    "UrlCamera": "https://www.domain.com/device/video/35408343202342345",  
  }  
}
```

Return error example:

```
{  
  "code":xxx,  
  "message": "imei doesn't exists"  
}
```

json

4.2 Send media instruction

4.2.1 Description

Send video or photo command to device.

4.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.meida.cmd.send

4.2.3 HTTP Request method

POST

4.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		Access token: used to identify legal client.
imei	string	Yes	-	Device IMEI

Parameter	Type	Required	Remark	Description
camera	string	Yes	mediaType=1 Only limited 1 or 2	1-front camera 2- inward camera 3- front + inward camera
mediaType	string	Yes		1 -photo 2-video
shootTime	string	No	0 or 3-10	mediaType=2 Recording duration 3-10

4.2.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	Description of sending command result.
result	JSON	<pre>{ "code": "100", "data": "1.3.3", "msg": "Communication successful response", "cmdSeqNo": "1" }</pre> Return code: 225: time out 226: Parameter error 227: The command is not executed correctly 228: The device is not online 229: Network error, connection error, etc. 238: Device interrupted 240: Data format error

Correct return example:

```
{
  "code": 0,
  "message": "Operation successful",
  "result": {
    "code": "255",
```

json

```

        "data": "1.3.3",
        "msg": "通信成功响应",
        "cmdSeqNo": "1"
    }
}

```

Return error example:

```

{
    "code": -1,
    "message": "Operation successful",
    "result": {
        "code": "228",
        "data": "1.3.3",
        "msg": "设备不在线",
        "cmdSeqNo": "1"
    }
}

```

json

4.3 Send history video instruction

4.3.1 Description

Send upload history video file command to device.

4.3.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.history.cmd.send

4.3.3 HTTP Request method

POST

4.3.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		Access token: used to identify legal client.
imei	string	Yes	-	Device IMEI
type	string	Yes		1-Full fragment 2-Event fragment
camera	string	Yes		1-out 2-in
fileName	string	No	type=1 is not null	Historical video file name
time	string	No	type=2 is not null	Event time point, time format yyyy-MM-dd HH:mm:ss

4.3.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	Description of sending command result.
result	JSON	<pre>{ "code": "100", "data": "1.3.3", "msg": "Communication successful response", "cmdSeqNo": "1" }</pre> Return code: 225: time out 226: Parameter error 227: The command is not executed correctly 228: The device is not online 229: Network error, connection error, etc. 238: Device interrupted 240: Data format error

Correct return example:

json

```
{
  "code": 0,
  "message": "Operation successful",
  "result": {
    "code": "255",
    "data": "1.3.3",
    "msg": "Successful response",
    "cmdSeqNo": "1"
  }
}
```

Return error example:

json

```
{
  "code": -1,
  "message": "Operation successful",
  "result": {
    "code": "228",
    "data": "1.3.3",
    "msg": "Device is offline",
    "cmdSeqNo": "1"
  }
}
```

4.4 Get Device JIMI Photo or Video URL

4.4.1 Description

Get device photo or video URL which capture by camera.

4.4.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.jimi.media.URL

4.4.3 HTTP Request method

POST

4.4.4 Request parameters

(1) [Common parameters](#)

(2) Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		Access token: used to identify legal client.
imei	string	Yes	-	Device IMEI
camera	string	Yes		1-front camera 2- inward camera 3 both
media_type	string	Yes		1 -photo 2-video 3-both
start_time	date	No		Start time of photo or video created.
end_time	date	No		End time of photo or video created.
token	string	No		Token used to validate whether can access photo or video or not.
page_no	int	No		Zero indexed, 0 by default.
page_size	int	No		10 rows by default.

4.4.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned data,could be multiple rows.

result list:

Key	Type	Description
thumb_URL	string	URL of video or photo thumbnail.

Key	Type	Description
file_URL	string	URL of video or photo.
mime_type	string	Mime type of video or photo
create_time	long	Create time of video or photo.Unix timestamp format
alarm_time	long	The time at which the alarm was triggered, Unix timestamp format
media_type	string	1-photo 2-video
camera	string	0-front camera 1-inward camera
file_size	int	File size of photo or video.

⚠ Remark: Unix timestamp; Example: 1611105520 = 2021-01-20 09:18:40

Correct return example:

json

```
{
  "code": 0,
  "message": "Operation successful",
  "result": [
    {
      "thumb_URL": "http://8.210.205.58:8081/normal/get?fileKey=2021_01_20_09_08_12108649",
      "file_URL": "http://8.210.205.58:8081/normal/get?fileKey=357730090564767",
      "create_time": 1611105520,
      "mime_type": "video/mp4",
      "media_type": 2,
      "alarm_time": 1611105469,
      "camera": 0,
      "file_size": "12108649"
    },
    {
      "thumb_URL": "http://8.210.205.58:8081/normal/get?fileKey=2021_01_20_08_12108649",
      "file_URL": "http://8.210.205.58:8081/normal/get?fileKey=357730090564767",
      "create_time": 1611101264,
      "mime_type": "video/mp4",
      "media_type": 2,
      "alarm_time": 1611101173,
      "camera": 0,
      "file_size": "48452069"
    }
  ]
}
```

```
]
}
```

Return error example:

```
{
  "code":xxx,
  "message": "imei doesn't exists"
}
```

json

4.5 Get Device Media Event URL

4.5.1 Description

Get Device Media Event URL

4.5.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.media.event.URL

4.5.3 HTTP Request method

POST

4.5.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		Access token: used to identify legal client.
imeis	String	Yes	-	Device IMEI. Separate imei by comma
event_type	String	No	-	Event Type Id
media_type	String	Yes	-	Media Type : 1 -photo 2-video 3-both

Parameter	Type	Required	Remark	Description
start_time	String	Yes	-	Start time of photo or video created.
end_time	String	Yes	-	End time of photo or video created.
page_no	int	Yes	-	page number
page_size	int	Yes	-	Records in one page.

4.5.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	
data	Object	The returned data

data list:

Key	Type	Description
currentPage	int	currentPage
pageSize	int	pageSize
startRow	int	startRow
endRow	int	endRow
totalRecord	int	totalRecord
totalPage	int	totalPage
result	Array[Object]	

result :

Key	Type	Description
imei	String	
event_type_id	String	Event type id
event_type	String	Event type
lat	String	latitude
lng	String	longitude
alarm_time	Long	The time at which the alarm was triggered, Unix timestamp format
create_time	Long	Create time of video or photo.Unix timestamp format
fileList	Array[Object]	File List

fileList :

Key	Type	Description
media_type	int	Media Type: 1 -photo 2-video 3-both
mime_type	String	Mime type of video or photo : video/mp4, image/jpeg
thumb_URL	String	URL of video or photo thumbnail.
file_URL	String	File URL
camera	int	Channel
file_size	String	File size

⚠ Remark: Unix timestamp; Example: 1611105520 = 2021-01-20 09:18:40

Correct return example:

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": {
    "currentPage": 1,
    "pageSize": 3,
```

json

```
"startRow": 0,
"endRow": 0,
"totalRecord": 72,
"totalPage": 24,
"result": [
  {
    "imei": "862798051058689",
    "event_type_id": "147",
    "event_type": "Collision Alert(DVR)",
    "lat": "22.576639",
    "lng": "113.943077",
    "alarm_time": 1756450743,
    "create_time": 1756450743,
    "fileList": [
      {
        "media_type": 2,
        "mime_type": "video/mp4",
        "thumb_URL": "https://sg-file.heytrack.com/normal/get?fileKey",
        "file_URL": "https://sg-file.heytrack.com/normal/get?fileKey",
        "camera": 1,
        "file_size": "17495844"
      }
    ]
  },
  {
    "imei": "862798051058689",
    "event_type_id": "143",
    "event_type": "Distraction Alert",
    "lat": "22.576551",
    "lng": "113.943057",
    "alarm_time": 1756261402,
    "create_time": 1756261402,
    "fileList": [
      {
        "media_type": 2,
        "mime_type": "video/mp4",
        "thumb_URL": "https://sg-file.heytrack.com/normal/get?fileKey",
        "file_URL": "https://sg-file.heytrack.com/normal/get?fileKey",
        "camera": 2,
        "file_size": "1653648"
      }
    ]
  },
  {
```



```

    "imei": "862798051058689",
    "event_type_id": "143",
    "event_type": "Distraction Alert",
    "lat": "22.576551",
    "lng": "113.943057",
    "alarm_time": 1756261217,
    "create_time": 1756261217,
    "fileList": [
      {
        "media_type": 2,
        "mime_type": "video/mp4",
        "thumb_URL": "https://sg-file.heytrack.com/normal/get?fileKey",
        "file_URL": "https://sg-file.heytrack.com/normal/get?fileKey",
        "camera": 2,
        "file_size": "1644248"
      }
    ]
  }
]
}

```

Return error example:

json

4.6 Get Device Live Streaming Address

4.6.1 Description

Get the device live streaming address

4.6.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.media.live.stream

4.6.3 HTTP Request method

POST

4.6.4 Request parameters

(1) [Common parameters](#)

(2) Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
imei	string	Yes	-	Imei of DVR device
channel	string	Yes	Concox Protocol Devices: e.g., JC261, JC400 (Channel numbers start from 0) JT808/1078 Protocol Devices: e.g., JC371, JC181, JC182, JC450, JC451 (Channel numbers start from 1)	DVR device channel
appld	string	Yes	-	Client identification ID, the same ID is used for each session, different sessions use different IDs, 15 random letters and numbers in length

4.6.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100: Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message

key	Type	Description
result	string	Live streaming address The streaming address websocket and http protocols can be interchanged, and customers can adjust as needed.

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": "http://113.108.62.203:11014/1/869247060113161.flv?secret=035c73f7-bb6",
  "data": null
}
```

Wrong return example:

json

```
{
  "code": 1100,
  "message": "Business exception ",
  "result": null,
  "data": null
}
```

4.7 Send Command to Device to Query Historical Video List

4.7.1 Description

The historical video list is stored in the device, so it is necessary to send a command to the device to query the historical video list.

4.7.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.media.history.list.cmd

4.7.3 HTTP Request method

POST

4.7.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
imei	string	Yes	-	Imei of DVR device
channel	string	Yes	Concox Protocol Devices: e.g., JC261, JC400 (Channel numbers start from 0) JT808/1078 Protocol Devices: e.g., JC371, JC181, JC182, JC450, JC451 (Channel numbers start from 1)	DVR device channel
dateTime	string	Yes	-	Query date, format: yyyy-MM-dd
instructionId	string	Yes	-	Instruction ID uniquely identifies an instruction and is used for the correspondence between downlink instructions and uplink responses. UUID can be used.
appId	string	Yes	-	Client identification ID, the same ID is used for each session, different sessions use different IDs, 15 random

Parameter	Type	Required	Remark	Description
				letters and numbers in length

example

bash

```
imei=862798052005515&channel=0&dateTime=2025-11-13&instructionId=5bd5e93158ec4dd3b12
```



4.7.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100: Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	
data	string	

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": null
}
```

Wrong return example:

json

```
{
  "code": 1100,
```

```
"message": "Business exception ",
"result": null,
"data": null
}
```

4.8 Query Historical Video List

4.8.1 Description

⚠ After the device receives the command to upload the historical video list, it asynchronously uploads the historical file list, so it is necessary to use the instructionId used when issuing the command to query the result.

For this interface, if the received code is 1207, the list reported by the device has not yet reached the system. It is necessary to poll this interface after a short sleep until the code is 0 or the maximum number of polls is reached.

It is recommended to query once per second and poll 20 times.

4.8.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.media.history.list.get

4.8.3 HTTP Request method

POST

4.8.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
instructionId	string	Yes	-	Instruction ID uniquely identifies an instruction and is used for the correspondence between downlink

Parameter	Type	Required	Remark	Description
				instructions and uplink responses. UUID can be used.

example

bash

```
instructionId=5bd5e93158ec4dd3b123076add7c19f5
```

4.8.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100: Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	array[object]	Device returned history list data.

result list:

key	Type	Description
channel	string	DVR device channel
beginTime	string	Start time, format: yyyy-MM-dd HH:mm:ss
endTime	string	End time, format: yyyy-MM-dd HH:mm:ss
alarmFlag	string	For expansion, not used currently
resourceType	string	For expansion, not used currently Audio and video resource type (0: audio and video, 1: audio, 2: video, 3: video or audio and video)
codeType	string	For expansion, not used currently Code stream type (0: all code streams, 1: main code stream, 2: sub-code stream)
storageType	string	For expansion, not used currently Storage type (0: all storages, 1: main storage, 2: disaster recovery)

key	Type	Description
		storage)
fileSize	string	File size
sortBeginTime	string	Sorting field
fileName	string	File name, only available for Concox Protocol Devices: e.g., JC261, JC400, not available for JT808/1078 Protocol Devices: e.g., JC371, JC181, JC182, JC450, JC451 Devices

Correct return example:

⚠ Concox Protocol Devices: e.g., JC261, JC400

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "channel": "0",
      "beginTime": "2025-11-13 10:34:19",
      "endTime": "2025-11-13 10:35:19",
      "alarmFlag": null,
      "resourceType": null,
      "codeType": 2,
      "storageType": null,
      "fileSize": null,
      "sortBeginTime": 1763030059000,
      "fileName": "2025_11_13_10_34_19_01.mp4"
    },
    {
      "channel": "0",
      "beginTime": "2025-11-13 10:35:20",
      "endTime": "2025-11-13 10:36:20",
      "alarmFlag": null,
      "resourceType": null,
      "codeType": 2,
      "storageType": null,
      "fileSize": null,
      "sortBeginTime": 1763030120000,
      "fileName": "2025_11_13_10_35_20_01.mp4"
    }
  ]
}
```



```

    },
    {
      "channel": "0",
      "beginTime": "2025-11-13 10:36:20",
      "endTime": "2025-11-13 10:37:20",
      "alarmFlag": null,
      "resourceType": null,
      "codeType": 2,
      "storageType": null,
      "fileSize": null,
      "sortBeginTime": 1763030180000,
      "fileName": "2025_11_13_10_36_20_01.mp4"
    }
  ],
  "data": null
}

```

 JT808/1078 Protocol Devices: e.g., JC371, JC181, JC182, JC450, JC451

json

```

{
  "code": 0,
  "message": "success",
  "result": [
    {
      "channel": "1",
      "beginTime": "2025-11-13 13:55:41",
      "endTime": "2025-11-13 13:58:42",
      "alarmFlag": 0,
      "resourceType": 0,
      "codeType": 2,
      "storageType": 0,
      "fileSize": 6630206,
      "sortBeginTime": 1763042141000,
      "fileName": null
    },
    {
      "channel": "1",
      "beginTime": "2025-11-13 13:58:42",
      "endTime": "2025-11-13 14:01:43",
      "alarmFlag": 0,
      "resourceType": 0,

```

```

        "codeType": 2,
        "storageType": 0,
        "fileSize": 8325778,
        "sortBeginTime": 1763042322000,
        "fileName": null
    },
    {
        "channel": "1",
        "beginTime": "2025-11-13 14:01:43",
        "endTime": "2025-11-13 14:04:44",
        "alarmFlag": 0,
        "resourceType": 0,
        "codeType": 2,
        "storageType": 0,
        "fileSize": 8383870,
        "sortBeginTime": 1763042503000,
        "fileName": null
    }
],
"data": null
}

```

Wrong return example:

json

```

{
    "code": 1100,
    "message": "Business exception ",
    "result": null,
    "data": null
}

```

4.9 Get Device Historical Video Streaming Address

4.9.1 Description

According to the device historical video file list, obtain the streaming address of historical videos.

4.9.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.media.history.stream

4.9.3 HTTP Request method

POST

4.9.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
imei	string	Yes	-	Imei of DVR device
channal	int	Yes	-	DVR device channel
beginTime	string	No	For JT/T 808 / GB/T 1078 Protocol Devices (e.g., JC371, JC181, etc.):Use the beginTime and endTime fields returned by the jimi.device.media.history.list.get API method to request the video stream.	Start time of JT808/1078 Protocol Devices, format: yyyy- MM-dd HH:mm:ss

Parameter	Type	Required	Remark	Description
endTime	string	No	For JT/T 808 / GB/T 1078 Protocol Devices (e.g., JC371, JC181, etc.):Use the beginTime and endTime fields returned by the jimi.device.media.history.list.get API method to request the video stream.	End time of JT808/1078 Protocol Devices, format: yyyy-MM-dd HH:mm:ss
fileNameList	string	No	For Concox Protocol Devices (e.g., JC261, JC400):Use the fileName field returned by the jimi.device.media.history.list.get API method to request the video stream.	Concox Protocol Devices, file list, multiple files are separated by English commas
appld	string	Yes	-	Client identification ID, the same ID is used for each session, different sessions use different IDs, 15 random letters and numbers in length

Example

⚠ Concox Protocol Devices: e.g., JC261, JC400 (Channel numbers start from 0)

bash

```
imei=862798052005515&channel=0&beginTime=&endTime=&fileNameList=2025_11_13_10_34_19_
```

⚠ JT808/1078 Protocol Devices: e.g., JC371, JC181, JC182, JC450, JC451 (Channel numbers start from 1)

```
imei=865478070000239&channel=1&beginTime=2025-11-13 13:55:41&endTime=2025-11-13 13:5
```

4.9.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100: Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	Device historical video streaming address

Example

```
{
  "code": 0,
  "message": "success",
  "result": "ws://113.108.62.203:11014/1/865478070000239.history.flv?secret=035c73",
  "data": null
}
```

4.10 Close Streaming

4.10.1 Description

Stop streaming.

4.10.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.media.close.stream

4.10.3 HTTP Request method

POST

4.10.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
imei	string	Yes	-	Imei of DVR device
channal	int	Yes	Concox Protocol Devices: e.g., JC261, JC400 (Channel numbers start from 0) JT808/1078 Protocol Devices: e.g., JC371, JC181, JC182, JC450, JC451 (Channel numbers start from 1)	DVR device channel
type	string	Yes	-	0: real-time video 1: historical video
appld	string	Yes	-	Client identification ID, the same ID is used for each session, different sessions use different IDs, 15 random letters and numbers in length

Example

bash

```
imei=865478070000239&channel=1&type=1&appId=W1g3vp27z06a486
```

4.10.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100: Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	Device historical video streaming address

5. Command Management

5.1 Get command list supported by device

5.1.1 Description

Get command list supported by device

5.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.instruction.list

5.1.3 HTTP Request method

POST

5.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		accesstoken: used for identifying legal third party
imei	string	Yes	-	Device imei

5.1.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned data

Result list:

Key	Type	Description
id	string	Command code
orderName	string	Command name
orderContent	string	Command template
orderExplain	string	Command explanation
orderMsg	string	prompt
isOffLine	string	if support offline command 0-no; 1-yes

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "id": 81,
      "orderName": "SOS setting",
      "orderContent": "SOS,A,{0},{1},{2}#",
      "orderExplain": "SOS is used for receive alerts and SOS alerts. SOS numb
      "orderMsg": "",
      "isOffLine": "1"
    }
  ]
}
```


Return error example:

json

```
{
  "code":xxx,
  "message": "Illegal device"
}
```

5.2 Send command to device

5.2.1 Description

Send command to device.

⚠ Before sending instructions to the device, please use the method **jimi.open.instruction.list** to query the list of instructions supported by the device.

5.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.instruction.send

5.2.3 HTTP Request method

POST

5.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		accesstoken: used for identifying legal third party
imei	string	Yes	-	Device imei
inst_param_json	string	Yes	-	Command message json character string

inst_param_json description

Parameter	Type	Required	Remark	Description
inst_id	string	Yes		Command code
inst_template	string	Yes	-	Command template
params	Array[string]	Yes	-	Command params string Array
is_cover	Boolean	No	false	Whether cover the existed offline command or not true-cover false-not cover

⚠ Example 1

json

Get command list supported by device:

```
{
  "id": 81,
  "orderName": "Add SOS Number",
  "orderContent": "SOS,A,{0},{1},{2}#",
  "orderExplain": "SOS setting",
  "orderMsg": null,
  "isOffLine": "0"
}
```

Send command to device:

```
{"inst_id": "81","inst_template":"SOS,A,{0},{1},{2}#","params":["0528989490","052898
```

⚠ Example 2

json

Get command list supported by device:

```
{
  "id": 163,
  "orderName": "Fuel/Power Remote Control",
  "orderContent": "RELAY,{0}#",
  "orderExplain": null,
  "orderMsg": null,
  "isOffLine": "0"
}
```

Send command to device:

```
{"inst_id": "163","inst_template":"RELAY,{0}#","params":["1"],"is_cover":"true"}
```

⚠ Example 3

json

User-defined command:

Get command list supported by device:

```
{
  "id": 99,
  "orderName": "User defined command",
  "orderContent": "{0}",
  "orderExplain": null,
  "orderMsg": null,
  "isOffLine": "0"
}
```

Send command to device:

```
{"inst_id": "99", "inst_template": "{0}", "params": ["RELAY,1#"], "is_cover": "true"}
```

5.2.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned parameters

Correct return example:

json

```
{
  "code": 0,
  "message": "command is successfully sent.",
  "result": null
}
```

Return error example:

json

```
{
  "code": 12005,
  "message": "Fail to send command. Result code: 226",
  "result": null
}
```

5.3 Get results of command execution

5.3.1 Description

Get results of sending command.

5.3.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.instruction.result

5.3.3 HTTP Request method

POST

5.3.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		accesstoken: used for identifying legal third party
imei	string	Yes	-	Device imei

5.3.5 Response

Key	Type	Description	
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description	
message	string	If code is not 0, there will be a corresponding error message	
result	string	The returned data	

Result list:

Key	Type	Description
codeId	string	Command code
code	string	Command sent
content	string	Content replied by device
isExecute	string	command status: 0: execution failed, 1: successful execution, 3: to be sent, 4: canceled
sendTime	string	Time, format: yyyy-MM-dd HH:mm:ss
sender	string	sender
receiveDevice	string	Received imei
isOffLine	string	0: online 1: offline
idsource	string	Command description

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "codeId": "99",
      "code": "status#",
      "content": "Parameter error",
      "isExecute": "4",
      "sendTime": "2017-06-19 11:46:00",
      "sender": "jimitest",
      "receiveDevice": "86812011111117",
      "isOffLine": "1",
      "idsource": "User-defined command"
    }
  ]
}
```

Return error example:

json

```
{
  "code":xxx,
  "message": "Illegal device"
}
```

5.4 Send raw command data to device

5.4.1 Description

Send raw command to device.

5.4.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.instruction.raw.send

5.4.3 HTTP Request method

POST

5.4.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		accesstoken: used for identifying legal third party
imei	String	Yes	-	Device imei
raw_cmd	string	Yes	-	Raw command data(hex string)

⚠ Raw Command Example: 0B02C3A405060708

5.4.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned parameters

Correct return example:

json

```
{  
  "code": 0,  
  "message": "command is successfully sent.",  
  "result": null  
}
```

Return error example:

json

```
{  
  "code": 12005,  
  "message": "Fail to send command. Result code: 226",  
  "result": null  
}
```

6. Geofencing Function

6.1 Create Geo-fence for IMEI

6.1.1 Description

Create Geo-fence for IMEI

6.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.device.fence.create

6.1.3 HTTP Request method

POST

6.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		accesstoken: used for identifying legal third party
imei	string	Yes	-	Device Imei
fence_name	string	Yes	-	Geo-fence name
alarm_type	string	Yes	-	Alarm type (in / out / in, out)
report_mode	string	Yes	-	Alarm reporting mode, 0: GPRS,1: SMS+GPRS
alarm_switch	string	Yes	-	Fence alarm switch(ON/OFF)
lng	string	Yes	-	Longitude
lat	string	Yes	-	latitude
radius	string	Yes	-	Fence radius(1~ 9999; unit: 100 meters)
zoom_level	string	Yes	-	Zoom level (3-19)
map_type	string	Yes	-	Map (GOOGLE)

6.1.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message

Key	Type	Description
result	string	The returned data. Fence serial number returned if succeed.

Correct return example:

json

```
{
  "code": 0,
  "message": "Successfully create geo-fence.",
  "result": "5"
}
```

Return error example:

json

```
{
  "code": 41003,
  "message": "Device is not online, geo-fence creation failed ",
  "result": null
}
```

6.2 Delete Geo-fence for device

6.2.1 Description

Delete Geo-fence for device.

6.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.device.fence.delete

6.2.3 HTTP Request method

POST

6.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		accesstoken: used for identifying legal third party
imei	string	Yes	-	Device imei
instruct_no	string	Yes	-	Geo-fence command serial number

6.2.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned data

Correct return example:

json

```
{
  "code": 0,
  "message": "delete the geo-fence successfully",
  "result": null
}
```

Return error example:

json

```
{
  "code": 41003,
  "message": "The device is not online and geo-fence can't be deleted",
  "result": null
}
```

6.3 Create platform Geo-fence

6.3.1 Description

Create a platform geofence, the newly created platform geofence belongs to the default group.

6.3.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.fence.create

6.3.3 HTTP Request method

POST

6.3.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal thi
account	string	Yes	-	The account to which the new fence belo
fence_name	string	Yes	-	The name of the new fence
fence_type	string	Yes	circle or polygon	Fence type (circle/polygon)
fence_color	string	No	default: #3B7AFF	Fence color, standard RGB16 color columr
geom	string	Yes	-	Collection of coordinate points Polygon: Latitude and longitude are separ locations are separated by '#', such as: 22.581714259546697,113.894600679447! 341832019817 (Need to transcode to Mar Round: 22.57540001979625, 113.888148C Note: latitude comes before longitude
radius	string	No	200-5000 default: 200	Fence radius, in m, range 200m~5000m, v be passed in, otherwise it will become a p

Parameter	Type	Required	Remark	Description
description	string	No	-	fence description

6.3.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1114: Fence name already exists -1:The system is busy Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	null
data	string	The returned data. fence_id returned if succeed.

Correct return example:

json

```
{  
  "code": 0,  
  "message": "success",  
  "result": null,  
  "data": "c33b80d46d2b41d588a5afbd6f8b6285"  
}
```

Return error example:

json

```
{  
  "code": 1114,  
  "message": "That name already exists ",  
  "result": null,  
  "data": null  
}
```

6.4 Edit platform Geo-fence

6.4.1 Description

Edit platform geofence informatio.

6.4.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.fence.create

6.4.3 HTTP Request method

POST

6.4.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal thi
account	string	Yes	-	The account to which the fence belongs
fence_id	string	Yes	-	Fence id that needs to be edited
fence_name	string	Yes	-	The name of the new fence
fence_type	string	Yes	circle or polygon	Fence type (circle/polygon)
fence_color	string	No	default: #3B7AFF	Fence color, standard RGB16 color columr
geom	string	Yes	-	Collection of coordinate points Polygon: L separated by commas, and multiple locati as: 22.581714259546697,113.894600679447! 341832019817 (Need to transcode to Mar: Round: 22.57540001979625, 113.888148C Note: latitude comes before longitude

Parameter	Type	Required	Remark	Description
radius	string	No	200-5000 default: 200	Fence radius, in m, range 200m~5000m, must be passed in, otherwise it will become a p
description	string	No	-	fence description

6.4.5 Response

key	Type	Description
code	int	Return code: 0: return correctly -1:The system is busy Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	null
data	string	The returned data. fence_id returned if succeed.

Correct return example:

json

```
{  
  "code": 0,  
  "message": "success",  
  "result": null,  
  "data": "c33b80d46d2b41d588a5afbd6f8b6285"  
}
```

Return error example:

json

```
{  
  "code": -1,  
  "message": "The system is busy ",  
  "result": null,  
  "data": null  
}
```

6.5 Delete platform Geo-fence

6.5.1 Description

Delete platform geofence.

6.5.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.fence.delete

6.5.3 HTTP Request method

POST

6.5.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
account	string	Yes	-	The account to which the new fence belongs
fence_id	string	Yes	-	Fence id that needs to be deleted

6.5.5 Response

key	Type	Description
code	int	Return code: 0: return correctly -1:The system is busy Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	null
data	string	null

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": null
}
```

Return error example:

json

```
{
  "code": -1,
  "message": " The system is busy ",
  "result": null,
  "data": null
}
```

6.6 Geo-fence related device

6.6.1 Description

Geofence related device.

6.6.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.fence.bind

6.6.3 HTTP Request method

POST

6.6.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third
fence_id	string	Yes	-	
imeis	string	No	-	Example values:869247060001770,8692470600012
alert_type	string	No	-	Alarm types, if multiple alarms are configured, separate them with commas "," 1.in: into the fence; 2.out: out of the fence; 3.stayTimeIn: If you do not enter the fence, the alarm will be triggered; 4.stayTimeOut: If you do not leave the fence for more than N days, the alarm will be triggered;
stay_time_in	int	No	-	Do not enter the fence for more than N days. When there is a value here, you need to pass alert_type.
stay_time_out	int	No		Do not leave the fence for more than N days alarm. When there is a value here, you need to pass stayTimeOut in alert_type.

6.6.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	null
data	string	The returned data. the number of related devices returned if succeed.

Correct return example:

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": "3"
}
```

Return error example:

```
{
  "code": 1100,
  "message": "Business exception ",
  "result": null,
  "data": null
}
```

6.7 List platform geofences of an account

6.7.1 Description

Query platform geofences of a specified account.

6.7.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.fence.list

6.7.3 HTTP Request method

POST

6.7.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
account	string	Yes	-	The account to which the geofences belong
page_no	number	No	>=1 default:1	Page number
page_size	number	No	1-50 default:10	Records in one page.

6.7.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	object	Number of fences belonging to the account and details of each fence

result:

Parameter	Type	Description
total	string	Number of fences belonging to the account
rows	Array[Object]	The returned data

Rows list:

Parameter	Type	Description
fence_id	string	Fence_id
fence_name	string	The name of the geofence
fence_type	string	Fence type (circle/polygon)

Parameter	Type	Description
fence_color	string	default: #3B7AFF
coordinates	string	Collection of coordinate points Polygon: Latitude and longitude are separated by commas, and multiple locations are separated by ';', such as: 22.581714259546697,113.89460067944759;22.57323797629247,113.8341832019817 (Need to transcode to Mars coordinate system) Round: 22.57540001979625, 113.88814802356858 Note: latitude comes before longitude
radius	string	Fence radius, in m, range 200m~5000m, When it is a circle, it needs to be passed in, otherwise it will become a polygon
description	string	fence description
imeis	string	Example values:869247060001770,869247060001259,869247060001804
alert_type	string	Alarm types, separated by commas 1.in: into the fence; 2.out: out of the fence; 3.stayTimeIn: If you do not enter the fence for more than N days, the alarm will be triggered; 4.stayTimeOut: If you do not leave the fence for more than N days, the alarm will be triggered;
stay_time_in	int	Do not enter the fence for more than N days to trigger an alarm. When there is a value here, you need to pass in stayTimeIn in the alert_type.
stay_time_out	int	Do not leave the fence for more than N days to trigger an alarm. When there is a value here, you need to pass in stayTimeOut in alert_type.
account	string	account

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": {
    "total": 294,
```

```

"rows": [
  {
    "fence_id": "dfab43ea3e7a40e987056c857cccae7b",
    "fence_name": "test fence",
    "fence_type": "circle",
    "fence_color": "#3b7aff",
    "coordinates": "22.544382,114.004037",
    "radius": "4153",
    "description": "",
    "imeis": "231011234567990,869247060001655,868598060001827,8692470600",
    "alert_type": "in",
    "stay_time_out": null,
    "stay_time_in": null,
    "account": "hao001"
  }
]
}

```

Return error example:

json

```

{
  "code": -1,
  "message": "The system is busy ",
  "result": null,
  "data": null
}

```

6.8 Query single fence information

6.8.1 Description

Query single fence information based on fence id

6.8.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.fence.detail

6.8.3 HTTP Request method

POST

6.8.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
fence_id	string	Yes	-	Unique id of fence

6.8.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	object	Detailed information of fence

result:

Parameter	Type	Description
fence_id	string	Fence_id
fence_name	string	The name of the geofence
fence_type	string	Fence type (circle/polygon)
fence_color	string	default: #3B7AFF
coordinates	string	Collection of coordinate points Polygon: Latitude and longitude are separated by commas, and multiple locations are separated by ';', such as: 22.581714259546697,113.89460067944759;22.57323797629247,113.8

Parameter	Type	Description
		341832019817 (Need to transcode to Mars coordinate system) Round: 22.57540001979625, 113.88814802356858 Note: latitude comes before longitude
radius	string	Fence radius, in m, range 200m~5000m, When it is a circle, it needs to be passed in, otherwise it will become a polygon
description	string	fence description
imeis	string	Example values: 869247060001770, 869247060001259, 869247060001804
alert_type	string	Alarm types, separated by commas 1.in: into the fence; 2.out: out of the fence; 3.stayTimeIn: If you do not enter the fence for more than N days, the alarm will be triggered; 4.stayTimeOut: If you do not leave the fence for more than N days, the alarm will be triggered;
stay_time_in	int	Do not enter the fence for more than N days to trigger an alarm. When there is a value here, you need to pass in stayTimeIn in the alert_type.
stay_time_out	int	Do not leave the fence for more than N days to trigger an alarm. When there is a value here, you need to pass in stayTimeOut in alert_type.
account	string	account

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": {
    "fence_id": "dfab43ea3e7a40e987056c857cccae7b",
    "fence_name": "test fence",
    "fence_type": "circle",
    "fence_color": "#3b7aff",
    "coordinates": "22.544382,114.004037",
    "radius": "4153",
    "description": ""
  }
}
```

```
"imeis": "231011234567990,869247060001655,868598060001827,869247060001259",
"alert_type": "in",
"stay_time_out": null,
"stay_time_in": null,
"account": "hao001"
}
}
```

Return error example:

json

```
{
  "code": -1,
  "message": "The system is busy ",
  "result": null,
  "data": null
}
```

7. Push Function

7.1 Receive Notification

7.1.1 Description

Please develop a service that supports submitting data in **x-www-form-urlencoded** format via POST requests, and provide the access URL of the service. JIMI server will push the notification by sending a HTTP request using this URL.

7.1.2 Message service List

Message Type	Description
jimi.push.device.alarm	Alarm data

Request content:

Key	Type	Description
msgType	String	Message type, corresponding to the message service list
data	String	The content of the message, corresponding to msgType

7.1.3 Message content (jimi.push.device.alarm)

Alarms pushed are as follows

Key	Type	Description
imei	string	Device imei
deviceName	string	Device name
alarmType	string	Alarm type Corresponding to alertType in the appendix
alarmName	string	Alarm name Corresponding to alertType in the appendix
lat	string	Latitude
lng	string	Longitude
alarmTime	string	Alarm time, format (yyyy-MM-dd HH: mm: ss)

E.g:

Parameter1:

Key = msgType

Value = jimi.push.device.alarm

Parameter2:

Key = data

Value = {

"imei": "868120145233604",

"deviceName": "868120145233604",

"alarmType": "2",

"alarmName": "Power off alarm",

"lat": 40.65615416521587,

"lng": 109.89894039833524,

"alarmTime": "2017-05-08 12:00:00"

}

7.2 Push Received Raw Data

7.2.1 Description

Third-party platform should provide an URL(same as messages push URL) to receive the raw data(please contact us and provide the URL manually), JIMI server will push the raw data by sending a HTTP request using this URL.

7.2.2 Message service List

Message Type	Description
jimi.open.instruction.raw.receive	Raw data receive message type, different from alarm message.

Request content:

Key	Type	Description
msgType	string	Message type, corresponding to the message service list
data	string	The content of the message, corresponding to msgType

7.2.3 Message content (jimi.open.instruction.raw.receive)

Alarms pushed are as follows:

Key	Type	Description
imei	string	Device imei
deviceName	string	Device name
raw_data	string	raw data from device.(hex string)

E.g:

Parameter1:

Key = msgType

Value = jimi.open.instruction.raw.receive

Parameter2:

Key = data

Value = {

```
"imei": "868120145233604",  
"deviceName": "868120145233604",  
"raw_data": "0A0C0F01182E0101"  
}
```

8. OBD

8.1 Get the OBD data of devices

8.1.1 Description

Query CAN bus diagnosis data reported by OBD device.

8.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.obd.list

8.1.3 HTTP Request method

POST

8.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal th
account	string	Yes	-	The account to which the new fence belc
imeis	string	Yes	-	Device imei(s), separate by comma. No n time.Supports querying the data of the ac account devices.Example values:869247060001770,86924706000
start_time	string	Yes	-	Start time Format: yyyy-MM-dd HH:mm:ss
end_time	string	Yes	-	End time Format: yyyy-MM-dd HH:mm:ss earlier than current time. Query up to 31 days of data at a time.

Parameter	Type	Required	Remark	Description
page_no	int	Yes	>=1 default:1	Page number
page_size	int	Yes	1-100 default:10	Recordsin one page.

8.1.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
data	object	The returned data.

data list:

key	Type	Description
currentPage	int	The current page, same as page_no.
pageSize	int	Recordsin one page, same as page_size.
totalRecord	int	Total rows
result	array[object]	Data details

result list:

key	Type	Description
imei	string	Imei of device
dataReportTime	string	The time the data was reported
odometerReading	string	Vehicle meter mileage(Unit: KM)
deviceAccumulatedMileage	string	Mileage counted by the device

key	Type	Description
remainingFuel	string	Oil volume
remainingFuelPercentage	string	Oil percentage The data reported by different vehicles and devices are different. The Oil volume or Oil percentage is displayed based on the data actually reported by the device.
coolantTemperature	string	Coolant temperature(Unit: °C)
vehicleBatterVoltage	string	External input voltage
currentRPM	string	Instantaneous engine speed
currentSpeed	string	Current driving speed
vin	string	Vehicle Identification Number

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "data": {
    "currentPage": 1,
    "pageSize": 2,
    "startRow": 0,
    "endRow": 0,
    "totalRecord": 2684,
    "totalPage": 0,
    "result": [
      {
        "imei": "158511020000028",
        "dataReportTime": "2024-05-09 10:25:00",
        "odometerReading": "2049.6",
        "deviceAccumulatedMileage": "142.9",
        "remainingFuel": null,
        "remainingFuelPercentage": "58",
        "coolantTemperature": "77",
        "vehicleBatterVoltage": "118",
        "currentRPM": "5016",
        "currentSpeed": "88.5",
```

```
        "vin": "LC0CG4CF1H0029191"
      },
      {
        "imei": "158511020000028",
        "dataReportTime": "2024-05-09 1:27:23",
        "odometerReading": "2048.6",
        "deviceAccumulatedMileage": "143.9",
        "remainingFuel": null,
        "remainingFuelPercentage": "56",
        "coolantTemperature": "78",
        "vehicleBatterVoltage": "118",
        "currentRPM": "5016",
        "currentSpeed": "95.5",
        "vin": "LC0CG4CF1H0029191"
      }
    ]
  }
}
```

Return error example:

json

```
{
  "code": 1100,
  "message": "Business exception ",
  "result": null,
  "data": null
}
```

8.2 Get the OBD fault data of devices

8.2.1 Description

Query CAN bus fault code information reported by OBD device.

8.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.obd.fault

8.2.3 HTTP Request method

POST

8.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal th
account	string	Yes	-	The account to which the new fence belc
imeis	string	Yes	-	Device imei(s), separate by comma. No n time.Supports querying the data of the ac account devices.Example values:869247060001770,86924706000
start_time	string	Yes	-	Start time Format: yyyy-MM-dd HH:mm:ss
end_time	string	Yes	-	End time Format: yyyy-MM-dd HH:mm:ss earlier than current time. Query up to 31 days of data at a time.
page_no	int	Yes	>=1 default:1	Page number
page_size	int	Yes	1-100 default:10	Recordsin one page.

8.2.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
data	object	The returned data.

data list:

key	Type	Description
currentPage	int	The current page, same as page_no.
pageSize	int	Recordsin one page, same as page_size.
totalRecord	int	Total rows
result	array[object]	Data details

result list:

key	Type	Description
imei	string	lmei of device
deviceName	string	Device name
faultCode	string	The fault code of the fault
faultDetail	string	Fault detailed description
eventTime	string	Time when the fault was reported

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": {
    "currentPage": 1,
    "pageSize": 4,
    "startRow": 0,
    "endRow": 0,
    "totalRecord": 6,
    "totalPage": 0,
    "result": [
      {
        "imei": "2025099999999994",
        "deviceName": "VL502_E-99994",
```



```

        "faultCode": "P1502",
        "faultDetail": "High speed state of the vehicle - the front axle is
        "eventTime": "2024-07-03 08:16:49"
    },
    {
        "imei": "2025099999999994",
        "deviceName": "VL502_E-99994",
        "faultCode": "B0074",
        "faultDetail": "2nd row center seat belt pretensioner - start contro
        "eventTime": "2024-07-03 08:26:49"
    },
    {
        "imei": "2025099999999994",
        "deviceName": "VL502_E-99994",
        "faultCode": "P2407",
        "faultDetail": "Fuel evaporative emission system leak detection pump
        "eventTime": "2024-07-03 08:36:49"
    },
    {
        "imei": "2025099999999994",
        "deviceName": "VL502_E-99994",
        "faultCode": "U0464",
        "faultDetail": "Invalid data received from the navigation control mo
        "eventTime": "2024-07-03 08:46:49"
    }
]
}
}

```

Return error example:

json

```

{
    "code": 1100,
    "message": "Business exception ",
    "result": null,
    "data": null
}

```

9. Reports

9.1 Get entry and exit fence data of devices

9.1.1 Description

Query the report data of the device's entry and exit fence.

9.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.fence.duration

9.1.3 HTTP Request method

POST

9.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third
account	string	Yes	-	The account to which the new fence belongs
imeis	string	Yes	-	Example values: 869247060001770,869247060001259,869
start_time	string	Yes	-	Start time Format: yyyy-MM-dd HH:mm:ss
end_time	string	Yes	-	End time Format: yyyy-MM-dd HH:mm:ss end_time should be earlier than current time
start_row	string	Yes	-	Row number of result set.
page_size	string	Yes	-	Records in one page.

9.1.5 Response

key	Type	Description
code	int	Return code: 0: return correctly

key	Type	Description
		1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
data	object	The returned data.

data list:

key	Type	Description
totalTime	string	Request processing time
dataTotalRows	string	Total rows
rows	array[object]	Data details

rows list:

key	Type	Description
imei	string	Imei of device
deviceName	string	Device name
fenceName	string	Fence name
enterTime	string	Enter fence time
exitTime	number	Leave fence time
duration	number	Duration

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": {
    "totalTime": "0",
    "dataTotalRows": "2",
```

```

    "rows": [
      {
        "imei": "869247060001739",
        "deviceName": "JC450Pro-01739",
        "fenceName": "geofence1",
        "enterTime": "2022-12-10T01:05:33.000Z",
        "exitTime": "2022-12-10T04:17:48.000Z",
        "duration": "11535"
      },
      {
        "imei": "869247060001739",
        "deviceName": "JC450Pro-01739",
        "fenceName": "geofence1",
        "enterTime": "2022-12-10T01:05:33.000Z"
      }
    ]
  }
}

```

Return error example:

json

```

{
  "code": 1100,
  "message": "Business exception ",
  "result": null,
  "data": null
}

```

9.2 Get the trips report data of devices

9.2.1 Description

Query the trips report data of devices.

9.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.report.trips

9.2.3 HTTP Request method

POST

9.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
account	string	Yes	-	The account to which the new fence belongs
imeis	string	Yes	-	Example values: 869247060001770,869247060001259,869247060001259
type	string	Yes	-	day/list When type is day, the device itinerary data is returned by day. When it is list, the detailed data of the device is summarized and returned.
start_time	string	Yes	-	Start time Format: yyyy-MM-dd HH:mm:ss
end_time	string	Yes	-	End time Format: yyyy-MM-dd HH:mm:ss end_time should be earlier than current time
start_row	string	Yes	-	Row number of result set.
page_size	string	Yes	-	Records in one page.

9.2.5 Response

key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
data	object	The returned data.

data list:

key	Type	Description
dayList	array[object]	When type = list, the array is returned
datDatas	array[object]	When type = day, the array is returned

datDatas list:

key	Type	Description
deviceName	string	Device Name
deviceImei	string	Device imei
data	object	

datDatas.data:

key	Type	Description
date	string	Date
totalTrips	string	Total number of trips on the day
averageSpeed	string	Average speed
fuel	string	Fuel consumption
maxSpeed	string	Maximum speed
oilWear	string	Fuel consumption per 100 kilometers
totalMileage	string	Total mileage
travelTime	string	Total trip time

dayList list:

key	Type	Description
imei	string	Imei of device
deviceName	string	Device name

key	Type	Description
tripsData	Array[object]	Trip information, see the table below for details
inTotal	object	Trip information summary: allTrips: total number of trips totalDis: total mileage travelTime: total running time totalTime: formatted total running time totalAvgSpeed: average speed allTotalMaxSpeed: maximum average speed totalFuel: total fuel consumption oilWear: fuel consumption per 100 kilometers

dayList.tripsData:

key	Type	Description
Searchdate	string	date
tripNum	number	Number of trips on the day
inTotal	object	Data summary for the day : totalDis: total mileage travelTime: total running time totalTime: formatted total running time totalAvgSpeed: average speed allTotalMaxSpeed: maximum average speed totalFuel: total fuel consumption oilWear: fuel consumption per 100 kilometers
dayData	Array[object]	For each itinerary information, please see the table below for detailed information

dayList.tripsData.dayData:

key	Type	Description
imei	string	Device imei
startTime	string	Start time of the trip
endTime	string	End time of the trip

key	Type	Description
startLat	string	Start latitude of the trip
startLng	string	Start longitude of the trip
endLat	string	End latitude of the trip
endLng	string	End longitude of the trip
totalMileage	string	Mileage of the trip
travelTime	string	Time
averageSpeed	string	Average speed
maxSpeed	string	Maximum speed
oilWear	string	Fuel consumption per 100 kilometers
fuel	string	Fuel consumption
startMileage	string	Start mileage
endMileage	string	End mileage

Correct return example:

json

Return error example:

json

```
{
  "code": 1100,
  "message": "Business exception ",
  "result": null,
  "data": null
}
```

9.3 Get device alarm list

9.3.1 Description

Get device alarm list. Time range of searching criteria should be within 1 month. Return maximum 1000 rows.

9.3.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.alarm.list

9.3.3 HTTP Request method

POST

9.3.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes		accesstoken: used for identifying legal third party
imei	string	Yes	-	Device imei: This field can be used when querying a single device.
alertTypeId	string	No		If not specify alertTypeId , all alert type will return.
begin_time	date	No		if not provide begin_time & end_time, returns latest 50 alerts of last 1 month.
end_time	date	No		
imeis	string	Yes		Device imei(s), separate by comma.Query single or multiple devices No more than 100 each time. Select one of the IMEI and IMEIS fields to fill in.
page_no	int	Yes	>=1 default:1	Page number

Parameter	Type	Required	Remark	Description
page_size	int	Yes	1-100 default:50	Records in one page.

9.3.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned data

Result list:

Key	Type	Description
deviceName	string	Device Name
imei	string	IMEI
model	string	Device Model
account	string	Account
alertTypeId	string	Alert type ID
alertTypeName	string	Alert type name
alertTime	string	Alert time
positioningTime	string	Time of alert positioning
lng	double	longitude
lat	double	latitude
speed	string	speed
geoid	string	Fence ID

Correct return example:

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "deviceName": "ABC-34352",
      "imei": "343503422910345",
      "model": "GT06N",
      "account": "test1234",
      "alertTypeId": "1002",
      "alarmTypeName": "ACC On",
      "alertTime": "2019-03-14 14:02:03",
      "positioningTime": "2019-03-14 14:02:03",
      "lat": 22.577144898887813,
      "lng": 113.91674845964586,
      "speed": "10",
      "geoid": "se8yg081p0qh5vnniqrakr1nr0tdh6a0"
    }
  ]
}
```

Return error example:

```
{
  "code":xxx,
  "message": "Illegal device"
}
```

9.4 Get RFID reporting information

9.4.1 Description

Query the RFID information reported within a certain period of time.

9.4.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.device.rfid.list

9.4.3 HTTP Request method

POST

9.4.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
account	string	Yes	-	The account to which the device belongs. If the device to be queried belongs to multiple different users, please enter the common superior account of these users here.
imeis	string	No	-	Device imei(s), separate by comma.No more than 100 each time If neither imei nor card id is entered, all RFID reporting records within the query time period will be queried.
card_ids	string	No	-	RFID(s),separate by comma.No more than 100 each time If neither imei nor card id is entered, all RFID reporting records within the query time period will be queried.
begin_time	number	Yes	-	Start time Format: yyyy-MM-dd HH:mm:ss
end_time	number	Yes	-	End time Format: yyyy-MM-dd HH:mm:ss end_time should be earlier than current time Query up to 1 month of data at a time
page_no	int	no	>=1 default:1	Page number

Parameter	Type	Required	Remark	Description
page_size	int	no	1-100 default:10	Records in one page.

9.4.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
data	object	The returned parameters

data object:

Key	Type	Description
currentPage	number	Current page code
pageSize	number	Records in one page.
totalRecord	number	Total amount of data that meets the conditions
result	Array[Object]	The returned data

result list:

Key	Type	Description
cardId	string	The corresponding RFID in the reporting record
imei	string	RFID record reporting corresponding imei
photo	string	Photo taken by the device during RFID reporting
operationTime	string	RFID record reporting time

Correct return example:

```
{
  "code": 0,
  "message": "success",
  "data": {
    "currentPage": 1,
    "pageSize": 10,
    "startRow": 1,
    "endRow": 10,
    "totalRecord": 34,
    "totalPage": 4,
    "result": [
      {
        "imei": "890768902346789",
        "cardId": "278907",
        "operationTime": "2024-04-22 09:12:23",
        "photo":
      }
    ]
  }
}
```

Return error example:

```
{
  "code": "xxx",
  "message": "no permissions"
}
```

9.5 Retrieve Health Data

9.5.1 Description

Retrieve health data.

9.5.2 Request URL

[See the unique request URL.](#)

Method = jimi.device.health.data

9.5.3 HTTP Request method

POST

9.5.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
imei	string	Yes	-	Device imei
query_type	String	Yes		day: query today's data; week: query data within a week; month: query data within a month

9.5.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	
data	object	The returned parameters

data object

Key	Type	Description
currentSteps	int	Last reported steps

Key	Type	Description
currentBloodOxygen	int	Last reported blood oxygen
currentHearRate	int	Last reported heart rate
historyHealthVOList	array[object]	Health report data

historyHealthVOList list

Key	Type	Description
avgBloodOxygen	int	Average blood oxygen
avgHeartRate	int	Average heart rate
postTime	string	Statistical time
step	int	Steps

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": {
    "currentSteps": 327,
    "currentBloodOxygen": 99,
    "currentHeartRate": 70,
    "historyHealthVOList": [
      {
        "avgBloodOxygen": 0,
        "avgHeartRate": 0,
        "postTime": "2025-11-04 00:00:00",
        "step": 0
      },
      {
        "avgBloodOxygen": 97,
        "avgHeartRate": 91,
        "postTime": "2025-11-04 01:00:00",
        "step": 0
      }
    ]
  }
}
```



```
        "avgBloodOxygen": 98,  
        "avgHeartRate": 95,  
        "postTime": "2025-11-04 02:00:00",  
        "step": 0  
    },  
    {  
        "avgBloodOxygen": 98,  
        "avgHeartRate": 84,  
        "postTime": "2025-11-04 03:00:00",  
        "step": 50  
    },  
    {  
        "avgBloodOxygen": 98,  
        "avgHeartRate": 70,  
        "postTime": "2025-11-04 06:00:00",  
        "step": 327  
    }  
],  
"healthPostTime": "2025-11-04 06:28:55"  
}  
}
```

Return error example:

json

9.6 Retrieve DLT Report Information

9.6.1 Description

Retrieve DLT report information.

9.6.2 Request URL

[See the unique request URL.](#)

Method = jimi.open.platform.dlt.report

9.6.3 HTTP Request method

POST

9.6.4 Request parameters

(1) [Common parameters](#)

(2) Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	accesstoken: used for identifying legal third party
start_time	string	Yes	-	Start time yyyy-MM-dd HH:mm:ss
end_time	string	Yes	-	End time yyyy-MM-dd HH:mm:ss
imei	string	No	-	Device imei
dlt	string	No		DLT card number

9.6.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly 1100:Business exception Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	
data	array[object]	The returned parameters

data list

Key	Type	Description
deviceName	string	Device name
deviceStatus	int	Visa status: 1 for check-in, 2 for check-out
driverNo	string	Driver number
driverName	string	Driver name

Key	Type	Description
numberPlate	string	License plate number
status	int	Card swiping status: 1 for alarm, 0 for normal
operationTime	string	Operation time (UTC time zone)
coordinates	string	Longitude and latitude
imei	string	Device IMEI
dlt	string	DLT card number

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": null,
  "data": [
    {
      "deviceName": "JC371-00643",
      "deviceStatus": 1,
      "driverNo": null,
      "driverName": null,
      "numberPlate": null,
      "status": 0,
      "operationTime": "2025-10-27 10:43:07",
      "coordinates": "113.943096,22.576624",
      "imei": "865478070000643",
      "dlt": "232000455700107"
    },
    {
      "deviceName": "JC371-00643",
      "deviceStatus": 2,
      "driverNo": null,
      "driverName": null,
      "numberPlate": null,
      "status": 0,
      "operationTime": "2025-10-27 10:42:09",
      "coordinates": "113.943108,22.576613",
      "imei": "865478070000643",

```

```
      "dlt": "232000455700107"
    },
    {
      "deviceName": "JC371-00643",
      "deviceStatus": 1,
      "driverNo": null,
      "driverName": null,
      "numberPlate": null,
      "status": 0,
      "operationTime": "2025-10-27 10:41:07",
      "coordinates": "113.943113,22.576603",
      "imei": "865478070000643",
      "dlt": "232000455700107"
    }
  ]
}
```

Return error example:

json

10. Account Management

10.1 List all sub-account

10.1.1 Description

List all sub-account of a specified account.

10.1.2 Request URL

[See the unique request URL.](#)

Method = jimi.user.child.list

10.1.3 HTTP Request method

POST

10.1.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	Access token for security access JIMI Server.
target	string	Yes	-	The specified account for inquired.

10.1.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	Array[Object]	The returned parameters

result

key	Type	Description
account	string	log in account
name	string	name
type	int	Account Type 3: App user 8: Distributor 9: ordinary users 10: ordinary distributor 11: sales
displayFlag	int	Available or not (1:Available,0:not available)
address	string	location
birth	string	birthday
companyName	string	Company Name

key	Type	Description
email	string	mailbox
phone	string	contact number
language	string	Language (zh,en)
sex	int	Gender 0 male, 1 female
enabledFlag	int	Flag:1 Available, 0not available
remark	string	Remark

Correct return example:

json

```
{
  "code": 0,
  "message": "success",
  "result": [
    {
      "account": "123123",
      "name": "test",
      "type": 8,
      "displayFlag": 1,
      "address": null,
      "birth": "2017-04-22 00:00:00",
      "companyName": "",
      "email": "",
      "phone": "",
      "language": "zh",
      "sex": 0,
      "enabledFlag": 1,
      "remark": null
    }
  ]
}
```

Return error example:

json

```
{
  "code": "xxx",
```

```
"message": "The account does not exist"
}
```

10.2 Create sub-account

10.2.1 Description

Create a sub-account of a specified account.

10.2.2 Request URL

[See the unique request URL.](#)

Method = jimi.user.child.create

10.2.3 HTTP Request method

POST

10.2.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	Access token for security access JIMI Server.
super_account	string	No	-	The specified parent account. If not provided, use API account instead.
account_id	string	Yes		Account id, length of 3~30 characters. Support special characters like "_@." as well as a - Z, 0 - 9.
nick_name	string	Yes		Nick name or customer name
account_type	int	Yes		1 - Distributor 2 - End User 3 - Sales
password	string	Yes		Password with md5.

Parameter	Type	Required	Remark	Description
telephone	string	No		
Email	string	Yes		User could retrieve password if forgot it.
contact_person	string	No		
company_name	string	No		
permissions	string	Yes		6 permissions can be set: Web Login App Login Send Command Set Working Mode Edit by Web Edit by App 0 - disable, 1 - enable, 6 digital represents 6 kinds of permissions enable/disable perssion. For example, 111000

10.2.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned parameters

Correct return example:

json

```
{
  "code": 0,
  "message": "Vehicle information modification successful",
  "result": null
}
```


Return error example:

json

```
{
  "code": "xxx",
  "message": "The account does not exist"
}
```

10.3 Move account

10.3.1 Description

Move account from one sub-account to another sub-account.

10.3.2 Request URL

[See the unique request URL.](#)

Method = jimi.user.child.move

10.3.3 HTTP Request method

POST

10.3.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	Access token for security access JIMI Server.
account	string	Yes	-	The account will be moved.
target_account	string	Yes		The target account to move in.

10.3.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned parameters

Correct return example:

json

```
{
  "code": 0,
  "message": "Vehicle information modification successful",
  "result": null
}
```

Return error example:

json

```
{
  "code": "xxx",
  "message": "no permissions"
}
```

10.4 Remove sub-account

10.4.1 Description

Remove a sub-account of a specified account.

10.4.2 Request URL

[See the unique request URL.](#)

Method = jimi.user.child.del

10.4.3 HTTP Request method

POST

10.4.4 Request parameters

(1) [Common parameters](#)

(2) Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	Access token for security access JIMI Server.
super_account	string	No	-	The specified parent account. If not provided, use API account instead.
account_id	string	Yes		Account id, length of 3~30 characters. Support special characters like "_@." as well as a - Z, 0 - 9.

10.4.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned parameters

Correct return example:

json

```
{
  "code": 0,
  "message": "Vehicle information modification successful",
  "result": null
}
```

Return error example:

json

```
{
  "code": "xxx",
```

```
"message": "no permissions"
}
```

10.5 Edit user information

10.5.1 Description

Edit the user information of the platform, only edit the user's nickname, mobile phone number, email address, contact person, company name and permissions.

10.5.2 Request URL

[See the unique request URL.](#)

Method = jimi.user.child.update

10.5.3 HTTP Request method

POST

10.5.4 Request parameters

(1)[Common parameters](#)

(2)Private parameters as follow:

Parameter	Type	Required	Remark	Description
access_token	string	Yes	-	Access token for security access JIMI Server.
edit_account	String	Yes		Account name, length of 3~30 characters. Support special characters like "_@." as well as a-Z, 0-9.
nick_name	String	Yes		Nick name or customer name
telephone	String	No		
Email	String	Yes		User could retrieve password if forgot it.
contact_person	String	No		contact

Parameter	Type	Required	Remark	Description
company_name	String	No		Company name
permissions	String	Yes		Web Login App Login Send Command Set Working Mode Edit by Web Edit by App 6 digital represents enable/disable perssion.

10.5.5 Response

Key	Type	Description
code	int	Return code: 0: return correctly Other: failure. Refer to the error code description
message	string	If code is not 0, there will be a corresponding error message
result	string	The returned data,could be multiple rows.

*Remark: Unix timestamp; Example: 1611105520 = 2021-01-20 09:18:40** **Correct return example:**

json

```
{
  "code": 0,
  "message": "Account update success!",
  "result": null,
  "data": null
}
```

Return error example:

json

11.Appendix

Device alarm type

The alertTypeld of the alarm type actively reported by the device is a number.

The alertTypeld of the alarm generated after platform logic judgment is English text.

alertTypeld	alertType
1	SOS alert
10	Enter GPS blind zone alert
100	Cancel Notification for Temperature Alert
101	Cancel Notification for Collision Alert
11	Exit GPS blind zone alert
113	Increase in oil level
114	Install alert
115	Oil Sence Timeout
119	High voltage at ADC1
12	Booting notification
120	Low voltage at ADC1
126	High humidity
127	Low humidity
128	DVR vibration alert
13	GPS first fix notification
135	Overspeed alert(DVR)
136	Power off alert(DVR)
138	Immobilization ON
139	Immobilization OFF
14	Low external power alert
140	Close eyes Alert
141	Switch Land Transport Mode Alarm

alertTypeid	alertType
142	Environmental Anomaly Alarm
143	Distraction Alert
144	Sudden Acceleration Alert(DVR)
145	Sudden Deceleration Alert(DVR)
146	Sharp Turn Alert(DVR)
147	Collision Alert(DVR)
148	No Face Alert
149	Switch Ocean Transport Mode Alarm
15	Low power protection alert
150	Switch Static Transport Mode Alarm
151	Phone Calling Alert
154	Smoking Alert
16	Sim card change alert
160	Yawn Alert
163	Head lowered
165	RFID reporting event
168	Engine failure
169	Undervoltage
17	Power off alert
170	Drinking
171	Light detected alert
172	Bluetooth MAC searched
173	Bluetooth MAC lost
18	Airplane mode after low power protection

alertTypeld	alertType
19	Disassembly alert
191	Device Plug-out Alert
197	Engine ON
198	Engine OFF
199	Overtime driving alert
2	Power cut off alert
20	Door detection alert
202	overspeed warning
203	Overtime parking warning
204	Forward collision warning
205	Lane departure warning
206	Vehicle too close warning
207	pedestrian collision warning
208	DMS fatigue warning
21	Battery low power shutdown
22	Voice alarm
224	Device Plug-in Alert
227	Overheating
230	INPUT1 was activated
231	INPUT1 was deactivated
232	INPUT2 was activated
233	INPUT2 was deactivated
24	Cover Move Alert
25	Internal low battery alert

alertTypeld	alertType
254	Ignition on
256	Fence entry alarm (Bluetooth)
257	Exit fence alarm (Bluetooth)
258	Fence entry alarm (WIFI)
259	Exit fence alarm (WIFI)
260	long periods of stillness
261	Start exercise reminder
262	Stop exercise reminder
263	LTE Jamming Detected
266	LTE Jamming Ended
267	GPS Jamming Detected
268	GPS Jamming Ended
28	Door open alert
29	Door close alert
3	Vibration alert
35	Fall Alert
36	Plug in charger
39	Unauthorized Open Alert
4	Enter geo-fence(terminal)
40	Initiative Offline(Power Off) Alert
41	Sudden Acceleration Alert
42	Sharp Turn Left Alert
43	Sharp Turn Right Alert
44	Collision Alert

alertTypeid	alertType
45	Vehicle Turn Over Alarm
48	Sudden Deceleration Alert
5	Exit geo-fence(terminal)
50	Device Pull Out Alarm
55	Collision Alert
58	Cancel Notification for Unauthorized Open Alert
6	Overspeed alert(terminal)
71	Fatigue driving alert
76	Sharp turn alarm
77	Abrupt lane switching alarm
78	Vehicle stability
79	Vehicle angle abnormality
80	Door close alert
81	Door open alert
82	Temperature Alert
83	Stealing oil alarm
86	Start charging
87	Stop charging/remove charger
89	full of reminders
9	Displacement alert(terminal)
90	Low battery alert
91	High Temperature Alert(terminal)
92	Low Temperature Alert(terminal)
ACC_OFF	ACC OFF

alertTypeld	alertType
ACC_ON	ACC ON
burglarStatus_0	Disarm
burglarStatus_1	Arm
burglarStatus_2	Alert
carFault	Vehicle fault alert
displacementAlarm	Night Driving Alert
DMSAlert	DMS Alert
drivingBehaviorAlert	Driving Behavior Alert
drivingBehaviorAlertDVR	Driving Behavior Alert(DVR)
fenceOverspeed	Fence Overspeed alert
geozone	Geo-fence alert
high_temp_alarm	High Temperature Alert(platform)
in	Enter geo-fence
laneshift	Route Deviation Alert
low_temp_alarm	Low Temperature Alert(platform)
mileageAlarm	Maintenance alert
obd	OBD alert
offline	Offline alert
other	Other alerts
out	Exit geo-fence
overSpeed	Overspeed alert(platform)
sensitiveAreasFence	Sensitive areas fence
statusLeftFrontDoors_0	Left front door close
statusLeftFrontDoors_1	Left front door open

alertTypeld	alertType
statusLeftFrontWindows_0	Left front window close
statusLeftFrontWindows_1	Left front window open
statusLeftRearWindows_0	Left rear door close
statusLeftRearWindows_1	Left rear door open
statusRightFrontDoors_0	Right front door close
statusRightFrontDoors_1	Right front door open
statusRightFrontWindows_0	Right front window close
statusRightFrontWindows_1	Right front window open
statusRightRearDoors_0	Right rear door close
statusRightRearDoors_1	Right rear door open
statusRightRearWindows_0	Right rear window close
statusRightRearWindows_1	Right rear window open
statusTrunk_0	Trunk close
statusTrunk_1	Trunk open
stayAlert	Parking alert
stayAlertOn	Idling alert
stayTimeIn	Long time not enter the Geo-fence
stayTimeOut	Long time not exit the Geo-fence
ubiAcce	Harsh acceleration
ubiColl	Collision
ubiDece	Harsh braking
ubiLane	Sudden lane change
ubiRoll	Rollover
ubiSatt	Roll and pitch

alertTypeld	alertType
ubiStab	Skidding
ubiTurn	Harsh cornering