

Reference excerpt 02-018

Source: arXiv:1604.05177v1 | License: CC BY 4.0 | Word window: 646-905

CSA of the IJV in correspondence of the waves a, c, x, v and y, during the i-th cycle are indicated by the parameters a_i , c_i , x_i , v_i and y_i . These parameters are detected on the JVP trace by means of an algorithm based on the following definitions: $a_1 = \max(CSA(t)) : 0 < t < T$
 $c_i = \max(CSA(t)) : t_{y_{i-1}} + t_{ya} - T_c < t < t_{y_{i-1}} + t_{ya} + T_c$
 $c_i = \max(CSA(t)) : t_{ai} + t_{ac} - T_c < t < t_{ai} + t_{ac} + T_c$
 $x_i = \min(CSA(t)) : t_{ai} + t_{ax} - T_c < t < t_{ai} + t_{ax} + T_c$
 $v_i = \max(CSA(t)) : t_{xi} + t_{xv} - T_c < t < t_{xi} + t_{cx} + T_c$
 $y_i = \min(CSA(t)) : t_{vi} + t_{vy} - T_c < t < t_{vi} + t_{vy} + T_c$
(1) Figure 1: The figure represents an illustrative sequence of three sonograms from a video-clip obtained by a transverse ultrasound scan of the IJV. In each picture it is visible the IJV (ellipses), the common carotid artery (circular) and the ECG trace (blue line). The active phase of the ECG is indicated by the red cursor. Below, it shows the IJV CSA trace obtained by measuring the CSA in cm^2 on each sonogram of the video-clip. The parameter ranges between 0 and 1 (typically 0.05) and serves to take account of heart rate variation (HRV) during acquisition. The t_{ai-1} is the