

Reference excerpt 02-030

Source: arXiv:1604.05177v1 | License: CC BY 4.0 | Word window: 1101-1360

10 % of the points are normally not properly detected by the algorithm, while it was possible to identify them manually (see Fig. 4). The parameters a_i , v_i , tax_i and tv_{yi} were calculated as in Eq. (2). The mean values and standard deviations of the parameters are presented in Table 1. JVP and ECG time relationship The time interval between the wave a and the events P and R and the wave x and the event T are calculated for each cardiac cycle. These intervals are denoted as: $taR_i = t_{ai} - t_{Ri}$ $taP_i = t_{ai} - t_{Pi}$ $txT_i = t_{xi} - t_{Ti}$ (3) 2 Table 1: Example of mean value and standard deviation of main JVP parameters are presented. a x v a v t a x t v y HR (cm²) (cm²) (cm²) (cm²) (cm²) (s) (s) Bpm 1.57 0.18 1.29 0.16 1.33 0.18 0.29 0.04 0.04 0.02 0.33 0.06 0.11 0.05 61 Table 2: Example of mean value and standard deviation of time intervals t_{aR} and t_{xT} averaged over several cardiac cycles. taR txT taP (s) (s) (s) 0,03 0,02 0,12 0,06 0.14 0.05 Figure 2: The figure shows an illustrative JVP trace during a cardiac cycle together with the ECG trace. The waves a, c, x, v and y of the JVP and the events P, R and T of the ECG are indicated. The average and the standard deviation of these three parameters is calculated. The mean values and standard deviations of the parameters taR , txT and