+24V_CTRL_OUT FROM DWG 005

1.1

COM0 COM1 COM2

PLC-01
LS XBC-DR32H
DIGITAL RELAY OUTPUT
24VDC INTERPOSING RELAY CONTROL

OUTPUT GROUP 0
COM0 → +24V_CTRL_OUT
P20 → K20 Coil
P21 → K21 Coil
P22 → K22 Coil
P23 → K23 Coil

OUTPUT GROUP 1
COM1 → +24V_CTRL_OUT
P24 → K24 Coil
P25 → K25 Coil
P26 → K26 Coil
P27 → K27 Coil

OUTPUT GROUP 2
COM2 → +24V_CTRL_OUT
P28 → K28 Coil
P29 → K29 Coil
P2A → SPARE
P2B → SPARE

P2C ~ P2F
SPARE OUTPUTS
RESERVED

SOL-01~SOL-04:
24VDC SOLENOID COIL.
INSTALL FLYBACK DIODE AT COIL TERMINALS UNLESS SUPPRESSION DIODE IS INTEGRATED.

D20~D29:
FLYBACK DIODE ACROSS 24VDC RELAY COIL.
CATHODE TO +24V SIDE, ANODE TO 0V SIDE.
OMIT EXTERNAL DIODE IF RELAY MODULE HAS INTERNAL POLARITY-SUPPRESSION DEVICE.

D20 P20 A1 A2 K20 24VDC
MTR-01 RUN COMMAND

D21 P21 A1 A2 K21 24VDC
MTR-01 DIRECTION COMMAND

D22 P22 A1 A2 K22 24VDC
SOL-01 TEST CLAMP

D23 P23 A1 A2 K23 24VDC
SOL-02 PASS GATE

D24 P24 A1 A2 K24 24VDC
SOL-03 FAIL GATE

D25 P25 A1 A2 K25 24VDC
SOL-04 RETEST GATE

D26 P26 A1 A2 K26 24VDC
LT-01 GREEN

D27 P27 A1 A2 K27 24VDC
LT-01 YELLOW

D28 P28 A1 A2 K28 24VDC
LT-01 RED

D29 P29 A1 A2 K29 24VDC
BZ-01 BUZZER

0V_CTRL FROM DWG 005

1.1

K26 -TB-OUT-IND GN -TB-0V-IND
01 01

K27 YE
02 02

K28 RD
03 03

K29
04 04

1.1

+24V_SAFE_ACT
FROM DWG 005 / SR-01 K1-A

K22 -TB-OUT-ACT -TB-0V-ACT
01 01

K23
02 02

K24
03 03

K25
04 04

K20 & K21 NO CONTACT:
SEE DWG 008, SHEET 2, MOTOR CONTROL INTERFACE

[CROSS REFERENCE]
K20 NO CONTACT: SEE DWG 008 / SHEET 2
K21 NO CONTACT: SEE DWG 008 / SHEET 2
MTR-01 MOTOR CIRCUIT: SEE DWG 008 / SHEET 2

NO.	DATE	REVISION
A	2026-08-29	INITIAL RELEASE

DWG TITLE
EDS Wafer Map Linked Package
Final Test and Multi-Bin Sorting Cell
PLC Digital Output Circuit

DRAWN BY: J. H. KO
DATE: 2026-08-29
DWG NO: 008
SHEET NO: 1 OF 1