CONTINUOUS RUN CONTROL POLICY		
Event	Repeat memory	Current product / next action
Single→continuous selection	Remains OFF without fresh START	Selection alone never starts a product
Continuous→single	OFF	Current product completes, then wait
Environment permit lost	OFF	Current product completes; restored permit needs new START
STOP / safety / alarm / RESET	OFF	Existing abort or recovery policy; no automatic restart
RUN / program restart	OFF; mode initialized single	Prepare, rearm, RESET and START again

CONTINUOUS REQUEST MEMORY

M02101 = fresh START AND M00064 AND M00066 AND valid D01220
M02103 = M00066 AND Auto0 AND Continuous1 AND environment permit AND state not0/900
M02100_next = (M02100_old OR M02101) AND M02103

OPERATING MODE DEFINITION		
Register	Value	Behavior
D00053	0 / Auto	Sequence allowed in single or continuous operation
D00053	1 / Manual	START inhibited; count reset: current/next10 + M00063 + alarm0 + fresh M00204
D01220	0 / Single	One fresh START accepts one product
D01220	1 / Continuous	Fresh initial START arms M02100; next product starts only when ready

NEXT CYCLE CONDITION

(M02101 OR M02100) AND state10 AND M00066 AND M00064 → next_state20

M00064 remains OFF while outfeed product/feedback is present. Do not require M00064 in the continuous-memory rung.

STOP immediately aborts an active cycle. Selecting Single lets the existing product finish. Individual actuator Jog is not implemented.

NO.	DATE	REVISION
R0	2026-10-22	FUNCTION RECORD

DWG TITLE

SEMICON SORTER PROJECT
Final Test and Multi-Bin Sorting Cell

OPERATING MODES AND RESTART POLICY

DRAWN BY	DATE
J. H. KO	2026-10-14

DWG NO
007

SHEET NO
1 OF 1