VIRTUAL ATE REGISTER MAP				
Offset0	Server addr1	LS device	Function	Writer
0	1	Virtual	ATE_LINK_TEST	시험자
1	2	D00022	ATE_REQUEST	PLC
2	3	D00024	ATE_REQUEST_ID	PLC
3	4	D00020	ATE_RESULT	검사기
4	5	D00025	ATE_RESPONSE_ID	검사기
5	6	D00021	ATE_DONE	검사기
6	7	D00102	TEST_RESULT_LATCH	PLC
7	8	D00100	SEQ_STATE	PLC
8	9	D00310	ALARM_CODE	PLC
9	10	D00026	PLC_RX_RESULT	PLC
10	11	D00027	PLC_RX_DONE	PLC
11	12	D00028	PLC_RX_RESPONSE_ID	PLC
12	13	D00029	PLC_ACCEPTED_ID	PLC
13	14	D00030	PLC_LIVE_COUNTER	PLC

WRITE AND VERIFY ORDER

LabVIEW FC16 offset3 count2: [RESULT, RESPONSE_ID] wait PLC echo D00026/D00028.
LabVIEW FC06 offset5: DONE=1 wait accepted D00029 + result latch; then append CSV.
Cleanup: DONE=0 and wait echo0 before payload clear; do not assume CIMON cache write equals PLC receipt.

SERVER ADDRESSING

LabVIEW client connects to CIMON Modbus TCP server1502, unit1; FC03 offset0 reads14 holding registers.
Offset0 corresponds to server address1 / 40001 notation. LS side is the XGT driver, not this Modbus server.

R0	2026-10-22	FUNCTION RECORD
NO.	DATE	REVISION

DWG. TITLE

SEMICON SORTER PROJECT
Final Test and Multi-Bin Sorting Cell

LS / VIRTUAL ATE REGISTER TRANSACTION

DRAWN BY	DATE
J. H. KO	2026-10-14

DWG. NO
008

SHEET NO
1 OF 1