HMI PAGE FUNCTION SUMMARY	
Saved page	Function
MAIN	State, ready/run/alarm, device commands, counts; START/STOP/RESET/ACK
ALARM	Current/acknowledged history; process and environment views
INSPECTION	Last accepted result and recent CSV inspection records
ENVIRONMENT	FX judgment, FX→LS bridge, recovery and permit
SENSOR	ESP raw/packed values; sensor→FX staging and ACK diagnostics
SAFETY	Current small mock-control popup; E-stop/door/rearm/model clear; cycle choice

OPERATOR COMMAND MAP		
Command function	PLC target	Operation
START /STOP /RESET	M00200 /M00201 /M00202	Momentary /existing
ACK /COUNT RESET	M00203 /M00204	Momentary
Safety rearm /clear	M02002 /M02003	Fresh pulse
E-stop /door	M02000 /M02001	Maintained input
Single /continuous	D01220	Write0/1; no START
PLC setup mode	D00053	XG5000 setup: Auto0 / Manual1

TAG AND DISPLAY POLICY

Read tag = PLC feedback/command read-back.
Write tag = configured writable address/item.
Virtual UI tag = command intention, not PLC confirmation.
Tag action: write_tag = virtual_tag, on both value changes.
XG-SIM M read2000/write3200 is user-confirmed for M02000 only; do not generalize other addresses.
Keep actual groups ESP / FXTEL / ENVIRONMENT as stored.

CURRENT SCOPE

No production trend/position/vibration/setpoint screens, individual Jog, login audit or TDMS are claimed by this revision.
String state/alarm display is computed from code tags. Popup uses saved position and native close X; closing does not clear PLC commands.
Actual tag groups, item addresses and scripts: see baseline BL-001.
PLC read tags confirm state; write tags carry operator commands.

NO.	DATE	REVISION
R0	2026-10-22	FUNCTION RECORD

DWG TITLE

SEMICON SORTER PROJECT
Final Test and Multi-Bin Sorting Cell

CIMON PAGES COMMANDS AND DISPLAY

DRAWN BY	DATE
J. H. KO	2026-10-14

DWG NO
016

SHEET NO
1 OF 1