Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
5	**GENERAL CONDITIONS FOR TESTING**		
	Testing is carried out according to clause 5, e.g. nature of supply, sequence of testing, etc.		
5.2	Addition : If the protective device becomes open-circuited during the test of 21.101, the test is continued on a separate apparatus. (SNI IEC 60335-2-3:2022)		
	Test 21.102 is performed on a separate apparatus. Additional test 25.14 is performed on a separate apparatus. (SNI IEC 60335-2-3:2022)		
5.3	Addition : For irons with thermostats, the 21.101 test is performed before the Article 11 test. (SNI IEC 60335-2-3:2022)		
	Test 22.102 was performed during the Article 11 test. (SNI IEC 60335-2-3:2022)		
5.101	The iron is tested as a heating appliance even though it is equipped with a motor. (SNI IEC 60335-2-3:2022)		
5.102	If the cordless iron can also be directly connected to the mains supply during ironing, the relevant tests apply to both operating modes. (SNI IEC 60335-2-3:2022)		
6	**CLASSIFICATION**		
6.1	Equipment must be class 0, class 0I, class I, class II, class III..... :		
	For class III construction with removable power supply parts, the appliance is classified according to the removable power supply parts		
602	Protection against dangerous water ingress		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
7	**MARKING AND INSTRUCTIONS**		
7.1	Rated voltage or voltage range (V) ..... :		
	Symbol for the nature of supply, or …… :		
	Rated frequency (Hz) …….. :		
	Modifications: Equipment must be marked with its rated power input. (SNI IEC 60335-2-3:2022) or ……. :		
	Rated current (A) …… :		
	Name, trademark, or identification mark of the manufacturer or vendor responsible for ..... :		
	Model or reference type …… :		
	IEC 60417-5172 symbol, for class II equipment		
	IP number, other than IPX0 ..... :		
	IEC 60417-5180 symbols, for class III equipment, except		
	equipment operated only by batteries, or		
	This equipment is powered by a rechargeable battery that is recharged inside the equipment.		
	User-accessible equipment outlets and user-accessible outlets:		
	- which is incorporated into equipment connected to a power source, and		
	- operating at rated voltage		
	marked with the socket load (W or A) ..... :		
	Equipment intended to be supplied from the removable part of the power supply for recharging batteries:		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
	- ISO 7000-0790 symbol		
	- IEC 60417-6181 symbols		
	- reference model or type of removable power supply components, or ..... :		
	the substance of the following:		
	Use only with <model or type reference> supply unit		
	IEC 60417-5018 symbol, for class II and class III appliances incorporating functional earthing		
	IEC 60417-5036 symbol, for electrically operated water valve closures on external hose sets for connecting equipment to the mains, if the working voltage exceeds extra-low voltage		
	Addition : Separate stands must be marked with:. (SNI IEC 60335-2-3:2022)		
	-name, trademark or identification mark of the manufacturer or responsible vendor; (SNI IEC 60335-2-3:2022)		
	-model reference or type of stand. (SNI IEC 60335-2-3:2022)		
	The cordless iron stand must be marked		
	- rated voltage or rated voltage range; (SNI IEC 60335-2-3:2022)		
	– rated power input. (SNI IEC 60335-2-3:2022)		
7.2	Warning for stationary equipment for dual supply		
	Warnings are placed around the terminal cover.		
7.3	A range of identifier values marked with lower and upper limits separated by a hyphen.		
	Different values are indicated by values		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
	separated by a slash.		
	These requirements also apply to equipment that has provisions for connection to single-phase and multi-phase supplies.		
7.4	Equipment that can be adjusted for different rated voltage or rated frequency, the voltage or frequency setting can be clearly seen		
	If frequent changes in voltage or frequency settings are not required, the rated voltage or rated frequency to which the appliance is to be adjusted can be determined from the wiring diagram.		
	A wiring diagram may be located inside the enclosure which must be removed to connect the supply conductors.		
	Wiring diagrams are not on labels loosely attached to the equipment		
7.5	Equipment with more than one rated voltage or one or more rated voltage ranges, is characterized by the rated input or rated current for each rated voltage or range, except		
	power or current input is related to the arithmetic mean value of the rated voltage range		
	The relationship between the markings for the upper and lower limits of rated power input or rated current and voltage is clear.		
7.6	Correct use of symbols		
	The symbol for the supply properties is placed next to the rated voltage.		
	The symbol for Class II equipment is placed so that it cannot be confused with other markings.		
	Units of physical quantities and their symbols according to the international standard system		
	Additional symbols do not cause misunderstandings		
	Symbols defined in IEC 60417 and ISO 7000 may		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
	be used		
7.7	Connection diagrams are installed on equipment to be connected to more than two supply conductors and equipment for dual supply, except		
	the correct connection mode is clear		
	For multi-phase equipment, the correct connection mode is considered clear if:		
	- indicated by an arrow pointing to the terminal, or		
	- marked with words		
	Connection diagram can be a wiring diagram		
7.8	Except for the Z-type connection, the terminals for connection to the power supply are shown as follows:		
	- special terminal marking for neutral conductor (letter N)		
	- marking of protective earthing terminals (symbol IEC 60417-5019)		
	- functional earth terminal marking (IEC 60417-5018 symbols)		
	- marking is not placed on removable parts		
7.9	Marking or placement of switches that may cause danger		
7.10	Switch indications on stationary equipment and controls on all equipment using pictures, letters or other visual means		
	This requirement also applies to switches that are part of the control		
	If using numbers, the off position (OFF) is indicated by the number 0.		
	The number 0 only indicates the OFF position, unless there is any confusion with the OFF position.		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
	The number 0 can be used on a digital programming keyboard.		
7.11	Indication for direction of control adjustment		
7.12	Safe use instructions are provided in printed form		
	Instructions may be marked on the equipment as long as they are visible during normal use.		
	Details regarding precautions during user maintenance		
	Instructions for the substance of the following:		
	- the equipment is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the equipment by a person responsible for their safety.		
	- children must be supervised to prevent them from playing with the equipment		
	For class III construction parts supplied from detachable power supply parts, the instructions state that the equipment is only to be used with the supplied unit.		
	The instructions for class III equipment state that such equipment may only be supplied at SELV, unless		
	This is a battery operated equipment, the battery is charged outside the equipment.		
	For equipment used at altitudes exceeding 2000 m, the maximum altitude is stated		
	The instructions for equipment using functional earthing state that the equipment uses an earth connection for functional purposes.		
	The instructions for equipment intended to be connected to a power supply for battery recharging state the warning to only use external power supplies with the specifications described.		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
	The instructions for equipment intended to be supplied from a removable power supply unit for battery recharging state a reference to the type of power supply unit together with a warning to use only the unit supplied with this equipment.		
	Instructions for equipment intended for use with batteries using metal ion chemistry state the normal temperature range for charging the batteries.		
	The meaning of the symbols for removable power supply components is explained, unless otherwise specified.		
7.12.1	Sufficient details for installation are provided		
	For equipment intended to be permanently connected to the water supply and not connected by a hose-set, this is stated		
	If a different rated voltage or a different rated frequency is marked, the instructions state what action must be taken to adapt the equipment.		
	Addition : The instructions must contain the following substance: (SNI IEC 60335-2-3:2022)		
	− the iron should not be left unattended while connected to the mains supply; (SNI IEC 60335-2-3:2022)		
	- the iron should not be stored until it has cooled down; (SNI IEC 60335-2-3:2022)		
	− The plug must be removed from the socket before the water reservoir is filled with water (for steam irons and irons equipped with a water sprayer); (SNI IEC 60335-2-3:2022)		
	− filling, decalcification, rinsing or inspection holes that are under pressure must not be opened during use (only for steam irons with a pressurized compartment); (SNI IEC 60335-2-3:2022)		
	− the iron may only be used with the stand		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
	provided (for cordless irons); (SNI IEC 60335-2-3:2022)		
	− the iron is not intended for normal use (for travel irons);(SNI IEC 60335-2-3:2022)		
	− the iron must be used and placed on a flat and stable surface; (SNI IEC 60335-2-3:2022)		
	− when placing the iron on its stand, make sure the surface on which the stand is placed is stable; (SNI IEC 60335-2-3:2022)		
	− The iron should not be used if it has been dropped, if there are visible signs of damage, or if it is leaking. (SNI IEC 60335-2-3:2022)		
7.12.2	Stationary equipment that is not equipped with means for disconnecting from the mains supply having contact separation in all poles providing complete disconnection under overvoltage category III, the instructions state that means for disconnecting must be included in the fixed wiring in accordance with the wiring rules		
7.12.3	Insulation of fixed cables in contact with parts exceeding 50 K during clause 11; the instruction states that fixed cables must be protected		
7.12.4	Instructions for built-in appliances:		
	- dimensions of space		
	- dimensions and position of supports and mountings		
	- minimum distance between parts and surrounding structures		
	- minimum dimensions of ventilation openings and their arrangement		
	- connections for supplying power and interconnecting separate components		
	- allows disconnection of the equipment after installation, with an accessible plug or switch on the fixed wiring, except		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
	switch corresponding to 24.3		
7.12.5	Cable replacement instructions, X-type connection with specially prepared cables		
	Cable replacement instructions, Y-type connection		
	Cable replacement instructions, Z-type connection		
7.12.6	Caution in the instructions for equipment using a non-self-resetting thermal cut-out which is reset by disconnecting the mains supply, if this disconnection is necessary to comply with the standards		
7.12.7	The instructions for fixed equipment state how the equipment is mounted on its support.		
7.12.8	Instructions for equipment connected to the water line:		
	- max. inlet water pressure (Pa) …….. :		
	- min. inlet water pressure, if necessary (Pa) …….. :		
	Instructions regarding new and existing hose sets for equipment connected to a water line with a detachable hose set		
7.12.9	The instructions specified in 7.12 and from 7.12.1 to 7.12.8 appear together before any other instructions supplied with the equipment		
	These instructions may be supplied with the equipment separately from the functional use booklet.		
	They can follow equipment descriptions that identify its parts, or follow pictures/sketches commonly used in instruction language.		
	Additionally, instructions are also available in alternative formats such as on a website or in formats such as DVD …….. :		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
7.13	Instructions and other texts in the official language		
7.14	Markings must be clearly legible and durable.		
	The signal words WARNING, CAUTION, DANGER in capital letters having the height as specified …… :		
	The capital letters of the text describing the word signal are not smaller than 1.6 mm …… :		
	A printed, engraved or stamped mark, whether raised above or having a depth below the surface of at least 0.25 mm, except		
	contrasting colors are used		
	Markings are checked by inspection, measurement and rubbing test as specified.		
	The markings are clear and durable, and on containers that are likely to be cleaned frequently, the markings do not use paint or enamel, etc.		
7.15	Markings on 7.1 to 7.5 must be on the main part		
	The markings can be clearly seen from the outside, if necessary after the cover is removed.		
	For portable equipment, the cover can be removed or opened without tools.		
	For stationary equipment, the name, trademark or identification mark and model or type reference can be seen after installation.		
	For fixed equipment, the name, trademark or identification mark and model or type reference can be seen after installation in accordance with the instructions.		
	Indications for switches and controls located on or near components. Markings are not on components that can be positioned or repositioned in such a way that the marking is misleading.		

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)

Klausul Clause	Persyaratan Requirements	Hasil Result	*Keterangan Remark
	The IEC 60417-5018 symbol is placed next to the IEC 60417-5172 or IEC 60417-5180 symbol		
	Reference to the type of removable power part placed on the symbol IEC 60417-6181		
	Place the outlet load close to the equipment outlet or wall outlet.		
7.16	Marking of replaceable thermal connections or fuse connections is clearly visible in connection with replacement of the connection.		

TABLE: Power Input Deviation

Input deviation from/on	P Identifier (W)	P Result (W)	ΔP (W ; %)	ConditionΔP (W ; %)	Decision	Additional information
1	2	3	4	5	6	7

TABLE: Heating Test

Input deviation from/on	P Identifier (W)	P Result (W)	ΔP (W ; %)	ConditionΔP (W ; %)	Decision	Additional information
8	9	10	11	12	13	14

* Keputusan hasil pengujian:
- Sampel uji memenuhi persyaratan : Lulus (L)
- Sampel uji tidak memenuhi persyaratan : Tidak Lulus (TL)
- Pengujian tidak berlaku untuk sampel uji : Tidak Berlaku (TB)