BATTERY (PCB-001, owner decisions 2026-10-04)
- One protected LiPo pouch cell, 1000 mAh or more, rated 0.5 C charge, charging 0 to 45 C, 2-wire JST-PH plug, + on pin 1 = RED WIRE.
  Charge current 494 mA (R14 1.8k; 3.6k for 500 mAh, up to 274 mA at tolerance). Approved test cell: see pcb/BATTERY.md.
- NO ON-BOARD REVERSE-POLARITY GUARD (rev 0.6, as on the Pico W). F1 polyfuse 1.5 A in the cell lead (rev 0.9) contains shorts and limits heat after a wiring mistake but does NOT save the two chips a reversed cell destroys. The keyed plug, the silkscreen, one approved cell listing and checking the wire colours BEFORE plugging in are the protection; a mis-wired cell can damage the DW01A and the charger's BAT pin (−0.3 V limits). UNPLUG USB BEFORE SWAPPING CELLS (the socket is live from the charger).
- The charger does not sense the cell's temperature with a two-wire cell (R12 10k fitted = check bypassed): the cell's protection board and the 0.5 C rate protect it. Safety timer about 6 h, longer while the charger throttles (DPPM, thermal).
- First power-ups: current-limited supply, no cell; then cell alone with the meter; then both. Charge on a non-flammable surface, never unattended. A tripped F1 resets only after the cell is unplugged.

Blocks left to right: core | USB, power | screen, input, audio, card, sensors | wireless.
Generated by pcb/tools/gen_sch.py from the connection table. Label-based: every pin carries its net

Pocket Chance

Sheet: /

File: pocket-chance-board.kicad_sch

Title: Pocket Chance board, spin 1

Size: A1	Date: 2026-10-04	**Rev: 0.10**
KiCad E.D.A. 10.0.6		Id: 1/1