Rev C - TOP SMT; headers customer soldered

D1 Top 0.0 deg | PESD3V3Z1BSFYL / C2908830
Board midpoint (16.000, 30.700) mm | TOP SMT
bidirectional nonpolar RF pad 1=pad 1 @ (15.800,30.700) net RF; bidirectional nonpolar GND pad 2=pad 2 @ (16.200,30.700) net GND

D2 Top 0.0 deg | 19-21/G6C-FM1N2B/4T / C2984263
Board midpoint (16.040, 4.300) mm | TOP SMT
cathode K=pad 1 @ (15.253,4.300) net GND; anode A=pad 2 @ (16.828,4.300) net PWR_A

D3 Top 0.0 deg | 19-21/G6C-FM1N2B/4T / C2984263
Board midpoint (16.040, 2.000) mm | TOP SMT
cathode K=pad 1 @ (15.253,2.000) net PPS_K; anode A=pad 2 @ (16.828,2.000) net PPS_A

J1 Top 0.0 deg | 20279-001E-03 / C3173448
Board midpoint (15.800, 33.700) mm | TOP SMT
connector/antenna mechanical centre @ (15.800,33.700); RF contact pad=pad 1 @ (15.800,32.175) net RF

J2 Bottom 180.0 deg | HX PH254-01-06-Z-L11.5 / C52016393
Board midpoint (3.610, 9.610) mm | CUSTOMER SOLDER ONLY
pin 1 / 3V3=pad 1 @ (3.610,15.960) net 3V3

J3 Bottom 180.0 deg | HX PH254-01-06-Z-L11.5 / C52016393
Board midpoint (21.390, 9.610) mm | CUSTOMER SOLDER ONLY
pin 1 / GND=pad 1 @ (21.390,15.960) net GND

Q1 Top 0.0 deg | BSS138 / C52895
Board midpoint (12.140, 9.500) mm | TOP SMT
gate G=pad 1 @ (11.203,10.450) net PPS_RAW; source S=pad 2 @ (11.203,8.550) net GND; drain D=pad 3 @ (13.078,9.500) net PPS_K

U1 Top 90.0 deg | MAX-M10S-00B / C4153167
Board midpoint (12.500, 21.900) mm | TOP SMT
pin 1=pad 1 @ (8.100,17.150) net GND

Top view; red = pad 1 (not polarity).
No backup storage components.
CPL uses actual component centre.
J2/J3: CUSTOMER solder, below PCB.

Check JLC preview against physical terminal polarity. Top alphanumeric markings are NOT assumed to encode polarity.