Description	Typical display	
Dry pump 1 inverter temperature	DP1 INV TMP	100 °C
Dry pump 2 inverter temperature	DP2 INV TMP	100 °C
Run hours	RUN HOURS	1000
Number of pump starts	PUMP STARTS	100
Time to stop (seconds)	TIME TO STOP	900
Active alarms and warnings		

Setup menu

Press the Setup button to enter. Menu title is shown at the top of the display. Scroll by pressing up/down keys. Press ENTER to open a sub menu or CANCEL to exit back to Normal menu.

Table 16 Setup menu

Description	Display
Commands menu*	Command Menu...
Display Inverter Fault History menu	Inv Fault Hist...
Software Version Display menu	S/W Version...
Display Serial Number	Serial Num...
Fit Accessory menu*	Fit Accessory...
Edit IP configuration menu	IP Config...
Edit Display attributes menu	Display Attr...
Set Time and Date†	Set Clock...
Display Pump Type	Show Pump type...

** This option requires a security code to access it.*

me is set automatically when connected to a Fabworks network.

h sub menu is described below.

Commands menu

Under the Setup menu. Scroll by pressing up/down keys. Press ENTER to open a sub menu or CANCEL to exit back to the SETUP menu.

Table 17 Commands menu

Gate Valve (Open/Shut)*
Green mode (On/Off)†
USB

** This option requires a security code to access it.*

me is set automatically when connected to a Fabworks network.

ss the up/down keys to select the new settings and press ENTER to accept or CANCEL
xit back to the COMMANDS menu.

Table 26 Warnings

Warning message on PDT	Action message on PDT
Warning 1.01 - Power interrupt on page 48	Check pwr supply
Warning 51.13 - Sup Missing on page 48	See manual
Warning 54.11 - DP2 high temperature on page 48	See manual
Warning 55.13 - Sensor missing on page 49	-
Warning 62.11 - DP1 high temperature on page 49	See manual
Warning 62.13 - Sensor missing on page 49	-
Warning 71.13 - AC Sup Missing on page 49	See manual
Warning 152.01 - Valve Not Shut on page 49	Check gate valve
Warning 153.01 - Valve Not Open on page 49	Check gate valve
Warning 176.01 - DP2 INV xxxx yyyy on page 49	xxxx yyyy aaaaaaaaaaaaaaaa
Warning 176.13 - No DP2 Inv Comms on page 49	See manual
Warning 186.01 - DP1 INV xxx yyy on page 50	xxxx yyyy aaaaaaaaaaaaaaaa
Warning 186.13 - No DP1 Inv Comms on page 50	See manual
Warning 314.11 - Speed too low on page 50	Stop pump/Contact service

Note:

1. Some of these warnings apply to pump sensors that are only present on certain system variants.

2. Some of these warnings apply to accessories and may only be encountered if the particular accessory is fitted.

Fault	Warning 1.01 - Power interrupt
Cause	**There has been a brownout of the electrical supply to the pump lasting more than 1 second.**
Remedy	Check the electrical supply.

Fault	Warning 51.13 - Sup Missing
Cause	**There is a communication problem in the pump controller. Refer to *Pump controller communications* on page 58 for more information.**
Remedy	Cycle the power to the pump. If the warning continues, contact us to replace the pump controller.

Fault	Warning 54.11 - DP2 high temperature
Cause	**The temperature of the DP2 is too high.**
Remedy	Check that cooling water is connected, set to on and is to specification given in *Cooling water data* on page 18.

9. Storage

WARNING: COOLANT CONDENSATION IN PIPELINE

Risk of damage to equipment. in the cooling water from the system if you will nsport or store it in conditions where the cooling water could freeze. ou do , the cooling water may freeze in the system and damage the pump(s) and/or the ling-water pipelines.

in the cooling water from the system if you will transport or store it in conditions ere the cooling water could freeze. ou do not, the cooling water may freeze in the tem and damage the pump(s) and/or the cooling-water pipelines.

Store the system as follows:

1. Follow the procedure set out in *Relocate the system for maintenance* on page 44.
2. Store the system in clean dry conditions until required.
3. When required for use, prepare and install the system as described in *Installation* on page 21.

10. Disposal

WARNING:

Dispose of the system and any components safely and in accordance with all local and national safety and environmental requirements.

This equipment may contain a lithium manganese dioxide battery which, under California law, requires notification for the presence of perchlorate: Perchlorate Material-special handling may apply, refer to *www.dtsc.ca.gov/hazardouswaste/perchlorate/*.

r products are supported by a world-wide network of our service centres. Each service centre offers a wide range of options including disposal. Refer to *Service* on page 61 for more information.

mp system materials suitable for recycling include cast iron, steel, SG iron, PTFE, nless steel, brass, aluminium, zinc alloy, nickel, mild steel, ABS, polyamide.

Take particular care with the following:

- Fluoroelastomers which may have decomposed as the result of being subjected to high temperatures.
- Components which have been contaminated with dangerous process substances.
- Lithium battery.

ADDITIONAL LEGISLATION AND COMPLIANCE INFORMATION (EU)

C (EU): Industrial equipment

tion: This equipment is not intended for use in residential environments and may not provide adequate protection to radio eption in such environments.

RoHS (EU): Material Exemption Information

This product is compliant with the following Exemptions (UKCA equivalent given in brackets).

Annex III:

- -I: **Lead** as an alloying element in steel for machining purposes containing up to 0.35 % lead by weight (Table 1-12)
- -II: **Lead** as an alloying element in steel for machining purposes and in galvanised steel containing up to 0.35 % lead by ght (UK: Table 1-12)
- : **Lead** as an alloying element in aluminium containing up to 0.4% by weight (Table 1-15)
- : Copper alloy containing up to 4% **lead** by weight (Table 1-18)
- : **Lead** in high melting temperature type solder (i.e. based alloys containing 85% by weight or more lead) (Table 1-19)
- I: Electrical and electronic components containing **lead** in a glass or ceramic other than dielectric ceramic in capacitors, e.g. oelectronic devices, or in a glass or ceramic matrix compound (Table 1-22)
- II: **Lead** in dielectric ceramic in capacitors for a rated voltage of 125 V AC or 250 V DC or higher (Table 1-22)
- : **Cadmium** and its compounds in electrical contacts (Table 1-24)
- **Lead** in solders to complete a viable electrical connection between semiconductor die and carrier within integrated circuit chip packages (Table 1-33)
- **Lead** in cermet-based trimmer potentiometer elements (Table 1-49)

CH (EU)

product is a complex article which is not designed for intentional substance release. To the best of our knowledge the materials used comply with the requirements of REACH. product manual provides information and instruction to ensure the safe storage, maintenance and disposal of the product including any substance based requirements.

cle 33.1 Declaration (EU)

product contains Candidate List Substances of Very High Concern above 0.1%ww by article as clarified under the 2015 opean Court of Justice ruling in case C-106/14.

- dimethoxyethane (EDGME)

  substance is sealed within the case of the compact lithium coin cell battery and is essential to the long life and reliable ormance of the battery.

- Cadmium (Cd)

  This substance is present in electronic contacts.

- Lead (Pb)

  This substance is present in certain steel/aluminium/brass/electrical or electronic components.

STE ELECTRICAL AND ELECTRONIC EQUIPMENT (EU)

product must be disposed of in accordance with the requirements of the WEEE Directive.