


# SWITCHING MODULES

## MC-L Series



The MC-4L is a 4 zone loudspeakers lines switching module, with channel "I" and channel "II" Inputs. In standby condition each zone is connected to the channel I. It is advisable to use this channel as a background music one. Connecting to ground the channel selectors Z1 to Z4, the Output is routed to the channel II. Each Output has three connections (+, S, -C), for the activation of the security paging function in those installations with attenuators. The module is also supplied with auxiliary contacts (NC, NO), for the control of accessory devices.

### MC-4L

<b>Power supply</b>	24 V.d.c.
<b>Maximum power for zone (100 V)</b>	500 W
<b>Number of zones</b>	4
<b>Channels</b>	2 (music / pagings)
<b>Selection</b>	By contact
<b>Security pagings</b>	Included, it combines with the AV series attenuators
<b>Max. Consumption</b>	220mA
<b>Dimensions (mm)</b>	150 (width) x 110 (height) x 75 (depth)
<b>Weight</b>	0.585 kg
<b>Format</b>	46277 & 50022 DIN rail

### BLOCK DIAGRAM

